


### Overview

### HPE ProLiant DL380 Gen10 Server

Adaptable for diverse workloads and environments, the secure 2P 2U HPE ProLiant DL380 Gen10 delivers world-class performance with the right balance of expandability and scalability. Designed for supreme versatility and resiliency while being backed by a comprehensive warranty make it ideal for multiple environments from Containers to Cloud to Big Data. Standardize on the industry's most trusted compute platform.



**Front View - SFF chassis with optional Universal Media bay with optical and 2 NVMe plus 16 NVMe shown**

- |   |   |
|---|---|
| 1. Quick removal access panel   | 10. UID button  |
| 2. Optional Universal Media bay. 2 USB 2.0 and Display port standard (8 SFF bay or 6 SFF+2NVMe or 8NVMe optional) | 11. iLO Front Service Port                                |
| 3. Optional Optical drive. Requires Universal Media bay   | 12. USB 3.0   |
| 4. Optional 2 SFF HDD, requires optional Universal Media bay  | 13. Serial label pull tag                                 |
| 5. Drive Bay 2. NVMe shown (8 SFF, 6SFF+2NVMe or 8 NVMe PCIe SSD optional)  | 14. Box 3   |
| 6. 8 SFF Drive Cage Bay   | 15. Box 2   |
| 7. Power On/Standby button and system power LED button  | 16. Box 1   |
| 8. Health LED   | 17. Optional front display port (Via Universal Media Bay) |
| 9. NIC status   | 18. Optional USB 2.0 (via Universal Media Bay)            |


### Overview



#### Front View - 8LFF chassis with Universal media bay and optional 2SFF and optical drive shown

- |  |   |
|--|---|
| 1. UID button  | 6. iLO Front Service Port                           |
| 2. Health LED  | 7. Serial label pull tag                            |
| 3. NIC status  | 8. Optional optical drive shown (blank as standard) |
| 4. Power On/Standby button and system power LED button | 9. Optional 2 SFF Drive bay, 2 NVMe shown           |
| 5. Front display port                                  |   |

### Overview




#### Internal View 8SFF chassis - with optional 2<sup>nd</sup> CPU, FlexLOM, Smart array shown

- |   |   |
|---|---|
| <ol style="list-style-type: none"> <li>1. Fan cage shown with 6 standard Hot-plug fans (High Performance temperature fans optional)</li> <li>2. 2 Processors, heatsink showing</li> <li>3. Optional HPE Smart Hybrid Capacitor or HPE Smart Storage Battery</li> <li>4. DDR4 DIMM slots. Shown fully populated in 24 slots (12 per processor)</li> <li>5. MicroSD card slot (Optional Dual Micro-SD option)</li> <li>6. Internal USB 3.0 connector</li> <li>7. Chassis intrusion detection connector</li> <li>8. Optional HPE Smart Array (P408i-a shown) Clear air baffle</li> </ol> | <ol style="list-style-type: none"> <li>9.. (Under) Hot Plug redundant HPE Flexible Slot Power supplies</li> <li>10. Connection for second (optional) riser (Requires second CPU)</li> <li>11. Embedded 4x1Gbe NIC (if equipped)<sup>1</sup></li> <li>12. Primary PCIe riser, standard (Optional double wide GPU riser)</li> <li>13. FlexibleLOM slot (Optional, depending on model selected)</li> <li>14. X4 SATA ports (1, 2 and 3)</li> <li>15. Clear air baffle</li> </ol> |
|---|---|

**Notes:** <sup>1</sup> Networking Choice (NC) models do not include an embedded NIC and have a FlexibleLOM pre-selected for Build-to-Order (BTO) models; Configure-to-Order (CTO) models require a primary networking choice of FlexibleLOM or select networking adapters NIC adapters. See "FlexibleLOM Adapters" and/or "HPE Networking" sections for available options.

### Overview



**Rear View - With optional FlexLOM, Rear drives and Serial port shown.**

- |  |   |
|--|---|
| <ol style="list-style-type: none"> <li>1. Primary Riser. PCI Slots (Slots 1-3 top to bottom, riser shipped standard, not shown), optional 2SFF rear drives</li> <li>2. Secondary Riser. PCI Slots (Slots 4-6 top to bottom, not shown, requires second riser card, and second processor). Showing optional 2 SFF rear</li> <li>3. Optional serial port</li> <li>4. Tertiary Riser (Slots 7-8). Optional rear 2 SFF HDD (supported in 24 SFF or 12 LFF front end)</li> <li>5. Power supply Power connection</li> <li>6. Power supply Power LED</li> <li>7. HPE Flexible Slot Power Supply bay 1 (800W shown)</li> <li>8. Power supply Power connection</li> </ol> | <ol style="list-style-type: none"> <li>9. Power supply Power LED</li> <li>10. HPE Flexible Slot Power Supply bay 2 (800W shown)</li> <li>11. VGA connector</li> <li>12. Embedded 4 x 1GbE Network Adapter (if equipped) <sup>1</sup></li> <li>13. Dedicated iLO management port</li> <li>14. USB connectors 3.0 (2)</li> <li>15. Unit ID LED</li> <li>16. FlexibleLOM ports (4 x 1GbE shown); optional, depending on model</li> </ol> |
|--|---|

**Notes:** <sup>1</sup> Networking Choice (NC) models do not include an embedded NIC and have a FlexibleLOM pre-selected for Build-to-Order (BTO) models; Configure-to-Order (CTO) models require a primary networking choice of FlexibleLOM or select networking adapters NIC adapters. See "FlexibleLOM Adapters" and/or "HPE Networking" sections for available options.

### What's New

- New Read-Intensive SFF Value SAS SSD (960GB/1.92TB/3.84TB/7.68TB)
- New Mixed-Use SFF Value SAS SSD (960GB/1.92TB/3.84TB)
- New Mixed-Use LFF Value SAS SSD (1.92TB)
- New HPE 32GB 1Rx4 DDR4-2933 Registered Memory Kit (P38466-B21)
- New HPE Trusted Supply Chain/HPE ProLiant DL380T Gen10 option (P36394-B21)



### Overview

## Platform Information

### Form Factor

- 2U rack

### Chassis Types

- 8 SFF with optional Universal Media Bay, and optional SFF or NVMe drive bay options
- 24 SFF bay with additional 6SFF rear drive bay option to total 30 SFF drives
- 8 LFF with Universal Media Bay
- 12 LFF with optional 4 LFF mid-plane and optional 3LFF + 2 SFF rear drive bay to total 19 LFF drives + 2 SFF drives

### Notes:

The 3 LFF rear drive box will consume space for the secondary and tertiary riser.

The 8 and 12 LFF chassis also supports the 2 SFF rear drive box which allows for the user to attach a secondary or tertiary riser.

The 8 NVMe drive option (826689-B21) can only be leveraged in the SFF chassis and replaces Box 1, 2 or 3, however there is a maximum of 20 NVMe drives supported with Partial population of Box 1.

The Premium cage (826690-B21, 6 SAS/SATA+2 NVMe) can only be leveraged in the SFF chassis and replaces Box 1, 2 or 3.

The Universal Media Bay (826708-B21) not available with the LFF chassis or the 24 SFF front end, and can only be populated in Box 1.

The 8 SFF can be upgraded with additional 8SFF drive box to total 16 or 24 SFF drives. For optimal upgrade Box 2 should be populated second, with Box 1 the last to be populated for a field upgrade to 24 SFF. For CTO builds requiring 24 SFF please use the 24 SFF chassis (868704-B21) or (P19719-B21). Note a field upgrade to 24 SFF will require a High Performance fan kit (867810-B21).

The 8 LFF chassis cannot be upgraded to 12 LFF front in the field; however the 4-LFF Mid plane (826686-B21) is supported, but will also require a performance fan kit (867810-B21).

The 8LFF chassis ships with 6-standard fans.

All models come with the S100i Smart Array Controller with embedded software RAID support for 12 drives. The S100i uses 14 embedded SATA ports, but only 12 ports are accessible as 2 are leveraged to support the 2 M.2 options on the primary riser.

### System Fans

- Standard - fan types included

### Notes:

– 1P models typically ship with 4 standard fans. The second processor option kit contains 2 additional fans. 1P Models have (4) (N+1 redundancy standard).

– 2P models typically ship with 6 standard fans. 2P Models have (6) (N+1 redundancy standard).

– The 12 LFF and 24 SFF chassis ship with 6 High performance fans as standard.

– The 8LFF chassis ships with 6 standard fans as standard.

– High performance fan kit is available to meet ambient temperature environments.

– High performance fan kits are required for rear drives, Graphics (GPU) card or NVMe configurations.

### Standard Features

**Processors** - Up to 2 of the following depending on model.

The 2nd digit of the processor model number "x1xx" and "x2xx" is used to denote the processor generation (i.e. 1=1st generation and 2=2nd generation)

**Notes:** Field upgrades from 1<sup>st</sup> generation processors (x1xx) to 2<sup>nd</sup> generation processors (x2xx) not supported.

"U" processors (i.e. 6212U) only supported in single socket configurations

For more information regarding Intel Xeon processors, please see the following <http://www.intel.com/xeon>.

This table covers the public Intel offering only.

Intel Xeon processors		
Processor Suffix	Description	Offering
<b>L</b>	Large memory tier	Up to 4.5 TB addressable memory per socket
<b>M</b>	Medium memory tier	Up to 2.0 TB addressable memory per socket (up to 1.5TB for 1st generation Intel Xeon Scalable Processors denoted with the "M" suffix)
<b>N</b>	NFV Optimized	Targeted at Network Function Virtualization (NFV) workloads. Intel® SST-BF improves performance by directing base frequency to high priority/bottleneck cores. Other workloads may see throttling, more details to be provided in upcoming documentation.
<b>S</b>	Search Optimized	Optimized base frequency to address 'search' workloads. Other workloads may see throttling, more details to be provided in upcoming documentation.
<b>U</b>	1 Socket Optimized	Focused on single socket (1P) configurations, delivering performance at competitive price points. Does not support two socket (2P) arrangements.
<b>V</b>	VM Optimized	Fosters enhanced VM density, allowing to support more/largervirtual machines per host.
<b>Y</b>	Speed Select	Intel® SST-PP increases base frequency when fewer cores are enabled. Allows greater flexibility, deployment options and platform longevity.

**Notes:** More than 1.5 TB memory per socket requires memory higher than 128 GB capacity

### Standard Features

2nd Generation Intel® Xeon® Scalable Processor Family							
Intel Xeon Models	CPU Frequency	Cores	L3 Cache (MB)	Power	UPI	DDR4	Memory per socket
Platinum 8280M Processor	2.7GHz	28	38.5	205W	3 @ 10.4 GT/s	2933 MT/s	2TB
Platinum 8280L Processor	2.7GHz	28	38.5	205W	3 @ 10.4 GT/s	2933 MT/s	4.5TB
Platinum 8280 Processor	2.7GHz	28	38.5	205W	3 @ 10.4 GT/s	2933 MT/s	1TB
Platinum 8276M Processor	2.2GHz	28	38.5	165W	3 @ 10.4 GT/s	2933 MT/s	2TB
Platinum 8276L Processor	2.2GHz	28	38.5	165W	3 @ 10.4 GT/s	2933 MT/s	4.5TB
Platinum 8276 Processor	2.2GHz	28	38.5	165W	3 @ 10.4 GT/s	2933 MT/s	1TB
Platinum 8270 Processor	2.7GHz	26	35.75	205W	3 @ 10.4 GT/s	2933 MT/s	1TB
Platinum 8268 Processor	2.9GHz	24	35.75	205W	3 @ 10.4 GT/s	2933 MT/s	1TB
Platinum 8260Y Processor	2.4/2.5 /2.7GHz	24/20/16	35.75	165W	3 @ 10.4 GT/s	2933 MT/s	1TB
Platinum 8260M Processor	2.4GHz	24	35.75	165W	3 @ 10.4 GT/s	2933 MT/s	2TB
Platinum 8260L Processor	2.4GHz	24	35.75	165W	3 @ 10.4 GT/s	2933 MT/s	4.5TB
Platinum 8260 Processor	2.4GHz	24	35.75	165W	3 @ 10.4 GT/s	2933 MT/s	1TB
Platinum 8256 Processor	3.8 GHz	4	16.5	105W	3 @ 10.4 GT/s	2933 MT/s	1TB
Platinum 8253 Processor	2.2GHz	16	22	125W	3 @ 10.4 GT/s	2933 MT/s	1TB

#### Notes:

Platinum - 8200 Series - Supports 6-Channel DDR4 @ 2933 MT/s providing up to 1TB memory capacity per socket (up to 2TB/socket on M series and up to 4.5TB/socket on L series); Intel Optane Persistent Memory for HPE (select skus), Vector Neural Network Instructions (VNNI) for inference acceleration, Intel Turbo Boost Technology, Intel Hyper-Threading Technology Intel AVX-512 (2x 512-bit FMA). 48 lanes PCIe 3.0, advanced RAS  
Processors with 130W TDP or higher and the 8256, 8156, 6128, 5222, and 5122 will ship with the High Performance heatsink. All other will processors will ship with the Standard heatsink.

### Standard Features

1st Generation Intel® Xeon® Scalable Processor Family							
Intel Xeon Models	CPU Frequency	Cores	L3 Cache (MB)	Power	UPI	DDR4	Memory per socket
Platinum 8180M Processor	2.5 GHz	28	38.5	205W	3 @ 10.4 GT/s	2666 MT/s	1.5TB
Platinum 8180 Processor	2.5 GHz	28	38.5	205W	3 @ 10.4 GT/s	2666 MT/s	768GB
Platinum 8176 Processor	2.1 GHz	28	38.5	165W	3 @ 10.4 GT/s	2666 MT/s	768GB
Platinum 8170 Processor	2.1 GHz	26	35.75	165W	3 @ 10.4 GT/s	2666 MT/s	768GB
Platinum 8168 Processor	2.7 GHz	24	33	205W	3 @ 10.4 GT/s	2666 MT/s	768GB
Platinum 8165 Processor	2.3 GHz	24	33	205W	3 @ 10.4 GT/s	2666 MT/s	768GB
Platinum 8164 Processor	2.0 GHz	26	35.75	150W	3 @ 10.4 GT/s	2666 MT/s	768GB
Platinum 8160 Processor	2.1 GHz	24	33	150W	3 @ 10.4 GT/s	2666 MT/s	768GB
Platinum 8158 Processor	3.0 GHz	12	24.75	150W	3 @ 10.4 GT/s	2666 MT/s	768GB
Platinum 8156 Processor	3.6 GHz	4	16.5	105W	3 @ 10.4 GT/s	2666 MT/s	768GB
Platinum 8153 Processor	2.0 GHz	16	22	125W	3 @ 10.4 GT/s	2666 MT/s	768GB

#### Notes:

Platinum - 8100 Series -2 Socket supports 2UPI, supports 6-Channel DDR4 @ 2666 MT/s providing up to 768GB memory capacity (1.5 TB on select processor skus). Intel Turbo Boost Technology, Intel Hyper-Threading Technology supported. Intel AVX-512 (2x 512-bit FMA), 48 lanes PCIe 3.0, advanced RAS.

Processors with 130W TDP or higher and the 8256, 8156, 6128, 5222, and 5122 will ship with the High Performance heatsink. All other will processors will ship with the Standard heatsink.

2nd Generation Intel® Xeon® Scalable Processor Family							
Intel Xeon Models	CPU Frequency	Cores	L3 Cache (MB)	Power (TDP)	UPI	DDR4	Memory per socket
Gold 6262V Processor	1.9GHz	24	33	135W	3 @ 10.4 GT/s	2933MT/s	1TB
Gold 6258R Processor	2.7GHz	28	38.5	205W	2 @ 10.4 GT/s	2933MT/s	1TB
Gold 6256 Processor <sup>4</sup>	3.6GHz	12	33	205W	3 @ 10.4 GT/s	2933MT/s	1TB
Gold 6254 Processor	3.1GHz	18	24.75	200W	3 @ 10.4 GT/s	2933MT/s	1TB
Gold 6252N Processor	2.3GHz	24	35.75	150W	3 @ 10.4 GT/s	2933MT/s	1TB
Gold 6252 Processor	2.1GHz	24	35.75	150W	3 @ 10.4 GT/s	2933MT/s	1TB



### Standard Features

Gold 6250L Processor	3.9GHz	8	35.75	185W	3 @ 10.4 GT/s	2933MT/s	4.5TB
Gold 6250 Processor <sup>4</sup>	3.9GHz	8	35.75	185W	3 @ 10.4 GT/s	2933MT/s	1TB
Gold 6248R Processor	3.0GHz	24	35.75	205W	2 @ 10.4 GT/s	2933MT/s	1TB
Gold 6248 Processor	2.5GHz	20	27.5	150W	3 @ 10.4 GT/s	2933MT/s	1TB
Gold 6246R Processor	3.4GHz	16	35.75	205W	2 @ 10.4 GT/s	2933MT/s	1TB
Gold 6246 Processor	3.3GHz	12	24.75	165W	3 @ 10.4 GT/s	2933MT/s	1TB
Gold 6244 Processor	3.6GHz	8	24.75	150W	3 @ 10.4 GT/s	2933MT/s	1TB
Gold 6242R Processor	3.1GHz	20	35.75	205W	2 @ 10.4 GT/s	2933MT/s	1TB
Gold 6242 Processor	2.8GHz	16	22	150W	3 @ 10.4 GT/s	2933MT/s	1TB
Gold 6240Y Processor	2.6/2.8/ 3.1 GHz	18/14/8	24.75	150W	3 @ 10.4 GT/s	2933MT/s	1TB
Gold 6240M Processor	2.6GHz	18	24.75	150W	3 @ 10.4 GT/s	2933MT/s	2TB
Gold 6240L Processor	2.6GHz	18	24.75	150W	3 @ 10.4 GT/s	2933MT/s	4.5TB
Gold 6240R Processor	2.4GHz	24	35.75	165W	2 @ 10.4 GT/s	2933MT/s	1TB
Gold 6240 Processor	2.6GHz	18	24.75	150W	3 @ 10.4 GT/s	2933MT/s	1TB
Gold 6238R Processor	2.2GHz	28	38.5	165W	2 @ 10.4 GT/s	2933MT/s	1TB
Gold 6238M Processor	2.1GHz	22	30.25	140W	3 @ 10.4 GT/s	2933MT/s	2TB
Gold 6238L Processor	2.1GHz	22	30.25	140W	3 @ 10.4 GT/s	2933MT/s	4.5TB
Gold 6238 Processor	2.1GHz	22	30.25	140W	3 @ 10.4 GT/s	2933MT/s	1TB
Gold 6234 Processor	3.3GHz	8	24.75	130W	3 @ 10.4 GT/s	2933MT/s	1TB
Gold 6230R Processor	2.1GHz	26	35.75	150W	2 @ 10.4 GT/s	2933MT/s	1TB
Gold 6230N Processor	2.3GHz	20	27.5	125W	3 @ 10.4 GT/s	2933MT/s	1TB
Gold 6230 Processor	2.1GHz	20	27.5	125W	3 @ 10.4 GT/s	2933MT/s	1TB
Gold 6226R Processor	2.9GHz	16	22	150W	2 @ 10.4 GT/s	2933MT/s	1TB
Gold 6226 Processor	2.7GHz	12	19.25	125W	3 @ 10.4 GT/s	2933MT/s	1TB
Gold 6222V Processor	1.8GHz	20	27.5	115W	3 @ 10.4 GT/s	2933MT/s	1TB

### Standard Features

Gold 6212U Processor	2.4GHz	24	35.75	165W	-	2933MT/s	1TB
Gold 6210U Processor	2.5GHz	20	27.5	150W	-	2933MT/s	1TB
Gold 6209U Processor	2.1GHz	20	27.5	125W	-	2933MT/s	1TB
Gold 6208U Processor	2.9GHz	16	22	150W	-	2933MT/s	1TB
Gold 5222 Processor <sup>1</sup>	3.8GHz	4	16.5	105W	2 @ 10.4 GT/s	2933MT/s	1TB
Gold 5220S Processor	2.7GHz	18	24.75	125W	2 @ 10.4 GT/s	2666MT/s	1TB
Gold 5220R Processor	2.2GHz	24	35.75	150W	2 @ 10.4 GT/s	2666MT/s	1TB
Gold 5220 Processor	2.2GHz	18	24.75	125W	2 @ 10.4 GT/s	2666MT/s	1TB
Gold 5218R Processor	2.1GHz	20	27.5	125W	2 @ 10.4 GT/s	2666MT/s	1TB
Gold 5218N Processor <sup>3</sup>	2.3GHz	16	22	110W	2 @ 10.4 GT/s	2666MT/s	1TB
Gold 5218B Processor <sup>2</sup>	2.3GHz	16	22	125W	2 @ 10.4 GT/s	2666MT/s	1TB
Gold 5218 Processor	2.3GHz	16	22	125W	2 @ 10.4 GT/s	2666MT/s	1TB
Gold 5217 Processor	3.0GHz	8	11	115W	2 @ 10.4 GT/s	2666MT/s	1TB
Gold 5215M Processor	2.5GHz	10	13.75	85W	2 @ 10.4 GT/s	2666MT/s	2TB
Gold 5215L Processor	2.5GHz	10	13.75	85W	2 @ 10.4 GT/s	2666MT/s	4.5TB
Gold 5215 Processor	2.5GHz	10	13.75	85W	2 @ 10.4 GT/s	2666MT/s	1TB

#### Notes:

<sup>1</sup> Gold Processor 5222 supports 2933 DDR4 and 2 512-bit FMA units

<sup>2</sup> Gold Processor 5218B has consistent features with the 5218 processor but is from a different die. Mixing both 5218B & 5218 in a system is not supported

<sup>3</sup> Gold Processor 5218N processor available April 2019, Intel® Speed Select Technology-Base Frequency enablement via System ROM upgrade targeting June 2019

Processors with 130W TDP or higher and the 8256, 8156, 6128, 5222, and 5122 will ship with the High Performance heatsink. All other processors will ship with the Standard heatsink.

<sup>4</sup> Configuration support and facilities-requirements matrix for Gold Processor 6256 and Gold Processor 6250 listed below:

### Standard Features

Intel Xeon Scalable Series 6250, 6250L, and 6256 Configuration and Facilities Requirements Matrix				
DL380 Gen10	6250 & 6250L		6256	
Max inlet temp.	Without DIMM blanks	With DIMM blanks kit <sup>1</sup>	Without DIMM blanks	With DIMM blanks kit <sup>1</sup>
8SFF	Up to 30°C / 86°F	Up to 35°C / 95°F <sup>1</sup>	Up to 30°C / 86°F	Up to 35°C / 95°F <sup>1</sup>
16SFF + front 2SFF	Up to 25°C / 77°F	Up to 30°C / 86°F <sup>1</sup>	Up to 30°C / 86°F	Up to 35°C / 95°F <sup>1</sup>
16SFF + 8NVMe	Not Supported	Not Supported	Not Supported	Not Supported
24SFF	Up to 25°C / 77°F	Up to 30°C / 86°F <sup>1</sup>	Up to 30°C / 86°F	Up to 35°C / 95°F <sup>1</sup>
24SFF + rear SFF	Not Supported	Not Supported	Not Supported	Not Supported
8LFF	Up to 25°C / 77°F	Up to 30°C / 86°F <sup>1</sup>	Up to 30°C / 86°F	Up to 35°C / 95°F <sup>1</sup>
12LFF	Up to 20°C / 68°F	Up to 25°C / 77°F <sup>1</sup>	Up to 20°C / 68°F	Up to 25°C / 77°F <sup>1</sup>
12LFF + rear 2SFF	Not Supported	Not Supported	Not Supported	Not Supported
High Perf. fans	Mandatory	Mandatory	Mandatory	Mandatory
NVMe SSDs	Not supported	Not supported	Not supported	Not supported
Rear 2SFF	Not supported	Not supported	Not supported	Not supported
GPUs	Not supported	Not supported	Not supported	Not supported
4LFF mid-tray	Not supported	Not supported	Not supported	Not supported

**Notes:** <sup>1</sup>Must install DDR4 DIMM blanks (P07818-B21) on all empty DIMM slots

1st Generation Intel® Xeon® Scalable Processor Family							
Intel Xeon Models	CPU Frequency	Cores	L3 Cache (MB)	Power	UPI	DDR4	Memory per socket
Gold 6154 Processor	3.0 GHz	18	24.75	200W	3 @ 10.4 GT/s	2666 MT/s	768GB
Gold 6152 Processor	2.1 GHz	22	30.25	140W	3 @ 10.4 GT/s	2666 MT/s	768GB
Gold 6150 Processor	2.7 GHz	18	24.75	165W	3 @ 10.4 GT/s	2666 MT/s	768GB
Gold 6148 Processor	2.4 GHz	20	27.5	150W	3 @ 10.4 GT/s	2666 MT/s	768GB
Gold 6146 Processor	3.2 GHz	12	24.75	165W	3 @ 10.4 GT/s	2666 MT/s	768GB
Gold 6144 Processor	3.5 GHz	8	24.75	150W	3 @ 10.4 GT/s	2666 MT/s	768GB
Gold 6143 Processor	2.8 GHz	16	22	205W	3 @ 10.4 GT/s	2666 MT/s	768GB
Gold 6142 Processor	2.6 GHz	16	22	150W	3 @ 10.4 GT/s	2666 MT/s	768GB
Gold 6140 Processor	2.3 GHz	18	24.75	140W	3 @ 10.4 GT/s	2666 MT/s	768GB
Gold 6138 Processor	2.0 GHz	20	27.5	125W	3 @ 10.4 GT/s	2666 MT/s	768GB
Gold 6137 Processor	3.9 GHz	8	24.75	205W	3 @ 10.4 GT/s	2666 MT/s	768GB
Gold 6136 Processor	3.0 GHz	12	24.75	150W	3 @ 10.4 GT/s	2666 MT/s	768GB
Gold 6134M Processor	3.2 GHz	8	24.75	130W	3 @ 10.4 GT/s	2666 MT/s	1.5TB

### Standard Features

Gold 6134 Processor	3.2 GHz	8	24.75	130W	3 @ 10.4 GT/s	2666 MT/s	768GB
Gold 6132 Processor	2.6 GHz	14	19.25	140W	3 @ 10.4 GT/s	2666 MT/s	768GB
Gold 6130 Processor	2.1 GHz	16	22	125W	3 @ 10.4 GT/s	2666 MT/s	768GB
Gold 6128 Processor	3.4 GHz	6	19.25	115W	3 @ 10.4 GT/s	2666 MT/s	768GB
Gold 6126 Processor	2.6 GHz	12	19.25	125W	3 @ 10.4 GT/s	2666 MT/s	768GB
Gold 5122 Processor	3.6 GHz	4	16.5	105W	2 @ 10.4 GT/s	2666 MT/s	768GB
Gold 5120 Processor	2.2 GHz	14	19.25	105W	2 @ 10.4 GT/s	2400 MT/s	768GB
Gold 5118 Processor	2.3 GHz	12	16.5	105W	2 @ 10.4 GT/s	2400 MT/s	768GB
Gold 5117 processor	2.0 GHz	14	19.25	105W	2 @ 10.4 GT/s	2400 MT/s	768GB
Gold 5115 Processor	2.4 GHz	10	13.75	85W	2 @ 10.4 GT/s	2400 MT/s	768GB

### Notes:

Gold - 6200 & 5200 Series - 6-Channel DDR4 @ 2933 MT/s (6200 & 5222 skus only) or 2666 MT/s (all Gold 5200 skus except 5222 @ 2933 MT/s); providing up to 1TB memory capacity per socket (up to 2TB/socket on M series and up to 4.5TB/socket on L series); Support for Intel Optane Persistent Memory for HPE (select skus), Vector Neural Network Instructions (VNNI) for inference acceleration.

Intel Turbo Boost Technology, Intel Hyper-Threading Technology Intel AVX-512 (2x 512-bit FMA for 6200 series and 5222; 1 x 512-bit FMA for 5200 series, except for 5222) 48 lanes PCIe 3.0, advanced RAS

Gold - 5100, 6100 Series - 2 Socket supports 2UPI, supports 6-Channel DDR4 @ 2400 MHz (SKU 5122=supports 2666) providing up to 768GB memory capacity (1.5 TB on select skus). Intel Turbo Boost Technology, Intel Hyper-Threading Technology, Intel AVX-512(1x 512-bit FMA) (SKU 5122 supports 2x 512 bit FMA), 48 lanes PCIe 3.0, advanced RAS supported.

Processors with 130W TDP or higher and the 8256, 8156, 6128, 5222, and 5122 will ship with the High Performance heatsink. All other will processors will ship with the Standard heatsink.

### 2nd Generation Intel® Xeon® Scalable Processor Family

Intel Xeon Models	CPU Frequency	Cores	L3 Cache (MB)	Power	UPI	DDR4	Memory per socket
Silver 4216 Processor	2.1GHz	16	22	100W	2 @ 9.6 GT/s	2400 MT/s	1TB
Silver 4215R Processor <sup>4</sup>	3.2GHz	8	11	130W	2 @ 9.6 GT/s	2400 MT/s	1TB
Silver 4215 Processor <sup>4</sup>	2.5GHz	8	11	85W	2 @ 9.6 GT/s	2400 MT/s	1TB
Silver 4214R Processor	2.4GHz	12	16.5	100W	2 @ 9.6 GT/s	2400 MT/s	1TB
Silver 4214Y Processor	2.2/2.3/2.4GHz	12/10/8	16.5	85W	2 @ 9.6 GT/s	2400 MT/s	1TB
Silver 4214 Processor	2.2GHz	12	16.5	85W	2 @ 9.6 GT/s	2400 MT/s	1TB
Silver 4210R Processor	2.4GHz	10-core	13.75	100W	2 @ 9.6 GT/s	2400 MT/s	1TB
Silver 4210 Processor	2.2GHz	10	13.75	85W	2 @ 9.6 GT/s	2400 MT/s	1TB
Silver 4208 Processor	2.1GHz	8	11	85W	2 @ 9.6 GT/s	2400 MT/s	1TB

Notes: <sup>4</sup> Silver Processors 4215R and 4215 support Intel Optane Persistent Memory for HPE

### Standard Features

1st Generation Intel® Xeon® Scalable Processor Family							
Intel Xeon Models	CPU Frequency	Cores	L3 Cache (MB)	Power	UPI	DDR4	Memory per socket
Silver 4116 Processor	2.1 GHz	12	16.50 MB	85W	2 @ 9.6 GT/s	2400 MT/s	768GB
Silver 4114 Processor	2.2 GHz	10	13.75 MB	85W	2 @ 9.6 GT/s	2400 MT/s	768GB
Silver 4112 Processor	2.6 GHz	4	8.25 MB	85W	2 @ 9.6 GT/s	2400 MT/s	768GB
Silver 4110 Processor	2.1 GHz	8	11.00 MB	85W	2 @ 9.6 GT/s	2400 MT/s	768GB
Silver 4108 Processor	1.8 GHz	8	11.00 MB	85W	2 @ 9.6 GT/s	2400 MT/s	768GB

#### Notes:

Silver - 4200 Series - 6-Channel DDR4 @ 2400 MT/s, providing up to 1TB memory capacity per socket; Support for: Intel® Vector Neural Network Instructions (VNNI) for inference acceleration; Intel Turbo Boost Technology, Intel Hyper-Threading Technology Intel AVX-512 (1x 512-bit FMA).48 lanes PCIe 3.0, standard RAS

Silver - 4100 Series - 2 Socket supports 2UPI @ 9.6 GT/s, 6-Channel DDR4 @ 2400 MHz providing up to 768 GB memory capacity. Intel Turbo Boost Technology, Intel Hyper-Threading Technology, Intel AVX-512(1x 512-bit FMA), 48 lanes PCIe 3.0, standard RAS supported.

2nd Generation Intel® Xeon® Scalable Processor Family							
Intel Xeon Models	CPU Frequency	Cores	L3 Cache (MB)	Power	UPI	DDR4	Memory per socket
Bronze 3206R Processor	1.9GHz	8	11	85W	2 @ 9.6 GT/s	2133MT/s	1TB
Bronze 3204 Processor	1.9GHz	6	8.25	85W	2 @ 9.6 GT/s	2133MT/s	1TB

**Notes:** Bronze - 3200 Series - 6-Channel DDR4 @ 2133 MT/s, providing up to 1TB memory capacity per socket; Support for: Intel® Vector Neural Network Instructions (VNNI) for inference acceleration; Intel AVX-512 (1x 512-bit FMA); 48 lanes PCIe 3.0, standard RAS

1st Generation Intel® Xeon® Scalable Processor Family							
Intel Xeon Models	CPU Frequency	Cores	L3 Cache (MB)	Power	UPI	DDR4	Memory per socket
Bronze 3106 Processor	1.7 GHz	8	11.00 MB	85W	2 @ 9.6 GT/s	2133 MT/s	768GB
Bronze 3104 Processor	1.7 GHz	6	8.25 MB	85W	2 @ 9.6 GT/s	2133 MT/s	768GB

**Notes:** Bronze - 3100 Series - 2 Socket supports 2UPI @ 9.6 GT/s, supports 6-Channel DDR4 @ 2133 MHz providing up to 768GB memory capacity. Intel AVX-512(1x 512-bit FMA), 48 lanes PCIe 3.0, standard RAS supported.

### Chipset

Intel C621 Chipset

For more information regarding Intel® chipsets, please see the following URL:

<http://www.intel.com/products/server/chipsets/>



### Standard Features

---

#### On System Management Chipset

HPE iLO 5 ASIC

Read and learn more in the [iLO QuickSpecs](#).

---

#### Memory

One of the following depending on model.

<b>Type</b>	HPE DDR4 SmartMemory, Registered (RDIMM), Load Reduced (LRDIMM)
<b>DIMM Slots Available</b>	24 12 DIMM slots per processor, 6 channels per processor, 2 DIMMs per channel
<b>Maximum capacity (LRDIMM)</b>	3.0 TB 24 x 128 GB LRDIMM @ 2933 MT/s
<b>Maximum capacity (RDIMM)</b>	1.54 TB 24 x 64 GB RDIMM @ 2933 MT/s
<b>Maximum capacity (Intel Optane Persistent Memory for HPE)</b>	6.0 TB 12 X 512 GB Memory Modules @ 2666 MT/s
<b>Maximum capacity (HPE NVDIMMs)</b>	192 GB 12 x 16 GB NVDIMM @ 2666 MT/s

#### Notes:

Intel Optane Persistent Memory for HPE only supported with select 2nd generation Intel Xeon Scalable Series Processors ONLY (82xx/62xx/52xx/4215R/4215) and can only be mixed with either RDIMMs or LRDIMMs.

HPE NVDIMMs are only supported on 1st generation Intel Xeon Scalable Series Processors and can only be mixed with RDIMMs.

Maximum memory per socket is dependent on processor selection. 2<sup>nd</sup> generation processors supporting 2 TB or 4.5 TB per CPU are indicated by the "M" and "L" in the processor model names (i.e. 8276M and 8276L). 1<sup>st</sup> generation processors supporting 1.5 TB per CPU are indicated by the "M" in the processor model names (ie 8160M)

Maximum memory per socket is dependent on processor selection. Processors supporting 1.5 TB per CPU is indicated by the "M" in the processor model names (i.e. 8160M).

Mixing of RDIMM and LRDIMM memory is not supported.

For General Server Memory and HPE NVDIMM Population Rules and Guidelines for Gen10 see details here:

<http://www.hpe.com/docs/memory-population-rules>

For details on the HPE Server Memory speed, visit: <https://www.hpe.com/docs/memory-speed-table>

To realize the performance memory capabilities listed in this document, HPE DDR4 SmartMemory is required.

For additional information, please see the [HPE DDR4 SmartMemory QuickSpecs](#).

---

#### Memory Protection

For details on the HPE Server Memory Options RAS feature, visit: <http://www.hpe.com/docs/memory-ras-feature>

---

### Standard Features

#### Expansion Slots

Primary Riser					
Slots #	Technology	Bus Width	Connector Width	Slot Form Factor	Notes
1	PCIe 3.0	X8	X8	Full-height, full-length slot	Proc 1
2	PCIe 3.0	X16	X16	Full-height, full-length slot	Proc 1
3	PCIe 3.0	X8	X8	Full-height, half-length slot	Proc 1

#### Notes:

Bus Width Indicates the number of physical electrical lanes running to the connector.

The specifications above correspond with the default primary riser which also supports dual m.2 cards. Additional Primary Riser options and specifications noted in the "Riser Information" table within this document.

Secondary Riser					
Slots #	Technology	Bus Width	Connector Width	Slot Form Factor	Notes
1	PCIe 3.0	X8	X8	Full-height, full-length slot	Proc 2
2	PCIe 3.0	X16	X16	Full-height, full-length slot	Proc 2
3	PCIe 3.0	X8	X8	Full-height, half-length slot	Proc 2

#### Notes:

Bus Width Indicates the number of physical electrical lanes running to the connector.

The Secondary Riser requires Processor 2 to be populated 870548-B21

The specifications above correspond with the x8/x16/x8 Secondary Riser Kit (870548-B21). Additional Secondary Riser options and specifications noted in the "Riser Information" table within this document.

Tertiary Riser					
Slots #	Technology	Bus Width	Connector Width	Slot Form Factor	Notes
1	PCIe 3.0	X8	X8	Full-height, full-length slot	Proc 2
2	PCIe 3.0	X8	X8	Full-height, full-length slot	Proc 2

#### Notes:

Bus Width Indicates the number of physical electrical lanes running to the connector.

### Standard Features

The Tertiary Riser requires Processor 2 to be populated

The specifications above correspond with the 2x8 Tertiary Riser Kit (875780-B21). Additional Tertiary Riser options and specifications noted in the "Riser Information" table within this document

### Graphics

#### Integrated Video Standard

- Video modes up to 1920 x 1200@60Hz (32 bpp)
- 16MB Video Memory

#### HPE iLO 5 on system management memory

- 32 MB Flash
- 4 Gbit DDR 3 with ECC protection

### Maximum Internal Storage

Drive	Capacity	Configuration
Hot Plug SFF SAS HDD	72.0 TB	24+6 x 2.4 TB* (with optional rear SFF drive cage)
Hot Plug SFF SATA HDD	60.0 TB	24+6 x 2 TB (with optional SFF drive cage)
Hot Plug LFF SAS HDD	311.68 TB	12+4+3 x 16 TB + 2 x 3.84 TB (with optional mid -tray and rear LFF drive cage, plus 2 SFF SSD rear)
Hot Plug LFF SATA HDD	311.68 TB	12+4+3 x 16 TB + 2 x 3.84 TB (with optional mid -tray and rear LFF drive cage, plus 2 SFF SSD rear)
Hot Plug SFF SAS SSD	459 TB	24+6 x 15.3 TB (with optional rear SFF drive cage)
Hot Plug SFF SATA SSD	230.4 TB	24+6 x 7.68 TB (with optional rear SFF drive cage)
Hot Plug LFF SATA SSD	44.16 TB	12+4+3 x 1.92 TB + 2 x 3.84 TB (with optional mid -tray and rear LFF drive cage, plus 2 SFF SSD rear)
Hot Plug LFF SAS SSD	44.16 TB	12+4+3 x 1.92 TB + 2 x 3.84 TB (with optional mid -tray and rear LFF drive cage, plus 2 SFF SSD rear)
Hot Plug SFF NVMe PCIe SSD	307.2 TB	20 x 15.36 TB NVMe

#### Notes:

2x m.2 drives are supported on the Primary Riser.

UFF drives are also supported.

### Internal Storage Devices

One of the following depending on model

- **Optical Drive**

Ships standard in Performance Models

### Standard Features

Optional: DVD-ROM, DVD-RW

- **Hard Drives**

None ship standard

---

### Power Supply

- HPE 500W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit

**Notes:** Available in 94% efficiency.

- HPE 800W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit

**Notes:**

Available in 94% and 96% efficiency.

Also available in -48VDC and 227VAC/380VDC power inputs.

- HPE 1600W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit

**Notes:**

Available in 94% efficiency.

Also available in -48VDC

HPE Flexible Slot (Flex Slot) Power Supplies share a common electrical and physical design that allows for hot plug, tool-less installation into HPE ProLiant Gen10 Performance Servers. Flex Slot power supplies are certified for high-efficiency operation and offer multiple power output options, allowing users to "right-size" a power supply for specific server configurations. This flexibility helps to reduce power waste, lower overall energy costs, and avoid "trapped" power capacity in the data center.

All pre-configured servers ship with a standard 6-foot IEC C-13/C-14 jumper cord (A0K02A). This jumper cord is also included with each standard AC power supply option kit. If a different power cord is required, please check the [ProLiant Power Cables](#) web page. To review the power requirements for your selected system, please use the [HPE Power Advisor Tool](#).

For information on power specifications and technical content visit [HPE Server power supplies](#).

---

### Storage Controllers

The Gen10 controller naming framework has been updated to simplify identification as depicted below. For a more detailed breakout of the available Gen10 Smart Array controllers visit the <https://www.hpe.com/psnow/doc/a00047736enw>

One of the following depending on model

#### Software RAID

- HPE Smart Array S100i SR Gen10 SW RAID

**Notes:**

---

### Standard Features

HPE Smart Array S100i SR Gen10 SW RAID will operate in UEFI mode only. For legacy support an additional controller will be needed, and for CTO orders please also select the Legacy mode settings part, 758959-B22. HPE Smart Array S100i SR Gen10 SW RAID is off by default and must be enabled. The S100i uses 14 embedded SATA ports, but only 12 ports are accessible as 2 are leveraged to support the 2 M.2 options on the primary riser. If more than 8 SATA devices are being supported on this controller, then a Qty=1 of the SAS 3POS Cable Kit (826709-B21) is required. The S100i supports Windows only. For Linux users, HPE offers a solution that uses in-distro open-source software to create a two-disk RAID 1 boot volume. For more information visit: <https://downloads.linux.hpe.com/SDR/project/lrrib/>

### Essential RAID Controller

- HPE Smart Array E208i-a SR Gen10 Controller
- HPE Smart Array E208i-p SR Gen10 Controller
- HPE Smart Array E208e-p SR Gen10 Controller

### Performance RAID Controller

- Broadcom MegaRAID MR416i-a Controller for HPE
- Broadcom MegaRAID MR416i-p Controller for HPE
- Broadcom MegaRAID MR216i-a Controller for HPE
- Broadcom MegaRAID MR216i-p Controller for HPE
- HPE Smart Array P408i-a SR Gen10 Controller
- HPE Smart Array P408i-p SR Gen10 Controller
- HPE Smart Array P408e-p SR Gen10 Controller
- HPE Smart Array P816i-a SR Gen10 Controller

#### Notes:

Performance RAID Controllers require the HPE Smart Hybrid Capacitor (P02377-B21) or the HPE Smart Storage Battery (P01366-B21) which are sold separately. For additional details, please see <https://www.hpe.com/psnow/doc/a00047736enw>

### Interfaces

<b>Serial</b>	Optional, rear
<b>Display Port</b>	1 (SFF 1 front, optional via Universal Media Bay, 826708-B21), 8 LFF chassis standard
<b>Network Ports</b>	4 x 1GbE embedded (if equipped/depending on model) One (1) FlexibleLOM slot available on all chassis types (supporting various NIC adapters)
<b>HPE iLO Remote Management Network Port</b>	1 Gb Dedicated
<b>Front iLO Service Port</b>	1 standard (Not available on 12 LFF chassis or when SID is ordered, note iLO dongle required, 880123-B21)
<b>Micro SD Slot</b>	1 Micro SD  <b>Notes:</b> The Micro SD slot is not a hot-pluggable device. Customers should not attempt to plug an SD card into the SD slot while the server is powered.
<b>USB 3.0</b>	Up to 5 total: 1 front, 2 rear, 2 internal (secure), 2 optional USB 2.0 front via Universal Media Bay, or standard on 8LFF chassis
<b>SID (Systems Insight Display)</b>	Optional <b>Notes:</b> Not shipping as standard. Available as a CTO option or as a field upgrade (826703-B21).



## Standard Features

## Operating Systems and Virtualization Software Support for ProLiant Servers 2<sup>nd</sup> Generation Intel® Xeon® Scalable Processor Family

- Windows Server 2022: Essentials, Standard, Datacenter
- Windows Server 2019: Essentials, Standard, Datacenter
- **Windows Server 2016**: Essentials, Standard, Datacenter
- **Windows Server 2012 R2**: Essentials, Standard, Datacenter
- Microsoft Hyper-V Server: 2012 R2, 2016 & 2019
- **VMware vSphere 6.0 U3**, 6.5 U2 through U.3 & 6.7 U1 through U3, 7.0

**Notes:** 6.5 U3, 6.7 U3 & 7.0 minimums for Xeon "R", Gold 6256, Gold 6250L & Gold 6250 processors.

- ClearOS: 7.6; ClearVM: 2.0
- **Red Hat Enterprise Linux (RHEL)** 7.6 w/ Kbase\*\*, 8.0
- **SUSE Linux Enterprise Server (SLES)** 12 SP3, 15 (includes Xen) \*\*

### Notes:

- SLES12 SP4 is the minimum for servers featuring Intel® Optane™ DC Persistent Memory.
- Ubuntu: 18.04 LTS (4.15.0)
- Oracle Linux: Oracle Linux 7.6 UEK Release 5 Update 2; Oracle VM 3.4.6 (UEK Release 4 Update 7)
- Citrix: Hypervisor: 8.0, 8.1, 8.2; XenServer 7.1, 7.4, 7.5, 7.6
- SD Card/USB media can still be used as a standalone boot option through all 7.x releases via published Customer Advisory [https://support.hpe.com/hpesc/public/docDisplay?docId=emr\\_na-a00118986en\\_us](https://support.hpe.com/hpesc/public/docDisplay?docId=emr_na-a00118986en_us) For any major release beyond VMware ESXi 7.x, VMware will require M.2 or another local persistent device as the standalone boot option.

## 1st Generation Intel® Xeon® Scalable Processor Family

- Windows Server 2019: Essentials, Standard & Datacenter
- **Windows Server 2016** : Essentials, Standard & Datacenter
- **Windows Server 2012 R2**: Essentials, Standard & Datacenter
- Microsoft Hyper-V Server: 2012 R2, 2016 & 2019
- VMware vSphere 6.0 U3, 6.5 through U.3 & 6.7 through U3, 7.0
- **ClearOS**: 7.6; ClearVM: 2.0
- **Red Hat Enterprise Linux (RHEL)** 6.9, 7.3 \*\*
- **SUSE Linux Enterprise Server (SLES)** 11 SP4, 12 SP2 & 15 (includes Xen) \*\*
- Ubuntu: 16.04.3 HWE (4.10), 18.04 LTS (4.15.0)
- Oracle Linux: Oracle Linux/UEK 6.9, 7.4; Oracle VM 3.4.4
- Citrix: Hypervisor: 8.0, 8.1, 8.2; XenServer 7.1, 7.4, 7.5, 7.6

### Notes:

- For more information on Hewlett Packard Enterprise Certified and Supported ProLiant Servers for OS and Virtualization Software and latest listing of software drivers available for your server <http://www.hpe.com/info/ossupport>
- \*\* 64-bit only; includes KVM
- SD Card/USB media can still be used as a standalone boot option through all 7.x releases via published Customer Advisory [https://support.hpe.com/hpesc/public/docDisplay?docId=emr\\_na-a00118986en\\_us](https://support.hpe.com/hpesc/public/docDisplay?docId=emr_na-a00118986en_us) For any major release beyond VMware ESXi 7.x, VMware will require M.2 or another local persistent device as the standalone boot option.

## HPE Server UEFI/Legacy ROM

Unified Extensible Firmware Interface (UEFI) is an industry standard that provides better manageability and more secured configuration than the legacy ROM while interacting with your server at boot time. HPE ProLiant Gen10 servers have a UEFI Class 2 implementation and support both UEFI Mode (default) and

### Standard Features

Legacy BIOS Mode.

**Notes:** The UEFI System Utilities tool is analogous to the HPE ROM-Based Setup Utility (RBSU) of legacy BIOS. For more information, please visit <http://www.hpe.com/servers/uefi>.

**UEFI enables numerous new capabilities specific to HPE ProLiant servers such as:**

- Secure Boot and Secure Start enable for enhanced security
- Embedded UEFI Shell
- Operating system specific functionality
- Mass Configuration Deployment Tool using iLO RESTful API that is Redfish API Conformant
- Support for > 2.2 TB (using GPT) boot drives
- PXE boot support for IPv6 networks
- USB 3.0 Stack
- Workload Profiles for simple performance optimization

### UEFI Boot Mode only:

- TPM 2.0 Support
- iSCSI Software Initiator Support.
- NVMe Boot Support
- HTTP/HTTPs Boot support as a PXE alternative.
- Platform Trust Technology (PTT) can be enabled.
- Boot support for option cards that only support a UEFI option ROM

### Notes:

For UEFI Boot Mode, boot environment and OS image installations should be configured properly to support UEFI.

UEFI FIO Setting (758959-B22) can be selected to configure the system in Legacy mode in the factory for your HPE ProLiant Gen10 Server.

---

### Industry Standard Compliance

- ACPI 6.1 Compliant
- PCIe 3.0 Compliant
- WOL Support
- Microsoft® Logo certifications
- PXE Support
- VGA/Display Port
  - Notes:** This support is on the optional Universal Media Bay.
- USB 3.0 Compliant (internal)
- USB 2.0 Compliant (external ports via SUV)
  - Notes:** This support is on the optional Universal Media Bay.
- Energy Star
- SMBIOS 3.1
- Redfish API
- IPMI 2.0

### Standard Features

- Secure Digital 4.0
- TPM 1.20 and 2.0 Support
- Advanced Encryption Standard (AES)
- Triple Data Encryption Standard (3DES)
- SNMP v3
- TLS 1.2
- DMTF Systems Management Architecture for Server Hardware Command Line Protocol (SMASH CLP)
- Active Directory v1.0
- ASHRAE A3/A4

**Notes:** For additional technical, thermal details regarding ambient temperature, humidity, and feature support, please visit <http://www.hpe.com/servers/ashrae>

- EU Lot9

**Notes:** European Union (EU) eco-design regulations for server and storage products, known as Lot 9, go into effect on March 1st, 2020. Among other requirements, for servers this directive establishes power thresholds for idle state, as well as efficiency and performance in active state which vary among configurations. HPE ProLiant Gen10 servers are compliant with Lot9 requirements.

Please visit: <https://www.hpe.com/us/en/about/environment/msds-specs-more.html> for more information regarding HPE Lot 9 conformance.

- UEFI (Unified Extensible Firmware Interface Forum) 2.6

**Notes:** UEFI is the default for the DL380 Gen10. Legacy mode can be selected in the field or as a CTO option (758959-B22); some configuration restrictions apply.

---

### Embedded Management

#### HPE Integrated Lights-Out (HPE iLO)

Monitor your servers for ongoing management, service alerting, reporting and remote management with HPE iLO.

Learn more at <http://www.hpe.com/info/ilo>.

#### UEFI

Configure and boot your servers securely with industry standard Unified Extensible Firmware Interface (UEFI).

Learn more at <http://www.hpe.com/servers/uefi>.

#### Intelligent Provisioning

Hassle free server and OS provisioning for 1 or more servers with Intelligent Provisioning.

Learn more at <http://www.hpe.com/servers/intelligentprovisioning..>

#### iLO RESTful API

iLO RESTful API is Redfish API conformance and offers simplified server management automation such as configuration and maintenance tasks based on modern industry standards. Learn more at

<http://www.hpe.com/info/restfulapi>

---

### Server Utilities

#### Active Health System

The HPE Active Health System (AHS) is an essential component of the iLO management portfolio that provides continuous, proactive health monitoring of HPE servers. Learn more at

### Standard Features

<http://www.hpe.com/servers/ahs>.

#### Active Health System Viewer

Use the Active Health System Viewer, a web-based portal, to easily read AHS logs and speed problem resolution with HPE self-repair recommendations, to learn more visit: <http://www.hpe.com/servers/ahsv>.

#### Smart Update

Keep your servers up to date with the HPE Smart Update solution by using Smart Update Manager (SUM) to optimize the firmware and driver updates of the Service Pack for ProLiant (SPP).

#### iLO Amplifier Pack

Designed for large enterprise and service provider environments with hundreds of HPE servers, the iLO Amplifier Pack is a free, downloadable open virtual application (OVA) that delivers the power to discover, inventory and update Gen8, Gen9 and Gen10 HPE servers at unmatched speed and scale. Use with an iLO Advanced License to unlock full capabilities.

Learn more at <http://www.hpe.com/servers/iLOAmplifierpack>.

#### HPE iLO Mobile Application

Enables the ability to access, deploy, and manage your server anytime from anywhere from select smartphones and mobile devices. For additional information please visit: <http://www.hpe.com/info/ilo/mobileapp>.

#### RESTful Interface Tool

RESTful Interface tool (iLOREST) is a single scripting tool to provision using iLO RESTful API to discover and deploy servers at scale. Learn more at <http://www.hpe.com/info/resttool>.

#### Scripting Tools

Provision one to many servers using your own scripts to discover and deploy with Scripting Tool (STK) for Windows and Linux or Scripting Tools for Windows PowerShell. Learn more at <http://www.hpe.com/servers/powershell>.

#### HPE OneView Standard

HPE OneView Standard can be used for inventory, health monitoring, alerting, and reporting without additional fees. It can monitor multiple HPE server generations. The user interface is similar to the HPE OneView Advanced version, but the software-defined functionality is not available. Learn more at <http://www.hpe.com/info/oneview>.

#### HPE Systems Insight Manager (HPE SIM)

Ideal for environments already using HPE SIM, it allows you to monitor the health of your HPE ProLiant Servers and HPE Integrity Servers. Also provides you with basic support for non-HPE servers. HPE SIM also integrates with Smart Update Manager to provide quick and seamless firmware updates. Learn more at <http://www.hpe.com/info/hpesim>.

---

### Security

- UEFI Secure Boot and Secure Start support
- Tamper-free updates - components digitally signed and verified
- Immutable Silicon Root of Trust

### Standard Features

- Ability to rollback firmware
  - FIPS 140-2 validation
  - Secure erase of NAND/User data
  - Common Criteria certification
  - TPM (Trusted Platform Module) 1.2 option
  - Configurable for PCI DSS compliance
  - TPM (Trusted Platform Module) 2.0 option
  - Advanced Encryption Standard (AES) and Triple Data Encryption Standard (3DES) on browser
  - Bezel Locking Kit option
  - Support for Commercial National Security Algorithms (CNSA)
  - Chassis Intrusion detection option
  - Secure Recovery - recover critical firmware to known good state on detection of compromised firmware
- 

### Warranty

This product is covered by a global limited warranty and supported by HPE Services and a worldwide network of Hewlett Packard Enterprise Authorized Channel Partners resellers. Hardware diagnostic support and repair is available for three years from date of purchase. Support for software and initial setup is available for 90 days from date of purchase. Enhancements to warranty services are available through HPE Pointnext operational services or customized service agreements. Hard drives have either a one year or three year warranty; refer to the specific hard drive QuickSpecs for details.

**Notes:** Server Warranty includes 3-Year Parts, 3-Year Labor, 3-Year Onsite support with next business day response. Warranty repairs may be accomplished through the use of Customer Self Repair (CSR) parts. These parts fall into two categories: 1) Mandatory CSR parts are designed for easy replacement. A travel and labor charge will result when customers decline to replace a Mandatory CSR part; 2) Optional CSR parts are also designed for easy replacement but may involve added complexity. Customers may choose to have Hewlett Packard Enterprise replace Optional CSR parts at no charge. Additional information regarding worldwide limited warranty and technical support is available at:

<http://h17007.www1.hpe.com/us/en/enterprise/servers/warranty/>.

---



### Optional Features

#### Server Management

##### HPE iLO Advanced

HPE iLO Advanced licenses offer smart remote functionality without compromise, for all HPE ProLiant servers. The license includes the full integrated remote console, virtual keyboard, video, and mouse (KVM), multi-user collaboration, console record and replay, and GUI-based and scripted virtual media and virtual folders. You can also activate the enhanced security and power management functionality.

##### HPE OneView Advanced

HPE OneView brings a new level of automation to infrastructure management by taking a template driven approach to provisioning, updating, and integrating compute, storage, and networking infrastructure. It provides full-featured licenses which can be purchased for managing Gen8, Gen9 and Gen10 servers.

To learn more visit <http://www.hpe.com/info/oneview>.

##### HPE InfoSight for Servers

HPE InfoSight for Servers combines the cloud-based machine learning of InfoSight with the health and performance monitoring of Active Health System (AHS) and iLO to optimize performance and predict and prevent problems. The end result is an intelligent environment that modernizes IT operations and enhances the support experience by predicting and preventing the infrastructure issues that lead to application disruptions, wasted IT staff time and missed business opportunities.

Learn more at <https://www.hpe.com/servers/infosight>

##### HPE Insight Cluster Management Utility (CMU)

HPE Insight Cluster Management Utility is a HyperScale management framework that includes software for the centralized provisioning, management and monitoring of nodes and infrastructure. Learn more at <http://www.hpe.com/info/cmu>.

---

#### Accelerator and GPGPU Information

Hewlett Packard Enterprise supports various accelerators on select HPE ProLiant servers to support different workloads. The accelerators enable seamless integration of GPU computing with HPE ProLiant servers for high-performance computing, large data center graphics, deep learning and virtual desktop deployments. These accelerators deliver all of the standard benefits of GPU computing while enabling maximum reliability and tight integration with system monitoring and management tools such as HPE Insight Cluster Management Utility.

---

#### One Config Simple (SCE)

SCE is a guided self-service tool to help sales and non-technical people provide customers with initial configurations in 3 to 5 minutes. You may then send the configuration on for configuration help, or use in your existing ordering processes. If you require "custom" rack configuration or configuration for products not available in SCE, please contact Hewlett Packard Enterprise Customer Business Center or an Authorized Partner for assistance. <https://h22174.www2.hpe.com/SimplifiedConfig/Welcome#>

---

#### Rack and Power Infrastructure

---

### Optional Features

The story may end with servers, but it starts with the foundation that makes compute go - and business grow. We've reinvented our entire portfolio of rack and power products to make IT infrastructure more secure, more practical, and more efficient. In other words, we've created a stronger, smarter, and simpler infrastructure to help you get the most out of your IT equipment. As an industry leader, Hewlett Packard Enterprise is uniquely positioned to address the key concerns of power, cooling, cable management and system access.

HPE G2 Advanced and Enterprise Racks are perfect for the server room or today's modern data center with enhanced airflow and thermal management, flexible cable management, and a 10 year Warranty to support higher density computing.

HPE G2 PDUs offer reliable power in flexible form factors that operate at temperatures up to 60°C, include color-coded outlets and load segments and a low-profile design for optimal access to the rack and support for dense rack environments.

HPE Uninterruptible Power Systems are cost-effective power protection for any type workload. Some UPSs include options for remote management and extended runtime modules so your critical dense data center is covered in power outages.

HPE KVM Solutions include a console and switches designed to work with your server and IT equipment reliably. We've got a cost-effective KVM switch for your first rack and multiple connection IP switches with remote management and security capabilities to keep your data center rack up and running.

Learn more about HPE Racks, KVM, PDUs and UPSs at [\*\*HPE Rack and Power Infrastructure\*\*](#).

---

### Service and Support

#### HPE Pointnext - Service and Support

**Get the most from your HPE Products.** Get the expertise you need at every step of your IT journey with **HPE Pointnext Services**. We help you lower your risks and overall costs using automation and methodologies that have been tested and refined by HPE experts through thousands of deployments globally. HPE Pointnext **Advisory Services**, focus on your business outcomes and goals, partnering with you to design your transformation and build a roadmap tuned to your unique challenges. Our **Professional** and **Operational Services** can be leveraged to speed up time-to-production, boost performance and accelerate your business. HPE Pointnext specializes in flawless and on-time implementation, on-budget execution, and creative configurations that get the most out of software and hardware alike.

#### Consume IT on your terms

**HPE GreenLake** brings the cloud experience directly to your apps and data wherever they are—the edge, colocations, or your data center. It delivers cloud services for on-premises IT infrastructure specifically tailored to your most demanding workloads. With a pay-per-use, scalable, point-and-click self-service experience that is managed for you, HPE GreenLake accelerates digital transformation in a distributed, edge-to-cloud world.

- Get faster time to market
- Save on TCO, align costs to business
- Scale quickly, meet unpredictable demand
- Simplify IT operations across your data centers and clouds

#### Managed services to run your IT operations

**HPE GreenLake Management Services** provides services that monitor, operate, and optimize your infrastructure and applications, delivered consistently and globally to give you unified control and let you focus on innovation.

---

#### Recommended Services

HPE Pointnext Tech Care.

HPE Pointnext Tech Care is the new operational service experience for HPE products. Tech Care goes beyond traditional support by providing access to product specific experts, an AI driven digital experience, and general technical guidance to not only reduce risk but constantly search for ways to do things better. HPE Pointnext Tech Care has been reimagined from the ground up to support a customer-centric, AI driven, and digitally enabled customer experience to move your business forward. HPE Pointnext Tech Care is available in three response levels. Basic, which provides 9x5 business hour availability and a 2 hour response time. Essential which provides a 15 minute response time 24x7 for most enterprise level customers, and Critical which includes a 6 hour repair commitment where available and outage management response for severity 1 incidents.

<https://www.hpe.com/services/techcare>

#### HPE Pointnext Complete Care

HPE Pointnext Complete Care is a modular, edge-to-cloud IT environment service that provides a holistic approach to optimizing your entire IT environment and achieving agreed upon IT outcomes and business goals through a personalized and customer-centric experience. All delivered by an assigned team of HPE Pointnext Services experts. HPE Pointnext Complete Care provides:

- A complete coverage approach -- edge to cloud
- An assigned HPE team
- Modular and fully personalized engagement
- Enhanced Incident Management experience with priority access
- Digitally enabled and AI driven customer experience

<https://www.hpe.com/services/completecure>

### Service and Support

#### Other related Services

##### **HPE Server Hardware Installation**

Provides for the basic hardware installation of HPE branded servers, storage devices and networking options to assist you in bringing your new hardware into operation in a timely and professional manner.

<https://h20195.www2.hpe.com/v2/Getdocument.aspx?docname=5981-9356enw>

##### **HPE Installation and Startup Service**

Provides for the installation of your HPE hardware according to product specifications including options. The HPE service delivery technician will connect the product to a LAN as appropriate and enable remote support to allow for automatic case creation for hardware failures. Installation and start up services also includes the installation of one supported operating system type (Windows® or Linux).

##### **DC for Hyperscale**

Complete Care for Hyperscale is available for Service Providers and HPC customers who use a scale out approach to computing with a high volume homogenous infrastructure and resilient architecture can take advantage of this environment support tailored to their operating model.

##### **HPE Factory Express for Servers and storage**

HPE Factory Express offers configuration, customization, integration and deployment services for HPE servers and storage products. Customers can choose how their factory solutions are built, tested, integrated, shipped and deployed.

Factory Express offers service packages for simple configuration, racking, installation, complex configuration and design services as well as individual factory services, such as image loading, asset tagging, and custom packaging. HPE products supported through Factory Express include a wide array of servers and storage: HPE Integrity, HPE ProLiant, HPE Apollo, HPE ProLiant Server Blades, HPE BladeSystem, HPE 9000 servers as well as the MSAXxxx3PAR suite, XP, rackable tape libraries and configurable network switches.

##### **HPE Service Credits**

HPE Service Credits offers flexible services and technical skills to meet your changing IT demands. With a menu of service that is tailored to suit your needs, you get additional resources and specialist skills to help you maintain peak performance of your IT. Offered as annual credits, you can plan your budgets while proactively responding to your dynamic business.

##### **HPE Education Services**

Keep your IT staff trained making sure they have the right skills to deliver on your business outcomes. Book on a class today and learn how to get the most from your technology investment.

<http://www.hpe.com/ww/learn>

---

### Service and Support

#### HPE Support Center

The HPE Support Center is a personalized online support portal with access to information, tools and experts to support HPE business products. Submit support cases online, chat with HPE experts, access support resources or collaborate with peers.

Learn more <http://www.hpe.com/support/hpesc>.

The HPE Support Center Mobile App\* allows you to resolve issues yourself or quickly connect to an agent for live support. Now, you can get access to personalized IT support anywhere, anytime.

HPE Insight Remote Support and HPE Support Center are available at no additional cost with a HPE warranty, HPE Support Service or HPE contractual support agreement.

**Notes:** \*HPE Support Center Mobile App is subject to local availability.

For more information: <http://www.hpe.com/services>.

**Notes:** HPE ProLiant DL385 Gen10 Plus Server is covered under the HPE Service Contract applied to the HPE ProLiant Server. No separate HPE support services need to be purchased.

Warranty and Support Services will extend to include HPE options configured with your server or storage device. The price of support service is not impacted by configuration details. HPE sourced options that are compatible with your product will be covered under your server support at the same level of coverage allowing you to upgrade freely. Installation for HPE options is available as needed. To keep support costs low for everyone, some high value options will require additional support. Additional support is only required on select high value workload accelerators, fibre switches, InfiniBand and UPS batteries over 12KVA. See the specific high value options that require additional support [here](#).

---

#### Parts and Materials

Hewlett Packard Enterprise will provide HPE-supported replacement parts and materials necessary to maintain the covered hardware product in operating condition, including parts and materials for available and recommended engineering improvements.

Parts and components that have reached their maximum supported lifetime and/or the maximum usage limitations as set forth in the manufacturer's operating manual, product QuickSpecs, or the technical product data sheet will not be provided, repaired, or replaced as part of these services.

The defective media retention service feature option applies only to Disk or eligible SSD/Flash Drives replaced by Hewlett Packard Enterprise due to malfunction.

---

### Pre-configured Models

#### Powered by 2nd Generation Intel Processors

Worldwide & Japan BTO Models			
<b>SKU Number</b>	P56959-B21 P56959-291	P56960-B21 P56960-291	P56961-B21 P56961-291
<b>Model Name</b>	HPE ProLiant DL380 Gen10 4208 2.10GHz 8-core 1P 32GB-R MR416i-p 8SFF BC 800W PS Server	HPE ProLiant DL380 Gen10 4215R 3.2GHz 8-core 1P 32GB-R MR416i-p 8SFF BC 800W PS Server	HPE ProLiant DL380 Gen10 4210R 2.4GHz 10-core 1P 32GB-R MR416i-p 8SFF BC 800W PS Server
<b>Chassis</b>	8SFF Chassis (868703-B21)	8SFF NC Chassis (P19720-B21)	8SFF Chassis (868703-B21)
<b>Processor</b>	4208 (8 core, 2.1GHz, 85W)	4215R (8 core, 3.2GHz, 130W)	4210R (10 core, 2.4GHz, 100W)
<b>Number of Processors</b>	One with standard heatsink	One with standard heatsink	One with standard heatsink
<b>Memory</b>	32 GB RDIMM 2R 2933 MT/s (1x 32 GB)	32 GB RDIMM 2R 2933MT/s (1x 32 GB)	32 GB RDIMM 2R 2933 MT/s (1x 32GB)
<b>Network Controller</b>	Embedded 4 x 1GbE Ethernet Adapter	HPE Ethernet 10Gb 2-port FLR-T BCM57414 Adapter (817721-B21) plus optional stand-up card <b>Notes: No embedded networking</b>	Embedded 4 x 1GbE Ethernet Adapter
<b>Storage Controller</b>	Broadcom MegaRAID MR416i-p 4GB and Smart Storage Battery (SAS/SATA only)	Broadcom MegaRAID MR416i-p 4GB and Smart Storage Battery (SAS/SATA only)	Broadcom MegaRAID MR416i-p 4GB and Smart Storage Battery (SAS/SATA only)
<b>Hard Drive</b>	None Included	None Included	None Included
<b>Internal Storage</b>	8 SFF Chassis (upgradeable to 24 SFF front + 2SFF rear)	8 SFF Chassis (upgradeable to 24 SFF front + 2SFF rear)	8 SFF Chassis (upgradeable to 24 SFF front + 2SFF rear)
<b>PCIe Slots</b>	3-slots (x8, x16, x8 with dual m.2) as standard; upgradeable to 8-slots in a 2 processor configuration		
<b>Power Supply</b>	1x HPE 800W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit	1x HPE 800W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit	1x HPE 800W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit
<b>Fans</b>	4 - Standard	4 - Standard	4 - Standard
<b>Management</b>	HPE iLO Standard with Intelligent Provisioning (embedded), HPE OneView Standard (requires download); HPE iLO Advanced, HPE iLO Advanced Premium Security Edition and HPE OneView Advanced (require licenses)		
<b>Rail Kit</b>	SFF Easy Install Rail Kit; cable management arm	SFF Easy Install Rail Kit; cable management arm	SFF Easy Install Rail Kit; cable management arm
<b>Energy Star</b>	Energy Star 3.0		
<b>Form Factor</b>	2U Rack		
<b>Warranty</b>	3-year parts, 3-year labor, 3-year onsite support with next business day response.		



### Pre-configured Models

Worldwide, Japan & China BTO Models			
<b>SKU Number</b>	P56962-B21 P56962-291	P56967-AA1	P56968-AA1
<b>Model Name</b>	HPE ProLiant DL380 Gen10 5218 2.3GHz 16-core 1P 32GB-R MR416i-p 8SFF BC 800W PS Server	HPE ProLiant DL380 Gen10 3206R 1.9GHz 8-core 1P 16GB-R MR416i-p 8SFF BC 500W PS Server	HPE ProLiant DL380 Gen10 4210R 2.4GHz 10-core 1P 16GB-R MR416i-p NC 8SFF BC 800W PS Server
<b>Chassis</b>	8SFF NC Chassis (P19720-B21)	8SFF NC Chassis (P19720-B21)	8SFF NC Chassis (P19720-B21)
<b>Processor</b>	5218 (16 core, 2.3GHz, 125W)	3206R (8 core, 1.9GHz, 85W)	4210 (10 core, 2.4GHz, 100W)
<b>Number of Processors</b>	One with standard heatsink	One with standard heatsink	One with standard heatsink
<b>Memory</b>	32 GB RDIMM 2R 2933 MT/s (1x 32GB)	16 GB RDIMM 2R 2933MT/s (1x 16 GB)	32 GB RDIMM 2R 2933 MT/s (1x 32GB)
<b>Network Controller</b>	HPE Ethernet 10Gb 2-port FLR-T BCM57414 Adapter (817721-B21) plus optional stand-up card <b>Notes:</b> No embedded networking	HPE Ethernet 1Gb 4-port FLR-T I350-T4V2 Adapter (665240-B21) plus optional stand-up card <b>Notes:</b> No embedded networking	HPE Ethernet 1Gb 4-port FLR-T I350-T4V2 Adapter (665240-B21) plus optional stand-up card <b>Notes:</b> No embedded networking
<b>Storage Controller</b>	Broadcom MegaRAID MR416i-p 4GB and Smart Storage Battery (SAS/SATA only)	Broadcom MegaRAID MR416i-p 4GB and Smart Storage Battery (SAS/SATA only)	Broadcom MegaRAID MR416i-p 4GB and Smart Storage Battery (SAS/SATA only)
<b>Hard Drive</b>	None Included	None Included	None Included
<b>Internal Storage</b>	8 SFF Chassis (upgradeable to 24 SFF front + 2SFF rear)	8 SFF Chassis (upgradeable to 24 SFF front + 2SFF rear)	8 SFF Chassis (upgradeable to 24 SFF front + 2SFF rear)
<b>PCIe Slots</b>	3-slots (x8, x16, x8 with dual m.2) as standard; upgradeable to 8-slots in a 2 processor configuration		
<b>Power Supply</b>	1x HPE 800W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit	1x HPE 500W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit	1x HPE 500W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit
<b>Fans</b>	4 - Standard	4 - Standard	4 - Standard
<b>Management</b>	HPE iLO Standard with Intelligent Provisioning (embedded), HPE OneView Standard (requires download); HPE iLO Advanced, HPE iLO Advanced Premium Security Edition and HPE OneView Advanced (require licenses)		

### Pre-configured Models

<b>Rail Kit</b>	SFF Easy Install Rail Kit with Cable Management Arm	SFF Easy Install Rail Kit	SFF Easy Install Rail Kit
<b>Energy Star</b>	Energy Star 3.0		
<b>Form Factor</b>	2U Rack		
<b>Warranty</b>	3-year parts, 3-year labor, 3-year onsite support with next business day response.		

#### Notes:

Network Choice (NC) models do not include an embedded NIC. A pre-selected FlexibleLOM is included in the configuration with additional options available via stand-up card NIC adapters listed in the "HPE Networking" section.

UEFI is the standard default for all SMB models.

#### Country Code Key

- -B21 = Worldwide (excl. Japan and PRC)
- -291 = Japan
- -AA1 = China

Worldwide & Japan BTO Models			
<b>SKU Number</b>	P56964-B21 P56964-291	P56965-B21 P56965-291	P56966-B21 P56966-291
<b>Model Name</b>	HPE ProLiant DL380 Gen10 5218R 2.1GHz 20-core 1P 32GB-R MR416i-p NC 8SFF BC 800W PS Server	HPE ProLiant DL380 Gen10 6226R 2.9GHz 16-core 1P 32GB-R MR416i-p NC 8SFF BC 800W PS Server	HPE ProLiant DL380 Gen10 6248R 3.0GHz 24-core 1P 32GB-R MR416i-p NC 8SFF BC 800W PS Server
<b>Chassis</b>	8SFF Chassis (P19720-B21)	8SFF NC Chassis (P19720-B21)	8SFF NC Chassis (P19720-B21)
<b>Processor</b>	5218R (20 core, 2.1GHz, 125W)	6226R (16 core, 2.9GHz, 150W)	6248R (24 core, 3.0 GHz, 205W)
<b>Number of Processors</b>	One with standard heatsink	One with standard heatsink	One with standard heatsink
<b>Memory</b>	32 GB RDIMM 2R 2933 MT/s (1x 32 GB)	32 GB RDIMM 2R 2933MT/s (1x 32 GB)	32 GB RDIMM 2R 2933 MT/s (1x 32GB)
<b>Network Controller</b>	HPE Ethernet 10Gb 2-port FLR-T BCM57414 Adapter (817721-B21) plus optional stand-up card <b>Notes:</b> No embedded networking	HPE Ethernet 10Gb 2-port FLR-T BCM57414 Adapter (817721-B21) plus optional stand-up card <b>Notes:</b> No embedded networking	HPE Ethernet 10Gb 2-port FLR-T BCM57414 Adapter (817721-B21) plus optional stand-up card <b>Notes:</b> No embedded networking
<b>Storage Controller</b>	Broadcom MegaRAID MR416i-p 4GB and Smart Storage Battery (SAS/SATA only)	Broadcom MegaRAID MR416i-p 4GB and Smart Storage Battery (SAS/SATA only)	Broadcom MegaRAID MR416i-p 4GB and Smart Storage Battery (SAS/SATA only)
<b>Hard Drive</b>	None Included	None Included	None Included
<b>Internal Storage</b>	8 SFF Chassis (upgradeable to 24 SFF front + 2SFF rear)	8 SFF Chassis (upgradeable to 24 SFF front + 2SFF rear)	8 SFF Chassis (upgradeable to 24 SFF front + 2SFF rear)
<b>PCIe Slots</b>	3-slots (x8, x16, x8 with dual m.2) as standard; upgradeable to 8-slots in a 2 processor configuration		

### Pre-configured Models

<b>Power Supply</b>	1x HPE 800W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit	1x HPE 800W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit	1x HPE 800W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit
<b>Fans</b>	4 - Standard	4 - Standard	4 - Standard
<b>Management</b>	HPE iLO Standard with Intelligent Provisioning (embedded), HPE OneView Standard (requires download); HPE iLO Advanced, HPE iLO Advanced Premium Security Edition and HPE OneView Advanced (require licenses)		
<b>Rail Kit</b>	SFF Easy Install Rail Kit; cable management arm	SFF Easy Install Rail Kit; cable management arm	SFF Easy Install Rail Kit; cable management arm
<b>Energy Star</b>	Energy Star 3.0		
<b>Form Factor</b>	2U Rack		
<b>Warranty</b>	3-year parts, 3-year labor, 3-year onsite support with next business day response.		

Worldwide & Japan BTO Models	
<b>SKU Number</b>	P56963-B21 P56963-291
<b>Model Name</b>	HPE ProLiant DL380 Gen10 4214R 2.4GHz 12-core 1P 32GB-R MR416i-p 8SFF BC 800W PS Server
<b>Chassis</b>	8SFF Chassis (868703-B21)
<b>Processor</b>	4214R (12 core, 2.4GHz, 100W)
<b>Number of Processors</b>	One with standard heatsink
<b>Memory</b>	32 GB RDIMM 2R 2933 MT/s (1x 32 GB)
<b>Network Controller</b>	Embedded 4 x 1GbE Ethernet Adapter
<b>Storage Controller</b>	Broadcom MegaRAID MR416i-p 4GB and Smart Storage Battery (SAS/SATA only)
<b>Hard Drive</b>	None Included
<b>Internal Storage</b>	8 SFF Chassis (upgradeable to 24 SFF front + 2SFF rear)
<b>PCIe Slots</b>	3-slots (x8, x16, x8 with dual m.2) as standard; upgradeable to 8-slots in a 2 processor configuration
<b>Power Supply</b>	1x HPE 800W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit
<b>Fans</b>	4 - Standard
<b>Management</b>	HPE iLO Standard with Intelligent Provisioning (embedded), HPE OneView Standard (requires download); HPE iLO Advanced, HPE iLO Advanced Premium Security Edition and HPE OneView Advanced (require licenses)
<b>Rail Kit</b>	SFF Easy Install Rail Kit; cable management arm
<b>Energy Star</b>	Energy Star 3.0
<b>Form Factor</b>	2U Rack

### Pre-configured Models

<b>Warranty</b>	3-year parts, 3-year labor, 3-year onsite support with next business day response.
-----------------	--

Worldwide & Japan BTO Networking Choice (NC) Models			
<b>SKU Number</b>	P20182-B21 P20182-291	P20172-B21 P20172-291	P20174-B21 P20174-291
<b>Model Name</b>	HPE ProLiant DL380 Gen10 3204 1.9GHz 6-core 1P 16GB-R S100i NC 8LFF 500W PS Server	HPE ProLiant DL380 Gen10 4208 2.1GHz 8-core 1P 32GB-R P816i-a NC 12LFF 800W RPS Server	HPE ProLiant DL380 Gen10 4210 2.2GHz 10-core 1P 32GB-R P408i-a NC 8SFF 500W PS Server
<b>Chassis</b>	8LFF NC Chassis (P19717-B21)	12LFF NC Chassis (P19718-B21)	8SFF NC Chassis (P19720-B21)
<b>Processor</b>	3204 (6 core, 1.9GHz, 85W)	4208 (8 core, 2.1GHz, 85W)	4210 (10 core, 2.2GHz, 85W)
<b>Number of Processors</b>	One with standard heatsink	One with standard heatsink	One with standard heatsink
<b>Memory</b>	16 GB RDIMM 2R 2933 MT/s (1x 16 GB) <b>Notes:</b> Runs at 2133MT/s due to processor limitation	32 GB RDIMM 2R 2933MT/s (1x 32 GB) <b>Notes:</b> Runs at 2400MT/s due to processor limitation	32 GB RDIMM 2R 2933 MT/s (1x 32GB) <b>Notes:</b> Runs at 2400MT/s due to processor limitation
<b>Network Controller</b>	HPE Ethernet 1Gb 4-port FLR-T I350-T4V2 Adapter (665240-B21) plus optional stand-up card <b>Notes:</b> No embedded networking	HPE Ethernet 1Gb 4-port FLR-T I350-T4V2 Adapter (665240-B21) plus optional stand-up card <b>Notes:</b> No embedded networking	HPE Ethernet 1Gb 4-port FLR-T I350-T4V2 Adapter (665240-B21) plus optional stand-up card <b>Notes:</b> No embedded networking
<b>Storage Controller</b>	S100i embedded SW RAID with 14 SATA ports (12-ports accessible)	P816i-a/4GB with Smart Storage Battery	P408i-a/2GB with Smart Storage Battery
<b>Hard Drive</b>	None Included	None Included	None Included
<b>Internal Storage</b>	8 LFF chassis, with 2 SFF bays optional (upgradeable to 15LFF with 4LFF mid and 3LFF rear + 2SFF rear)	12 LFF chassis, with 2 SFF bays optional (upgradeable to 19LFF with 4LFF mid and 3LFF rear + 2SFF rear)	8 SFF Chassis (upgradeable to 24 SFF front + 6SFF rear)
<b>PCIe Slots</b>	3-slots (x8, x16, x8 with dual m.2) as standard; upgradeable to 8-slots in a 2 processor configuration		
<b>Power Supply</b>	1x HPE 500W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit	2x HPE 800W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit	1x HPE 500W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit
<b>Fans</b>	6 - Standard	6 - Performance	4 - Standard
<b>Management</b>	HPE iLO Standard with Intelligent Provisioning (embedded), HPE OneView Standard (requires download); HPE iLO Advanced, HPE iLO Advanced Premium Security Edition and HPE OneView Advanced (require licenses)		
<b>Rail Kit</b>	LFF Easy Install Rail Kit; cable management arm not included	LFF Easy Install Rail Kit with Cable Management Arm	SFF Easy Install Rail Kit with Cable Management Arm
<b>Energy Star</b>	Energy Star 3.0		
<b>Form Factor</b>	2U Rack		

### Pre-configured Models

<b>Warranty</b>	3-year parts, 3-year labor, 3-year onsite support with next business day response.
-----------------	--

#### Notes:

Network Choice (NC) models do not include an embedded NIC. A pre-selected FlexibleLOM is included in the configuration with additional options available via stand-up card NIC adapters listed in the "HPE Networking" section. UEFI is the standard default for all SMB models.

#### Country Code Key

- -B21 = Worldwide (excl. Japan and PRC)
- -291 = Japan

### Powered by 2nd Generation Intel Xeon Processors

#### SMB Models

- New SMB focused offers regionally released as "Smart Buy Express" in the U.S. and Canada, "Top Value" in Europe, and "Intelligent Buy" in Asia Pacific and Japan".
- SMB Models ship with the configurations below. Options can be selected from the Core or Additional options section of this QuickSpecs.
- Hewlett Packard Enterprise does not provide factory integration of options into SMB Models. Any additional options purchased will be shipped separately and would need to be field integrated.
- If you desire to custom configure an SMB Model please consult your preferred reseller.

SMB Networking Choice (NC) Models			
<b>SKU Number</b>	P23465-B21 P23465-291	P24840-B21 P24840-291	P24841-B21 P24841-291
<b>Model Name</b>	HPE ProLiant DL380 Gen10 4208 2.1GHz 8-core 1P 32GB-R P408i-a NC 8SFF 500W PS Server	HPE ProLiant DL380 Gen10 4210R 2.4GHz 10-core 1P 32GB-R P408i-a NC 24SFF 800W PS Server	HPE ProLiant DL380 Gen10 4210R 2.4GHz 10-core 1P 32GB-R P408i-a NC 8SFF 800W PS Server
<b>Chassis</b>	8SFF NC Chassis (P19720-B21)	24SFF NC Chassis (P19719-B21)	8SFF NC Chassis (P19720-B21)
<b>Processor</b>	4208 (2.1GHz, 8 core, 85W)	4210R (2.4GHz, 10 core, 100W)	4210R (2.4GHz, 10 core, 100W)
<b>Number of Processors</b>	One with standard heatsink	One with standard heatsink	One with standard heatsink
<b>Memory</b>	32 GB RDIMM 2R 2933 MT/s (1x 32 GB; P00924-B21) <b>Notes:</b> Runs at 2400 MT/s due to processor limitation.	32 GB RDIMM 2R 2933 MT/s (1x 32 GB; P00924-B21) <b>Notes:</b> Runs at 2400 MT/s due to processor limitation.	32 GB RDIMM 2R 2933 MT/s (1x 32 GB; P00924-B21) <b>Notes:</b> Runs at 2400 MT/s due to processor limitation.
<b>Network Controller</b>	HPE Ethernet 1Gb 4-port FLR-T I350-T4V2 Adapter (665240-B21) plus optional stand-up card <b>Notes:</b> No embedded networking	HPE Ethernet 1Gb 4-port FLR-T I350-T4V2 Adapter (665240-B21) plus optional stand-up card <b>Notes:</b> No embedded networking	HPE Ethernet 1Gb 4-port FLR-T I350-T4V2 Adapter (665240-B21) plus optional stand-up card <b>Notes:</b> No embedded networking
<b>Storage Controller</b>	P408i-a w/2GB cache (804331-B21) <b>Notes:</b> – 8-Port modular Smart Array.	P408i-a w/2GB cache (804331-B21) + HPE 12Gb SAS Expander Card Kit w/ cables (870549-B21)	P408i-a w/2GB cache (804331-B21) <b>Notes:</b> – 8-Port modular Smart Array.

### Pre-configured Models

	- Smart Storage battery (P01366-B21) included.	- 8-Port modular Smart Array. - Smart Storage battery (P01366-B21) included.	(P01366-B21) included.
<b>Hard Drive</b>	None ship as standard		
<b>Internal Storage</b>	8 SFF (upgradeable to 24 SFF front + 6SFF rear)	24 SFF (upgradeable + 6SFF rear)	8 SFF (upgradeable to 24 SFF front + 6SFF rear)
<b>PCIe Slots</b>	3-slots (x8, x16, x8 with dual m.2) as standard; upgradeable to 8-slots in a 2 processor configuration		
<b>Power Supply</b>	1x HPE 500W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit (865408-B21)	1x HPE 800W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit (865414-B21)	1x HPE 800W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit (865414-B21)
<b>Fans</b>	4-standard fans	6 - Performance	4-standard fans
<b>Management</b>	HPE iLO Standard with Intelligent Provisioning (embedded), HPE OneView Standard (requires download); HPE iLO Advanced, HPE iLO Advanced Premium Security Edition and HPE OneView Advanced (require licenses)		
<b>Rail Kit</b>	SFF Easy install rail kit (73360-B21) with Cable Management Arm (733664-B21)		
<b>Energy Star</b>	3.0 Certified		
<b>Form Factor</b>	2U Rack		
<b>Warranty</b>	3-year parts, 3-year labor, 3-year onsite support with next business day response.		

#### Notes:

Network Choice (NC) models do not include an embedded NIC. A pre-selected FlexibleLOM is included in the configuration with additional options available via stand-up card NIC adapters listed in the "HPE Networking" section.

UEFI is the standard default for all SMB models.

#### Country Code Key

- -B21 = Worldwide (excl. Japan and PRC)
- -291 = Japan

<b>SKU Number</b>	P24842-B21 P24842-291	P24848-B21 / P40425-B21 P24848-291 / P40425-291	P40717-B21 P40717-291
<b>Model Name</b>	HPE ProLiant DL380 Gen10 4214R 2.4GHz 12-core 1P 32GB-R P408i-a NC 8SFF 800W PS Server	HPE ProLiant DL380 Gen10 4215R 3.2GHz 8-core 1P 32GB-R S100i NC 8SFF 800W PS Server	HPE ProLiant DL380 Gen10 4215R 3.2GHz 8-core 1P 32GB-R P408i-a NC 8SFF 800W PS Server
<b>Chassis</b>	8SFF NC Chassis (P19720-B21)		
<b>Processor</b>	4214R (2.4GHz, 12 core, 100W)	4215R (3.2GHz, 8 core, 130W)	4215R (3.2GHz, 8 core, 130W)
<b>Number of Processors</b>	One with standard heatsink	One with performance heatsink	One with performance heatsink
<b>Memory</b>	32 GB RDIMM 2R 2933 MT/s (1x 32 GB; P00924-B21) <b>Notes:</b> Runs at 2400 MT/s due to processor limitation.	32 GB RDIMM 2R 2933 MT/s (1x 32 GB; P00924-B21) <b>Notes:</b> Runs at 2400 MT/s due to processor limitation.	32 GB RDIMM 2R 2933 MT/s (1x 32 GB; P00924-B21) <b>Notes:</b> Runs at 2400 MT/s due to processor limitation.
<b>Network Controller</b>	HPE Ethernet 1Gb 4-port FLR-T I350-T4V2 Adapter (665240-B21) plus optional stand-up card <b>Notes:</b> No embedded	P24848-B21 / 291 HPE Ethernet 10Gb 2-port FLR-SFP+ X710-DA2 Adapter (727054-B21) plus optional stand-	



### Pre-configured Models

	networking	up card <b>Notes:</b> No embedded networking	
		P40425-B21 /291 HPE Ethernet 10Gb 2-port FLR-SFP+ BCM57414 Adapter (P08440-B21) plus optional stand-up card <b>Notes:</b> No embedded networking	HPE Ethernet 10Gb 2-port FLR-SFP+ BCM57414 Adapter (P08440-B21) plus optional stand-up card <b>Notes:</b> No embedded networking
<b>Storage Controller</b>	P408i-a w/2GB cache (804331-B21) <b>Notes:</b> – 8-Port modular Smart Array. – Smart Storage battery (P01366-B21) included.	S100i embedded SW RAID with 14 SATA ports (12-ports accessible)	P408i-a w/2GB cache (804331-B21) <b>Notes:</b> – 8-Port modular Smart Array. – Smart Storage battery (P01366-B21) included.
<b>Hard Drive</b>	None ship as standard		
<b>Internal Storage</b>	8 SFF (upgradeable to 24 SFF front + 6SFF rear)		
<b>PCIe Slots</b>	3-slots (x8, x16, x8 with dual m.2) as standard; upgradeable to 8-slots in a 2 processor configuration		
<b>Power Supply</b>	1x HPE 800W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit (865414-B21)		
<b>Fans</b>	4-standard fans		
<b>Management</b>	HPE iLO Standard with Intelligent Provisioning (embedded), HPE OneView Standard (requires download); HPE iLO Advanced, HPE iLO Advanced Premium Security Edition and HPE OneView Advanced (require licenses)		
<b>Rail Kit</b>	SFF Easy install rail kit (73360-B21) with Cable Management Arm (733664-B21)		
<b>Energy Star</b>	3.0 Certified		
<b>Form Factor</b>	2U Rack		
<b>Warranty</b>	3-year parts, 3-year labor, 3-year onsite support with next business day response.		

#### Notes:

Network Choice (NC) models do not include an embedded NIC. A pre-selected FlexibleLOM is included in the configuration with additional options available via stand-up card NIC adapters listed in the "HPE Networking" section.

UEFI is the standard default for all SMB models.

#### Country Code Key

- -B21 = Worldwide (excl. Japan and PRC)
- -291 = Japan

### Pre-configured Models

SMB Networking Choice (NC) Models		
<b>SKU Number</b>	P36135-B21 P36135-291	P24844-B21 P24844-291
<b>Model Name</b>	HPE ProLiant DL380 Gen10 5218R 2.1GHz 20-core 1P 32GB-R S100i NC 8SFF 800W PS Server	HPE ProLiant DL380 Gen10 5218R 2.1GHz 20-core 1P 32GB-R S100i NC 8SFF 800W PS Server
<b>Chassis</b>	8SFF NC Chassis (P19720-B21)	
<b>Processor</b>	5218R (2.1GHz, 20 core, 125W)	
<b>Number of Processors</b>	One with standard heatsink	
<b>Memory</b>	32 GB RDIMM 2R 2933 MT/s (1x 32 GB; P00924-B21) <b>Notes:</b> Runs at 2666 MT/s due to processor limitation.	
<b>Network Controller</b>	P36135-B21 / 291 HPE Ethernet 10Gb 2-port FLR-T BCM57416 Adapter (817721-B21) plus optional stand-up card <b>Notes:</b> No embedded networking	P24844-B21 / 291 HPE Ethernet 10Gb 2-port FLR-SFP+ X710-DA2 Adapter (727054-B21) plus optional stand-up card <b>Notes:</b> No embedded networking
<b>Storage Controller</b>	S100i embedded SW RAID with 14 SATA ports (12-ports accessible)	
<b>Hard Drive</b>	None ship as standard	
<b>Internal Storage</b>	8 SFF (upgradeable to 24 SFF front + 6SFF rear)	
<b>PCIe Slots</b>	3-slots (x8, x16, x8 with dual m.2) as standard; upgradeable to 8-slots in a 2 processor configuration	
<b>Power Supply</b>	1x HPE 800W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit (865414-B21)	
<b>Fans</b>	4-standard fans	
<b>Management</b>	HPE iLO Standard with Intelligent Provisioning (embedded), HPE OneView Standard (requires download); HPE iLO Advanced, HPE iLO Advanced Premium Security Edition and HPE OneView Advanced (require licenses)	
<b>Rail Kit</b>	SFF Easy install rail kit (73360-B21) with Cable Management Arm (733664-B21)	
<b>Energy Star</b>	3.0 Certified	
<b>Form Factor</b>	2U Rack	
<b>Warranty</b>	3-year parts, 3-year labor, 3-year onsite support with next business day response.	

#### Notes:

Network Choice (NC) models do not include an embedded NIC. A pre-selected FlexibleLOM is included in the configuration with additional options available via stand-up card NIC adapters listed in the "HPE Networking" section.

UEFI is the standard default for all SMB models.

#### Country Code Key

- -B21 = Worldwide (excl. Japan and PRC)
- -291 = Japan

### Pre-configured Models

SMB Networking Choice (NC) Models			
<b>SKU Number</b>	P24845-B21/ P40422-B21 P24845-291/ P40422-291	P24846-B21/ P40423-B21 P24846-291/ P40423-291	P24847-B21/ P40424-B21 P24847-291/ P40424-291
<b>Model Name</b>	HPE ProLiant DL380 Gen10 5222 3.8GHz 4-core 1P 32GB-R S100i NC 8SFF 800W PS Server	HPE ProLiant DL380 Gen10 6226R 2.9GHz 16- core 1P 32GB-R S100i NC 8SFF 800W PS Server	HPE ProLiant DL380 Gen10 6234 3.3GHz 8- core 1P 32GB-R S100i NC 8SFF 800W PS Server
<b>Chassis</b>	8SFF NC Chassis (P19720-B21)		
<b>Processor</b>	5222 (3.8GHz, 4 core, 105W)	6226R (2.9GHz, 16 core, 150W)	6234 (3.3GHz, 8 core, 130W)
<b>Number of Processors</b>	One with performance heatsink	One with performance heatsink	One with performance heatsink
<b>Memory</b>	32 GB RDIMM 2R 2933 MT/s (1x 32 GB; P00924-B21)	32 GB RDIMM 2R 2933 MT/s (1x 32 GB; P00924-B21)	32 GB RDIMM 2R 2933 MT/s (1x 32 GB; P00924-B21)
<b>Network Controller</b>	P24845-B21 / 291, P24846-B21 / 291, P24847-B21 / 291 HPE Ethernet 10Gb 2-port FLR-SFP+ X710-DA2 Adapter (727054-B21) plus optional stand-up card <b>Notes: No embedded networking</b> P40422-B21 / 291,, P40423-B21 / 291, P40424-B21 / 291 HPE Ethernet 10Gb 2-port FLR-SFP+ BCM57414 Adapter (P08440-B21) plus optional stand-up card <b>Notes: No embedded networking</b>		
<b>Storage Controller</b>	S100i embedded SW RAID with 14 SATA ports (12-ports accessible)		
<b>Hard Drive</b>	None ship as standard		
<b>Internal Storage</b>	8 SFF (upgradeable to 24 SFF front + 6SFF rear)		
<b>PCIe Slots</b>	3-slots (x8, x16, x8 with dual m.2) as standard; upgradeable to 8-slots in a 2 processor configuration		
<b>Power Supply</b>	1x HPE 800W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit (865414- B21)		
<b>Fans</b>	4-standard fans		
<b>Management</b>	HPE iLO Standard with Intelligent Provisioning (embedded), HPE OneView Standard (requires download); HPE iLO Advanced, HPE iLO Advanced Premium Security Edition and HPE OneView Advanced (require licenses)		
<b>Rail Kit</b>	SFF Easy install rail kit (73360-B21) with Cable Management Arm (733664-B21)		
<b>Energy Star</b>	3.0 Certified		
<b>Form Factor</b>	2U Rack		
<b>Warranty</b>	3-year parts, 3-year labor, 3-year onsite support with next business day response.		

#### Notes:

Network Choice (NC) models do not include an embedded NIC. A pre-selected FlexibleLOM is included in the configuration with additional options available via stand-up card NIC adapters listed in the "HPE Networking" section.

UEFI is the standard default for all SMB models.

#### Country Code Key

- -B21 = Worldwide (excl. Japan and PRC)
- -291 = Japan

### Pre-configured Models

SMB Networking Choice (NC) Models		
<b>SKU Number</b>	P24849-B21/ P40426-B21 P24849-291/ P40426-291	P24850-B21/ P40427-B21 P24850-291/ P40427-291
<b>Model Name</b>	HPE ProLiant DL380 Gen10 6248R 3.0GHz 24-core 1P 32GB-R S100i NC 8SFF 800W PS Server	HPE ProLiant DL380 Gen10 6250 3.9GHz 8-core 1P 32GB-R S100i NC 8SFF 800W PS Server
<b>Chassis</b>	8SFF	
<b>Processor</b>	6248R (3.0GHz, 24 core, 205W)	6250 (3.9GHz, 8 core, 185W) <sup>1</sup>
<b>Number of Processors</b>	One with performance heatsink	One with performance heatsink
<b>Memory</b>	32 GB RDIMM 2R 2933 MT/s (1x 32 GB; P00924-B21)	
<b>Network Controller</b>	P24849-B21 / 291, P24850-B21 / 291 HPE Ethernet 10Gb 2-port FLR-SFP+ X710-DA2 Adapter (727054-B21) plus optional stand-up card <b>Notes:</b> No embedded networking	
	P40426-B21 / 291, P40427-B21 / 291 HPE Ethernet 10Gb 2-port FLR-SFP+ BCM57414 Adapter (P08440-B21) plus optional stand-up card <b>Notes:</b> No embedded networking	
<b>Storage Controller</b>	S100i embedded SW RAID with 14 SATA ports (12-ports accessible)	
<b>Hard Drive</b>	None ship as standard	
<b>Internal Storage</b>	8 SFF Chassis (upgradeable to 24 SFF front + 6SFF rear)	
<b>PCIe Slots</b>	3-slots (x8, x16, x8 with dual m.2) as standard; upgradeable to 8-slots in a 2 processor configuration	
<b>Power Supply</b>	1x HPE 800W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit (865414-B21)	
<b>Fans</b>	4-standard fans	6-high performance fans
<b>Management</b>	HPE iLO Standard with Intelligent Provisioning (embedded), HPE OneView Standard (requires download); HPE iLO Advanced, HPE iLO Advanced Premium Security Edition and HPE OneView Advanced (require licenses)	
<b>Rail Kit</b>	SFF Easy install rail kit (73360-B21) with Cable Management Arm (733664-B21)	
<b>Energy Star</b>	3.0 Certified	
<b>Form Factor</b>	2U Rack	
<b>Warranty</b>	3-year parts, 3-year labor, 3-year onsite support with next business day response.	

#### Notes:

Network Choice (NC) models do not include an embedded NIC. A pre-selected FlexibleLOM is included in the configuration with additional options available via stand-up card NIC adapters listed in the "HPE Networking" section.

UEFI is the standard default for all SMB models.

<sup>1</sup>Not supported with NVMe SSDs, nor 2SFF HDD kits (826687-B21; 826688-B21) installed in rear, nor GPUs, nor 4LFF mid-tray. Detailed configuration and facilities requirements can be found under "Intel Xeon Scalable Series 6250, 6250L, and 6256 Configuration and Facilities Requirements Matrix" with this document.

#### Country Code Key

- -B21 = Worldwide (excl. Japan and PRC)
- -291 = Japan

SMB Networking Choice (NC) Models			
<b>SKU Number</b>	P20245-B21/ P40428-B21 P20245-291/ P40428-291	P20248-B21/ P39380-B21 P20248-291/ P39380-291	P20249-B21 P20249-291

### Pre-configured Models

<b>Model Name</b>	HPE ProLiant DL380 Gen10 6242 2.8GHz 16-core 1P 32GB-R P408i-a NC 8SFF 800W PS Server	HPE ProLiant DL380 Gen10 5220 2.2GHz 18-core 1P 32GB-R P408i-a NC 8SFF 800W PS Server	HPE ProLiant DL380 Gen10 5218 2.3GHz 16-core 1P 32GB-R P408i-a NC 8SFF 800W PS Server
<b>Chassis</b>	8SFF		
<b>Processor</b>	6242 (16C, 2.8GHz, 150W)	5220 (18C, 2.2GHz, 125W)	5218 (16 core, 2.3 GHz, 125W)
<b>Number of Processors</b>	1	1	1
<b>Memory</b>	32 GB RDIMM 2R 2933 MT/s (1x 32 GB)	32 GB RDIMM 2R 2933 MT/s (1x 32 GB) <b>Notes:</b> Runs at 2666 MT/s due to processor limitation.	32 GB RDIMM 2R 2933 MT/s (1x 32 GB) <b>Notes:</b> Runs at 2666 MT/s due to processor limitation.
<b>Network Controller</b>	P20245-B21 / 291 HPE Ethernet 10/25Gb 2-port FLR-SFP28 MCX4121A-ACFT Adapter (817749-B21) plus optional stand-up card <b>Notes:</b> No embedded networking	P20248-B21 /291 HPE Ethernet 10/25Gb 2-port FLR-SFP28 MCX4121A-ACFT Adapter (817749-B21) plus optional stand-up card <b>Notes:</b> No embedded networking	HPE Ethernet 1Gb 4-port FLR-T I350-T4V2 Adapter (665240-B21) plus optional stand-up card <b>Notes:</b> No embedded networking
	P40428-B21 / 291 HPE Ethernet 10/25Gb 2-port FLR-SFP28 BCM57414 Adapter (817709-B21) plus optional stand-up card <b>Notes:</b> No embedded networking	P39380-B21 / 291 HPE Ethernet 10/25Gb 2-port FLR-SFP28 BCM57414 Adapter (817709-B21) plus optional stand-up card <b>Notes:</b> No embedded networking	
<b>Storage Controller</b>	P408i-a w/2GB cache <b>Notes:</b> 8-Port modular Smart Array. Smart Storage battery included.		
<b>Hard Drive</b>	None ship as standard		
<b>Internal Storage</b>	8 SFF Chassis (upgradeable to 24 SFF front + 6SFF rear)		
<b>PCIe Slots</b>	3-slots (x8, x16, x8 with dual m.2) as standard; upgradeable to 8-slots in a 2 processor configuration	3-slots (x8, x16, x8 with dual m.2) as standard; upgradeable to 8-slots in a 2 processor configuration	3-slots (x8, x16, x8 with dual m.2) as standard; upgradeable to 8-slots in a 2 processor configuration
<b>Power Supply</b>	1x HPE 800W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit	1x HPE 800W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit	1x HPE 800W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit
<b>Fans</b>	4-standard fans	4-standard fans	6-standard fans
<b>Management</b>	HPE iLO Standard with Intelligent Provisioning (embedded), HPE OneView Standard (requires download); HPE iLO Advanced, HPE iLO Advanced Premium Security Edition and HPE OneView Advanced (require licenses)		
<b>Rail Kit</b>	SFF Easy install rails with Cable Management Arm		
<b>Energy Star</b>	3.0 Certified		
<b>Form Factor</b>	2U Rack		
<b>Warranty</b>	3-year parts, 3-year labor, 3-year onsite support with next business day response.		

### Pre-configured Models

#### Notes:

Network Choice (NC) models do not include an embedded NIC. A pre-selected FlexibleLOM is included in the configuration with additional options available via stand-up card NIC adapters listed in the "HPE Networking" section.

UEFI is the standard default for all SMB models.

#### Country Code Key

- -B21 = Worldwide (excl. Japan and PRC)
- -291 = Japan

Worldwide & Japan BTO Networking Choice (NC) Models	
<b>HPE ProLiant DL380 Gen10 4210R 2.4GHz 10-core 1P 32GB-R P408i-a 8SFF 800W PS Server</b>	P50751-B21
<b>Model Name</b>	HPE ProLiant DL380 Gen10 4210R 2.4GHz 10-core 1P 32GB-R P408i-a 8SFF 800W PS Server
<b>Chassis</b>	8SFF Embedded NIC Chassis (868703-B21)
<b>Processor</b>	4210R (10 core, 2.4GHz, 100W)
<b>Number of Processors</b>	One with standard heatsink
<b>Memory</b>	32 GB RDIMM 2R 2933 MT/s (1x 32 GB; P00924-B21) <b>Notes:</b> Runs at 2400 MT/s due to processor limitation.
<b>Network Controller</b>	HPE Ethernet 1Gb 4-port plus optional stand-up card
<b>Storage Controller</b>	P408i-a w/2GB cache (804331-B21) <b>Notes:</b> – 8-Port modular Smart Array. – Smart Storage battery (P01366-B21) included.
<b>Hard Drive</b>	None Included
<b>Internal Storage</b>	8 SFF (upgradeable to 24 SFF front + 6SFF rear)
<b>PCIe Slots</b>	3-slots (x8, x16, x8 with dual m.2) as standard; upgradeable to 8-slots in a 2 processor configuration
<b>Power Supply</b>	1x HPE 800W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit (865414-B21)
<b>Fans</b>	4-standard fans
<b>Management</b>	HPE iLO Standard with Intelligent Provisioning (embedded), HPE OneView Standard (requires download); HPE iLO Advanced, HPE iLO Advanced Premium Security Edition and HPE OneView Advanced (require licenses)
<b>Rail Kit</b>	SFF Easy Install Rail Kit with Cable Management Arm
<b>Energy Star</b>	Energy Star 3.0
<b>Form Factor</b>	2U Rack
<b>Warranty</b>	3-year parts, 3-year labor, 3-year onsite support with next business day response.



### Configuration Information

This section lists some of the steps required to configure a Factory Integrated Model. To ensure only valid configurations are ordered, Hewlett Packard Enterprise recommends the use of an HPE approved configurator. Contact your local sales representative for information on configurable product offerings and requirements.

- Factory Integrated Models must start with a CTO Server.
- FIO indicates that this option is only available as a factory installable option.
- All Factory Integrated Models will be populated with sufficient hard drive blanks based on the number of initial hard drives ordered with the server.
- Some options may not be integrated at the factory. Contact your local sales representative for additional information.

**Step 1: Base Configuration** (choose one (1) of the following eight (8) configurable server models from the tables below)

The below (4) CTO server models denoted with "NC" in the SKU description, provide flexibility in the networking choice and require a FlexibleLOM Adapter or a validated alternative from the "HPE Networking" section be selected.

<b>Networking Choice CTO Server Models</b>	HPE ProLiant DL380 Gen10 8LFF NC CTO Server	HPE ProLiant DL380 Gen10 12LFF NC CTO Server	HPE ProLiant DL380 Gen10 8SFF NC CTO Server	HPE ProLiant DL380 Gen10 24SFF NC CTO Server
<b>SKU Number</b>	P19717-B21	P19718-B21	P19720-B21	P19719-B21
<b>HPE Trusted Supply Chain</b>	P36394-B21 Optional			
<b>TAA Instruction SKU</b>	P19713-B21 Optional			
<b>Processor</b>	Not included as standard	Not included as standard	Not included as standard	Not included as standard
<b>DIMM Slots</b>	24-DIMM slots	24-DIMM slots	24-DIMM slots	24-DIMM slots
<b>Storage Controller</b>	Embedded SW RAID with 14 SATA ports (12-ports accessible), choice of HPE modular Smart Array and PCIe plug-in controller			
<b>PCIe</b>	Three standard in primary riser (with dual M.2 support)			
<b>Drive Cage - included</b>	8 LFF	12 LFF	8 SFF	24 SFF
<b>Network Controller</b>	Choice of either HPE FlexibleLOM or select stand-up network adapters for primary networking selection plus additional/optional stand-up network adapters <b>Notes: No embedded networking</b>			
<b>Fans</b>	6-Standard	6-Performance	4-Standard	6-Performance
<b>Management</b>	HPE iLO with Intelligent Provisioning (standard), iLO Advances and OneView (optional)			
<b>USB</b>	1x 3.0 standard plus iLO front service port	None as standard	1x 3.0 standard plus iLO front service port	1x 3.0 standard plus iLO front service port

### Configuration Information

<b>Networking Choice CTO Server Models</b>	HPE DL380 Gen10 NC 8SFF BC CTO Svr
<b>SKU Number</b>	P56969-B21
<b>HPE Trusted Supply Chain</b>	P36394-B21 Optional
<b>Processor</b>	Not included as standard
<b>DIMM Slots</b>	24-DIMM slots
<b>Storage Controller</b>	Embedded SW RAID with 14 SATA ports (12-ports accessible), choice of HPE Tri-Mode controller
<b>PCIe</b>	Three standard in primary riser (with dual M.2 support)
<b>Drive Cage - included</b>	8 SFF
<b>Network Controller</b>	Choice of either HPE FlexibleLOM or select stand-up network adapters for primary networking selection plus additional/optional stand-up network adapters <b>Notes:</b> No embedded networking
<b>Fans</b>	4-Standard
<b>Management</b>	HPE iLO with Intelligent Provisioning (standard), iLO Advances and OneView (optional)
<b>USB</b>	1x 3.0 standard plus iLO front service port

#### Notes:

Network Choice (NC) server models require a networking selection of a FlexibleLOM from the options listed in the "FlexibleLOM Adapter" section or select network adapters in the "HPE Networking" section.

HPE Trusted Supply Chain (P36394-B21) is an optional security upgrade intended for agencies and regulated industries needing enhanced security and compliance needs. Applying this option to a DL380 Gen10 CTO server ensures it is built in the USA in a secured facility by vetted HPE personnel assigned to the manufacturing processes. A multitude of checkpoints/inspections for malicious microcode and counterfeit parts are performed throughout the server build, and additional safeguards are put in place against cyber-exploits throughout the server lifecycle. The HPE ProLiant DL380 Gen10 server is re-branded as a HPE ProLiant DL380T Gen10 to denote the HPE Trusted Supply Chain security enhancements. The DL380T Gen10 is currently supported in the USA, exclusively, and is Trade Agreement Act (TAA) compliant. See "HPE Security" section within this document for more detail and learn more at

<http://www.hpe.com/security>

HPE offers multiple Trade Agreement Act (TAA) compliant configurations to meet the needs of US Federal Government customers. These products are either manufactured or substantially transformed in a designated country. TAA compliance is only provided when HPE options are included as part of factory integrated orders (CTO).

To select a TAA model from the above, first select a Networking Choice CTO server model, then add the TAA Instruction SKU (P19713-B21).

The HPE ProLiant DL380 Gen10 12 LFF CTO Server ships with the cable required for the P816i-a installation.

All CTO servers are Energy Star 3.0 compliant.

The below (4) CTO server models come standard with an embedded HPE 1Gb Ethernet 4-port 331i adapter.

### Configuration Information

<b>Embedded LOM CTO Server Models</b>	HPE ProLiant DL380 Gen10 8LFF CTO Server	HPE ProLiant DL380 Gen10 12LFF CTO Server	HPE ProLiant DL380 Gen10 8SFF CTO Server	HPE ProLiant DL380 Gen10 24SFF CTO Server
<b>SKU Number</b>	868706-B21	868705-B21	868703-B21	868704-B21
<b>HPE Trusted Supply Chain</b>	P36394-B21 Optional			
<b>TAA Instruction SKU</b>	P19713-B21 Optional			
<b>Processor</b>	Not included as standard	Not included as standard	Not included as standard	Not included as standard
<b>DIMM Slots</b>	24-DIMM slots	24-DIMM slots	24-DIMM slots	24-DIMM slots
<b>Storage Controller</b>	Embedded SW RAID with 14 SATA ports (12-ports accessible), choice of HPE modular Smart Array and PCIe plug-in controller			
<b>PCIe</b>	Three standard in primary riser (with dual M.2 support)			
<b>Drive Cage - included</b>	8 LFF	12 LFF	8 SFF	24 SFF
<b>Network Controller</b>	HPE 1Gb Ethernet 4-Port 331i Adapter plus optional HPE FlexibleLOM or stand up card			
<b>Fans</b>	6-Standard	6-Performance	4-Standard	6-Performance
<b>Management</b>	HPE iLO with Intelligent Provisioning (standard), iLO Advances and OneView (optional)			
<b>USB</b>	1x 3.0 standard plus iLO front service port	None as standard	1x 3.0 standard plus iLO front service port	1x 3.0 standard plus iLO front service port

### Configuration Information

<b>Embedded LOM CTO Server Models</b>	HPE DL380 Gen10 8SFF BC CTO Svr
<b>SKU Number</b>	P56970-B21
<b>HPE Trusted Supply Chain</b>	P36394-B21 Optional
<b>Processor</b>	Not included as standard
<b>DIMM Slots</b>	24-DIMM slots
<b>Storage Controller</b>	Embedded SW RAID with 14 SATA ports (12-ports accessible), choice of HPE Tri-Mode storage controller for SAS/SATA only.
<b>PCIe</b>	Three standard in primary riser (with dual M.2 support)
<b>Drive Cage - included</b>	8 SFF
<b>Network Controller</b>	HPE 1Gb Ethernet 4-Port 331i Adapter plus optional HPE FlexibleLOM or stand up card
<b>Fans</b>	4-Standard
<b>Management</b>	HPE iLO with Intelligent Provisioning (standard), iLO Advances and OneView (optional)
<b>USB</b>	1x 3.0 standard plus iLO front service port

#### Notes:

HPE Trusted Supply Chain (P36394-B21) is an optional security upgrade intended for agencies and regulated industries needing enhanced security and compliance needs. Applying this option to a DL380 Gen10 CTO server ensures it is built in the USA in a secured facility by vetted HPE personnel assigned to the manufacturing processes. A multitude of checkpoints/inspections for malicious microcode and counterfeit parts are performed throughout the server build with additional safeguards in place against cyber-exploits throughout the server lifecycle. The HPE ProLiant DL380 Gen10 server is re-branded as a HPE ProLiant DL380T Gen10 Server to denote the HPE Trusted Supply Chain security enhancements. The DL380T Gen10 is currently supported in the USA, exclusively, and is Trade Agreement Act (TAA) compliant. See "HPE Security" section within this document for more detail and learn more at <http://www.hpe.com/security>

#### <http://www.hpe.com/security>

HPE offers multiple Trade Agreement Act (TAA) compliant configurations to meet the needs of US Federal Government customers. These products are either manufactured or substantially transformed in a designated country. TAA compliance is only provided when HPE options are included as part of factory integrated orders (CTO).

To select a TAA model from the above, first select an Embedded LOM CTO server model, then add the TAA Instruction SKU (P19713-B21)

The HPE ProLiant DL380 Gen10 12 LFF CTO Server ships with the cable required for the P816i-a installation.

All CTO servers are Energy Star 3.0 compliant.

### Configuration Information

CTO Server	8 SFF CTO Chassis	24 SFF CTO Chassis	8 LFF CTO Chassis	12 LFF CTO Chassis
Included Drive Cage	8 SFF SAS/SATA	3x 8 SFF SAS/SATA	8 LFF + UMB	12 LFF Chassis
Universal Media Bay	1 Optional	Not available	1 Included	Not available
ODD	1 Optional with UMB	Not available	1 Optional	Not available
8 SFF Drive Cage	Up to 2 Optional	Not available	Not available	Not available
8 NVME/SAS Bay	Up to 3 Optional	Not available	Not available	Not available
8 NVME Cage	Up to 3 Optional	Not available	Not available	Not available
2 SFF SAS/SATA (Front)	1 Optional with UMB	Not available	1 Optional	Not available
2 SFF SAS/SATA (Rear)	1 Optional	1 Optional	1 Optional	1 Optional
2 NVMe (Front)	1 Optional with UMB	Not available	1 Optional	Not available
4 LFF Mid-plane	Not available	Not available	1 Optional	1 Optional
3 LFF Rear	Not available	Not available	1 Optional	1 Optional

#### Notes:

This applies to CTO configurations; field upgrades may differ depending on field configuration.  
3x 8 NVMe option on SFF will only allow for partial population of Box1 to max 20 NVMe.

### Step 2: Choose Required Options (only one of the following unless otherwise noted)

Please select one -L21 processor required below.

For second processor, please select the same processor model with -B21 from Core Options - HPE Processors section.

For example: first processor, select 874752-L21 then for second processor, select 874752-B21.

#### Notes:

8SFF CTO 1P models ship with 4 standard fans. The second processor option kit contains 2 additional fans. 12 LFF and 24 SFF CTO Servers ship with 6 High performance fans included; 8LFF CTO Servers ship with 6 Standard fans included.

High performance fan kit is available to meet ambient temperature environments and are required for rear drives or NVMe configurations.

Maximum memory capacity per processor is dependent on processor models. All processors support up to 768 GB max memory per processor except "M" model processors will support up to 1.5 TB max memory per processor.

Mixing of 2 different processor models are NOT allowed.

DDR4 speed is the maximum memory speed of the processor. Actual memory speed may depend on the quantity and type of DIMMs installed.

Processors with 130W or higher will ship with the High Performance heat sink plus SKUs 8156, 6128, 5122 as noted below. All other will processors will ship with the Standard heat sink.

### Step 2a: Choose Processors

#### Processor Option Kits (Required Processor)

#### 2<sup>nd</sup> Generation Intel Xeon-Platinum

#### Notes:

Field upgrades from 1<sup>st</sup> generation processors (x1xx) to 2<sup>nd</sup> generation processors (x2xx) not supported.  
All the below models ships with Performance Heatsink.

## Configuration Information

Intel Xeon-Platinum 8280L (2.7GHz/28-core/205W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02540-L21
Intel Xeon-Platinum 8280 (2.7GHz/28-core/205W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02527-L21
Intel Xeon-Platinum 8276L (2.2GHz/28-core/165W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02539-L21
Intel Xeon-Platinum 8276 (2.2GHz/28-core/165W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02526-L21
Intel Xeon-Platinum 8270 (2.7GHz/26-core/205W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02525-L21
Intel Xeon-Platinum 8268 (2.9GHz/24-core/205W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02524-L21
Intel Xeon-Platinum 8260Y (2.4GHz/24-core/165W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02508-L21
Intel Xeon-Platinum 8260L (2.4GHz/24-core/165W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02538-L21
Intel Xeon-Platinum 8260 (2.4GHz/24-core/165W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02521-L21
Intel Xeon-Platinum 8256 (3.8GHz/4-core/105W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02519-L21
Intel Xeon-Platinum 8253 (2.2GHz/16-core/125W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02518-L21

**Notes:** Do not ship with Performance Heatsink.

**2<sup>nd</sup> Generation Intel Xeon-Gold****Notes:**

Field upgrades from 1<sup>st</sup> generation processors (x1xx) to 2<sup>nd</sup> generation processors (x2xx) not supported.  
All the below models ship with Performance Heatsink.

Intel Xeon-Gold 6262V (1.9GHz/24-core/135W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P11822-L21
Intel Xeon-Gold 6258R (2.7GHz/28-core/205W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P24474-L21
Intel Xeon-Gold 6256 (3.6GHz/12-core/205W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P24476-L21

**Notes:**

Requires high performance fan kit (867810-B21), unless 24SFF or 12LFF server models are selected, which provide high performance fans as the default.

Not supported with NVMe SSDs, nor 2SFF HDD kits (826687-B21; 826688-B21) installed in rear, nor GPUs, nor 4LFF mid-tray. Detailed configuration and facilities requirements can be found under "Intel Xeon Scalable Series 6250, 6250L, and 6256 Configuration and Facilities Requirements Matrix" with this document.

Intel Xeon-Gold 6254 (3.1GHz/18-core/200W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02517-L21
Intel Xeon-Gold 6252N (2.3GHz/24-core/150W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P11829-L21



## Configuration Information

Intel Xeon-Gold 6252 (2.1GHz/24-core/150W) FIO Processor Kit for HPE ProLiant DL380 Gen10 P02516-L21

Intel Xeon-Gold 6250L (3.9GHz/8-core/185W) FIO Processor Kit for HPE ProLiant DL380 Gen10 P28387-L21

**Notes:**

Requires high performance fan kit (867810-B21), unless 24SFF or 12LFF server models are selected, which provide high performance fans as the default.

Not supported with NVMe SSDs, nor 2SFF HDD kits (826687-B21; 826688-B21) installed in rear, nor GPUs, nor 4LFF mid-tray. Detailed configuration and facilities requirements can be found under "Intel Xeon Scalable Series 6250, 6250L, and 6256 Configuration and Facilities Requirements Matrix" with this document.

Intel Xeon-Gold 6250 (3.9GHz/8-core/185W) FIO Processor Kit for HPE ProLiant DL380 Gen10 P24475-L21

**Notes:**

Requires high performance fan kit (867810-B21), unless 24SFF or 12LFF server models are selected, which provide high performance fans as the default.

Not supported with NVMe SSDs, nor 2SFF HDD kits (826687-B21; 826688-B21) installed in rear, nor GPUs, nor 4LFF mid-tray. Detailed configuration and facilities requirements can be found under "Intel Xeon Scalable Series 6250, 6250L, and 6256 Configuration and Facilities Requirements Matrix" with this document.

Intel Xeon-Gold 6248R (3.0GHz/24-core/205W) FIO Processor Kit for HPE ProLiant DL380 Gen10 P24473-L21

Intel Xeon-Gold 6248 (2.5GHz/20-core/150W) FIO Processor Kit for HPE ProLiant DL380 Gen10 P02514-L21

Intel Xeon-Gold 6246R (3.4GHz/16-core/205W) FIO Processor Kit for HPE ProLiant DL380 Gen10 P24472-L21

Intel Xeon-Gold 6246 (3.3GHz/12-core/165W) FIO Processor Kit for HPE ProLiant DL380 Gen10 P15758-L21

Intel Xeon-Gold 6244 (3.6GHz/8-core/150W) FIO Processor Kit for HPE ProLiant DL380 Gen10 P02512-L21

Intel Xeon-Gold 6242R (3.1GHz/20-core/205W) FIO Processor Kit for HPE ProLiant DL380 Gen10 P24471-L21

Intel Xeon-Gold 6242 (2.8GHz/16-core/150W) FIO Processor Kit for HPE ProLiant DL380 Gen10 P02510-L21

Intel Xeon-Gold 6240R (2.4GHz/24-core/165W) FIO Processor Kit for HPE ProLiant DL380 Gen10 P24470-L21

Intel Xeon-Gold 6240L (2.6GHz/18-core/150W) FIO Processor Kit for HPE ProLiant DL380 Gen10 P02537-L21

Intel Xeon-Gold 6240Y (2.6GHz/18-14-8-core/150W) FIO Processor Kit for HPE ProLiant DL380 Gen10 P02507-L21

Intel Xeon-Gold 6240 (2.6GHz/18-core/150W) FIO Processor Kit for HPE ProLiant DL380 Gen10 P02509-L21

Intel Xeon-Gold 6238R (2.2GHz/28-core/165W) FIO Processor Kit for HPE ProLiant DL380 Gen10 P24469-L21

Intel Xeon-Gold 6238L (2.1GHz/22-core/140W) FIO Processor Kit for HPE ProLiant DL380 Gen10 P02536-L21

## Configuration Information

Intel Xeon-Gold 6238 (2.1GHz/22-core/140W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02504-L21
Intel Xeon-Gold 6234 (3.3GHz/8-core/130W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02503-L21
Intel Xeon-Gold 6230R (2.1GHz/26-core/150W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P24468-L21
Intel Xeon-Gold 6230 (2.1GHz/20-core/125W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02502-L21
<b>Notes:</b> Do not ship with Performance Heatsink.	
Intel Xeon-Gold 6230N (2.3GHz/20-core/125W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P11830-L21
<b>Notes:</b> Do not ship with Performance Heatsink.	
Intel Xeon-Gold 6226R (2.9GHz/16-core/150W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P24467-L21
Intel Xeon-Gold 6226 (2.7GHz/12-core/125W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02501-L21
<b>Notes:</b> Do not ship with Performance Heatsink.	
Intel Xeon-Gold 6222V (1.8GHz/20-core/115W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P11823-L21
<b>Notes:</b> Do not ship with Performance Heatsink.	
Intel Xeon-Gold 6212U (2.4GHz/24-core/165W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P11825-L21
<b>Notes:</b> 2-processor configurations NOT supported with this processor; secondary and tertiary risers not supported	
Intel Xeon-Gold 6210U (2.5GHz/20-core/150W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P11826-L21
<b>Notes:</b> 2-processor configurations NOT supported with this processor; secondary and tertiary risers not supported	
Intel Xeon-Gold 6209U (2.1GHz/20-core/125W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P11827-L21
<b>Notes:</b> 2-processor configurations NOT supported with this processor; secondary and tertiary risers not supported Do not ship with Performance Heatsink.	
Intel Xeon-Gold 6208U (2.9GHz/16-core/150W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P24477-L21
Intel Xeon-Gold 5222 (3.8GHz/4-core/105W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02500-L21
Intel Xeon-Gold 5220S (2.7GHz/18-core/125W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P11824-L21
<b>Notes:</b> Do not ship with Performance Heatsink.	
Intel Xeon-Gold 5220R (2.2GHz/24-core/150W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P23553-L21
Intel Xeon-Gold 5220 (2.2GHz/18-core/125W) FIO Processor Kit for HPE ProLiant DL380 Gen10	P02499-L21
<b>Notes:</b> Do not ship with Performance Heatsink.	

## Configuration Information

Intel Xeon-Gold 5218R (2.1GHz/20-core/125W) FIO Processor Kit for HPE ProLiant DL380 Gen10 P24466-L21

**Notes:** Do not ship with Performance Heatsink.

Intel Xeon-Gold 5218N (2.3GHz/16-core/110W) FIO Processor Kit for HPE ProLiant DL380 Gen10 P11831-L21

**Notes:** Do not ship with Performance Heatsink.

Intel Xeon-Gold 5218B (2.3GHz/16-core/125W) FIO Processor Kit for HPE ProLiant DL380 Gen10 P12513-L21

**Notes:**

5218B has consistent features with the 5218 processor but from a different die. Mixing both 5218B & 5218 in a system is not supported

Do not ship with Performance Heatsink.

Intel Xeon-Gold 5218 (2.3GHz/16-core/125W) FIO Processor Kit for HPE ProLiant DL380 Gen10 P02498-L21

**Notes:** Do not ship with Performance Heatsink.

Intel Xeon-Gold 5217 (3.0GHz/8-core/115W) FIO Processor Kit for HPE ProLiant DL380 Gen10 P02497-L21

**Notes:** Do not ship with Performance Heatsink.

Intel Xeon-Gold 5215L (2.5GHz/10-core/85W) FIO Processor Kit for HPE ProLiant DL380 Gen10 P02533-L21

**Notes:** Do not ship with Performance Heatsink.

Intel Xeon-Gold 5215 (2.5GHz/10-core/85W) FIO Processor Kit for HPE ProLiant DL380 Gen10 P02496-L21

**Notes:** Do not ship with Performance Heatsink.

**2<sup>nd</sup> Generation Intel Xeon-Silver****Notes:**

Field upgrades from 1<sup>st</sup> generation processors (x1xx) to 2<sup>nd</sup> generation processors (x2xx) not supported. All the below models do not ship with Performance Heatsink unless otherwise noted

Intel Xeon-Silver 4216 (2.1GHz/16-core/100W) FIO Processor Kit for HPE ProLiant DL380 Gen10 P02495-L21

Intel Xeon-Silver 4215R (3.2GHz/8-core/130W) FIO Processor Kit for HPE ProLiant DL380 Gen10 P24465-L21

**Notes:** Ships with Performance Heatsink.

Intel Xeon-Silver 4215 (2.5GHz/8-core/85W) FIO Processor Kit for HPE ProLiant DL380 Gen10 P02494-L21

Intel Xeon-Silver 4214R (2.4GHz/12-core/100W) FIO Processor Kit for HPE ProLiant DL380 Gen10 P23550-L21

Intel Xeon-Silver 4214Y (2.2GHz/12-10-8-core/85W) FIO Processor Kit for HPE ProLiant DL380 Gen10 P02506-L21

Intel Xeon-Silver 4214 (2.2GHz/12-core/85W) FIO Processor Kit for HPE ProLiant DL380 Gen10 P02493-L21

Intel Xeon-Silver 4210R (2.4GHz/10-core/100W) FIO Processor Kit for HPE ProLiant DL380 Gen10 P23549-L21

Intel Xeon-Silver 4210 (2.2GHz/10-core/85W) FIO Processor Kit for HPE ProLiant DL380 Gen10 P02492-L21

### Configuration Information

Intel Xeon-Silver 4208 (2.1GHz/8-core/85W) FIO Processor Kit for HPE ProLiant DL380 Gen10 P02491-L21

#### 2<sup>nd</sup> Generation Intel Xeon-Bronze

##### Notes:

Field upgrades from 1<sup>st</sup> generation processors (x1xx) to 2<sup>nd</sup> generation processors (x2xx) not supported. All the below models do not ship with Performance Heatsink.

Intel Xeon-Bronze 3206R (1.9GHz/8-core/85W) FIO Processor Kit for HPE ProLiant DL380 Gen10 P23547-L21

Intel Xeon-Bronze 3204 (1.9GHz/6-core/85W) FIO Processor Kit for HPE ProLiant DL380 Gen10 P02489-L21

**Notes:** Processors with 130W or higher will ship with the High Performance heatsink plus SKUs 8256, 8156, 6128, 5222, 5122 as noted below. All other will processors will ship with the Standard heat sink.

#### Step 2b: Choose Memory Options

Please select one or more memory from below.

For new Gen10 memory population rule whitepaper and optimal memory performance guidelines, please go to:

<https://www.hpe.com/docs/memory-population-rules>

For Gen10 memory speed table, please go to: <https://www.hpe.com/docs/memory-speed-table>

For memory Reliability, Accessibility, Serviceability (RAS) features whitepaper like Gen10 Fast Fault Tolerance and legacy mirrored memory feature etc. please go to: <http://www.hpe.com/docs/memory-ras-feature>

##### Notes:

The maximum memory speed and capacity is a function of the memory type, memory configuration, and processor model. DDR4-2933 Memory Kits are only supported with 2nd Generation Intel Xeon Scalable Series Processors and DDR4-2666 Memory Kits are only supported with 1st Generation Intel Xeon Scalable Series Processors.

#### Registered DIMMs (RDIMMs)

HPE 8GB (1x8GB) Single Rank x8 DDR4-2933 CAS-21-21-21 Registered Smart Memory Kit P00918-B21

HPE 8GB (1x8GB) Single Rank x8 DDR4-2666 CAS-19-19-19 Registered Smart Memory Kit 815097-B21

HPE 16GB (1x16GB) Single Rank x4 DDR4-2933 CAS-21-21-21 Registered Smart Memory Kit P00920-B21

HPE 16GB (1x16GB) Single Rank x4 DDR4-2666 CAS-19-19-19 Registered Smart Memory Kit 815098-B21

HPE 16GB (1x16GB) Dual Rank x8 DDR4-2933 CAS-21-21-21 Registered Smart Memory Kit P00922-B21

HPE 16GB (1x16GB) Dual Rank x8 DDR4-2666 CAS-19-19-19 Registered Smart Memory Kit 835955-B21

HPE 32GB (1x32GB) Single Rank x4 DDR4-2933 CAS-21-21-21 Registered Memory Kit P38446-B21

HPE 32GB (1x32GB) Dual Rank x4 DDR4-2933 CAS-21-21-21 Registered Smart Memory Kit P00924-B21

HPE 32GB (1x32GB) Dual Rank x4 DDR4-2666 CAS-19-19-19 Registered Smart Memory Kit 815100-B21

HPE 64GB (1x64GB) Dual Rank x4 DDR4-2933 CAS-21-21-21 Registered Smart Memory Kit P00930-B21

#### Load Reduced DIMMs (LRDIMMs)

## Configuration Information

HPE 128GB (1x128GB) Quad Rank x4 DDR4-2933 CAS-21-21-21 Load Reduced Smart Memory Kit P11040-B21

**HPE Persistent Memory (Intel Optane)**

Intel Optane 128GB persistent memory 100 Series for HPE 835804-B21

Intel Optane 256GB persistent memory 100 Series for HPE 835807-B21

Intel Optane 512GB persistent memory 100 Series for HPE 835810-B21

**Notes:**

A maximum of 12 Intel Optane Persistent Memory for HPE supported with select 2nd Generation Intel Xeon Scalable Series Processors ONLY (82xx/62xx/52xx/4215R/4215) and can only be mixed with either RDIMMs or LRDIMMs. For configurations exceeding 1TB/socket, the "M" series (2TB/socket) or "L" series processors (4.5TB/socket) are required.

When mixing Intel Optane persistent memory with RDIMM, all RDIMM must be of same capacity and type.

For information regarding Intel Optane Persistent Memory for HPE visit: <http://www.hpe.com/info/persistentmemory>

**HPE NVDIMMs**

HPE 16GB NVDIMM Single Rank x4 DDR4-2666 Module Kit 845264-B21

**Notes:**

A maximum of 12 HPE NVDIMMs supported.

Can only be mixed with RDIMMs.

For General Server Memory and HPE NVDIMM Population Rules and Guidelines for Gen10 see details here:

<http://www.hpe.com/docs/memory-population-rules>

For details on the HPE Server Memory speed, visit: <https://www.hpe.com/docs/memory-speed-table>

To realize the performance memory capabilities listed in this document, HPE DDR4 SmartMemory is required.

For additional information, please see the [HPE DDR4 SmartMemory QuickSpecs](#).

**Step 2c: Choose Power Supplies**

Select one or two power supplies from below.

**Notes:** Mixing of 2 different power supplies is NOT allowed.

**HPE Flex Slot Power Supplies**

HPE 500W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit 865408-B21

HPE 800W Flex Slot Titanium Hot Plug Low Halogen Power Supply Kit 865438-B21

HPE 800W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit 865414-B21

HPE 800W Flex Slot -48VDC Hot Plug Low Halogen Power Supply Kit 865434-B21

HPE 800W Flex Slot Universal Hot Plug Low Halogen Power Supply Kit 865428-B21

HPE 1600W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit 830272-B21

**Step 3: Choose Additional Factory Integratable Options**

One of the following from each list may be selected if desired at time of factory integration

**HPE Security Options**

HPE iLO Common Password FIO Setting P08040-B21

**Notes:**

Replaces iLO default randomized password by an HPE defined common password. HPE highly recommends changing this password immediately after the initial onboarding process.

Customers who want to choose their own custom iLO default password should use the HPE Factory Express Integration Services

HPE Trusted Platform Module 2.0 Gen10 Option 864279-B21

## Configuration Information

**Notes:**

HPE Trusted Platform Module 2.0 option works with Gen10 servers with UEFI Mode not Legacy Mode. It is not compatible with HPE ProLiant Gen8 servers or earlier generation variants.

HPE server systems can have a TPM module (of any type) installed only once. It cannot be replaced with any other TPM module.

HPE Gen10 TPM 1.2 FIO Setting 872108-B21

**Notes:** TPM 2.0 is set as default, for 1.2 TPM setting instead, please select this option.

HPE Server Platform LDevID FIO Setting P49803-B21

HPE Server Identity LDevID FIO Setting P49814-B21

HPE Server Security Optimized Service for HPE ProLiant (R9S59A) is an optional security upgrade intended for agencies and regulated industries with enhanced security and compliance needs. Applying this option to a DL3XX Gen10/Gen10 Plus CTO server ensures it is hardened by turning on advanced safeguards in place against cyber-exploits throughout the server lifecycle. An iLO Advanced License required for High Security Mode and compatible intrusion detection device option kits are prerequisites for the full optimization service.

**Factory Instructions and Server Settings**

HPE DL38X Gen10 4 NVMe Box 1 FIO Option 878186-B21

HPE DL38X Gen10 2 NVMe FIO Option 878189-B21

**Notes:**

This is a factory integrated only option.

This will connect 2 SFF cage installed in the front of the chassis to NVMe.

HPE DL380X/Apollo 6500 Gen10 6+2 NVMe FIO Option 878192-B21

**Notes:**

This is a factory integrated only option.

Indicates the cage will also have an NVMe connection.

HPE DL38X Gen10 8 SFF Front Cage Removal FIO Option 873763-B21

**Notes:**

This is a factory integrated only option.

Will remove the Primary 8SFF cage in Box 3 of the 8SFF and replace with a Box blank.

HPE DL38X Gen10 Primary Riser Removal FIO Option 873766-B21

**Notes:**

This is a factory integrated only option.

Will remove the Primary shipping PCIe riser.

HPE Legacy FIO Mode Setting 758959-B22

**Notes:** UEFI is the default, this FIO part can be used for CTO to enable Legacy mode.

HPE Smart Memory Fast Fault Tolerance FIO Setting 875293-B21

**Notes:** Fast Fault Tolerance is a new feature in Gen10 server memory that enables the system to boot with full memory performance while monitoring for DRAM device failures.

HPE 2U Bezel Air Filter NEBS-compliant Kit P05420-B21

**HPE Converged Infrastructure Management Software**

HPE OneView for ProLiant DL Server including 3yr 24x7 Support FIO Bundle Physical 1-server LTU E5Y43A

HPE OneView w/o iLO including 3yr 24x7 Support 1-server FIO LTU P8B31A



### Configuration Information

#### vSAN ReadyNode

- 3, 6, 8 or 16 node vSAN Clusters (3 node minimum)
- HW is optimized for vSAN
- VMware vSAN Advanced LTU bundled

**Notes:** Software Requirements: VMware vSphere 6.7 Update 1, VMware vSphere with Operations Management™ 6.1 (any edition), VMware vCloud Suite 6.0 (any edition updated with 6.5) or VMware vCenter Server 6.7 Update 1.

---

**Step 4: Choose additional options for Factory Integration from Core and Additional Options sections below**

---



## Core Options

Some options may not be integrated at the factory. To ensure only valid configurations are ordered, Hewlett Packard Enterprise recommends the use of an HPE approved configurator. Contact your local sales representative for additional information.

**Notes:** The <http://www.hpe.com/info/CablingMatrixGen10> can help to explain the cable routing for each option:

HPE DL38X NVMe 8 Solid State Drive Express Bay Enablement Kit 826689-B21

**Notes:**

This option provides support for up to 8 NVMe drives, and can only be populated in Box 1, Box 2 and Box 3 of the SFF chassis, note Box 1 can only be partially populated with four drives if Box 2 and Box 3 are fully populated with NVMe drives.

The HPE DL380 Gen10 High Performance fan kit is required for NVMe support (867810-B21).

The HPE DL38X Gen10 4-port 8 NVMe SlimSAS Riser (867807-B21) is required to support this.

There are limitations on GPU support with the NVMe bay installed.

If configuration is 2x CPU + HPE DL38X NVMe 8 Solid State Drive Express Bay Enablement Kit. Then can only select 4 Port Slimline Secondary riser (873732-B21). Box3: SAS/SATA. Box2: NVMe.

HPE DL38X Gen10 Universal Media Bay Kit 826708-B21

**Notes:**

The HPE DL380 Gen10 Universal Media bay provides front Display Port and 2xUSB 2.0; plus support for 2x SFF front drives or 2 NVME front drives (826687-B21, riser required) and ODD support (Not included); and can only be located in Box1 in either an 8 SFF or 8+8 SFF model.

This is a SFF model option only.

HPE DL38X Gen10 SFF Box1/2 Cage/Backplane Kit 826691-B21

**Notes:** Supports 8 SAS/SATA SFF drives in Box 1 or 2 to a max of 24 SFF SAS/SATA front.

HPE ProLiant DL380 Gen10 2SFF Premium HDD SAS/SATA BC Front/Rear Backplane Kit P57773-B21

**Notes:**

Max = 2

Supported only with the 8SFF Basic Carriers Model-X

Requires selection of a tri-mode controller

Requires selection of 2SFF Stacked Tri Mode Cable Kit (P55469-B21).

HPE ProLiant DL380 Gen10 8SFF SAS/SATA BC Box 1-2 Backplane Kit P57774-B21

**Notes:**

Max = 2

Supported only with the 8SFF Basic Carriers Model-X

Requires selection of a tri-mode controller

If Qty 2 of this 8SFF cage is selected then High Performance Fan Kit (867810-B21) must be selected.

Requires selection of HPE ProLiant DL38x 8SFF SAS/SATA Tri-Mode Cable Kit (P55467-B21).

HPE DL38X Gen10 Premium 6 SFF SAS/SATA + 2 NVMe or 8 SFF SAS/SATA Bay Kit 826690-B21

**Notes:**

This kit can be supported in Box 1, 2 or 3 and provides support for up to 6 SAS/SATA + 2 NVMe or 8 SFF SAS/SATA drives per Box. If only populating SFF SAS/SATA, the HPE DL38X Gen10 SFF Box1/2 Cage/Backplane Kit (826691-B21) is the more appropriate option.

With NVMe drives a specific riser is required.

When adding to Box 1 the addition of the High Performance Fan kit (867810-B21) is required.

HPE DL380 Gen10 High Performance Heat Sink Kit 826706-B21

**Notes:**

Required for GPU installations.

Processor kits above 130W include a High Performance Heatsink, along with the 8156, 6128 and 5122.

This kit contains 2 High Performance Heatsinks.

HPE DL38X Gen10 High Performance Temperature Fan Kit 867810-B21

## Core Options

**Notes:**

This kit is required for specific Ambient temperature environments

This kit is also required to support GPUs configurations.

This is required for NVMe configurations.

This kit provides maximum cooling for your Server.

This kit is required when Box 1, 2 and 3 are populated.

HPE DL38X Gen10 2SFF HDD SAS/SATA Riser Kit 826688-B21

**Notes:**

2 SFF in the rear is only supported with a 24 SFF model or 12 LFF model.

In the rear this leaves 1x16 slot accessible.

Rear drives require the addition of the High Performance Fan kit (867810-B21).

Supports UFF SCM drives.

HPE DL38X Gen10 2SFF Premium HDD Front NVMe or Front/Rear SAS/SATA Kit 826687-B21

**Notes:**

HPE DL38X Gen10 Universal Media Bay Kit (826708-B21).

NVMe drives require the addition of the High Performance Fan kit (867810-B21).

NVMe drives require the addition of an NVMe capable riser.

Drive cage can be used in the rear of the chassis, but will not support NVMe drives rear.

Supports UFF SCM drives.

HPE DL38X Gen10 8LFF Front 2NVMe HDD Bay Kit 873781-B21

**Notes:**

Supports 2 NVMe in the Universal Media bay (included) on the 8 LFF model.

For support of the 2 NVMe drives this will require the addition of the HPE DL38X Gen10 x8/x8/x8 1-port 2 NVMe SlimSAS Riser (867806-B21); or the HPE DL38X Gen10 2-port 4 NVMe SlimSAS Riser (867808-B21).

NVMe drives require the addition of the High Performance Fan kit (867810-B21).

HPE DL38X Gen10 12Gb SAS Expander Card Kit with Cables 870549-B21

**Notes:** SAS expander to enable 24 SFF field upgrade.

HPE DL380 Gen10 SFF Systems Insight Display Kit 826703-B21

**Notes:**

Systems Insight Display does not ship standard but is available as a Factory Integrated or field upgrade option.

Primary population in slot 3 of the primary riser.

HPE DL3XX Gen10 Rear Serial Cable and Enablement Kit 873770-B21

HPE DL38X Gen10 8LFF Front 2SFF SAS/SATA HDD Kit 867805-B21

**Notes:** HPE ProLiant DL380 Gen10 8LFF with Universal Media Bay Configure-to-order Server (868706-B21).

HPE 2U Bezel Air Filter NEBS-compliant Kit P05420-B21

## HPE Processors

## Processor Option Kits

2<sup>nd</sup> Generation Intel Xeon-Platinum**Notes:**

Field upgrades from 1<sup>st</sup> generation processors (x1xx) to 2<sup>nd</sup> generation processors (x2xx) not supported.

All the below models ship with Performance Heatsink unless otherwise noted.

Intel Xeon-Platinum 8280L (2.7GHz/28-core/205W) Processor Kit for HPE ProLiant DL380 Gen10 P02540-B21

Intel Xeon-Platinum 8280 (2.7GHz/28-core/205W) Processor Kit for HPE ProLiant DL380 Gen10 P02527-B21

## Core Options

Intel Xeon-Platinum 8276L (2.2GHz/28-core/165W) Processor Kit for HPE ProLiant DL380 Gen10	P02539-B21
Intel Xeon-Platinum 8276 (2.2GHz/28-core/165W) Processor Kit for HPE ProLiant DL380 Gen10	P02526-B21
Intel Xeon-Platinum 8270 (2.7GHz/26-core/205W) Processor Kit for HPE ProLiant DL380 Gen10	P02525-B21
Intel Xeon-Platinum 8268 (2.9GHz/24-core/205W) Processor Kit for HPE ProLiant DL380 Gen10	P02524-B21
Intel Xeon-Platinum 8260L (2.4GHz/24-core/165W) Processor Kit for HPE ProLiant DL380 Gen10	P02538-B21
Intel Xeon-Platinum 8260Y (2.4GHz/24-20-16-core/165W) Processor Kit for HPE ProLiant DL380 Gen10	P02508-B21
Intel Xeon-Platinum 8260 (2.4GHz/24-core/165W) Processor Kit for HPE ProLiant DL380 Gen10	P02521-B21
Intel Xeon-Platinum 8256 (3.8GHz/4-core/105W) Processor Kit for HPE ProLiant DL380 Gen10	P02519-B21
Intel Xeon-Platinum 8253 (2.2GHz/16-core/125W) Processor Kit for HPE ProLiant DL380 Gen10	P02518-B21

**Notes:** Do not ship with Performance Heatsink.

**2<sup>nd</sup> Generation Intel Xeon-Gold****Notes:**

Field upgrades from 1<sup>st</sup> generation processors (x1xx) to 2<sup>nd</sup> generation processors (x2xx) not supported. All the below models ship with Performance Heatsink unless otherwise noted.

Intel Xeon-Gold 6262V (1.9GHz/24-core/135W) Processor Kit for HPE ProLiant DL380 Gen10	P11822-B21
Intel Xeon-Gold 6258R (2.7GHz/28-core/205W) Processor Kit for HPE ProLiant DL380 Gen10	P24474-B21
Intel Xeon-Gold 6256 (3.6GHz/12-core/205W) Processor Kit for HPE ProLiant DL380 Gen10	P24476-B21

**Notes:**

Requires high performance fan kit (867810-B21), unless 24SFF or 12LFF server models are selected, which provide high performance fans as the default.

Not supported with NVMe SSDs, nor 2SFF HDD kits (826687-B21; 826688-B21) installed in rear, nor GPUs, nor 4LFF mid-tray. Detailed configuration and facilities requirements can be found under "Intel Xeon Scalable Series 6250, 6250L, and 6256 Configuration and Facilities Requirements Matrix" with this document.

Intel Xeon-Gold 6254 (3.1GHz/18-core/200W) Processor Kit for HPE ProLiant DL380 Gen10	P02517-B21
Intel Xeon-Gold 6252N (2.3GHz/24-core/150W) Processor Kit for HPE ProLiant DL380 Gen10	P11829-B21
Intel Xeon-Gold 6252 (2.1GHz/24-core/150W) Processor Kit for HPE ProLiant DL380 Gen10	P02516-B21
Intel Xeon-Gold 6250L (3.9GHz/8-core/185W) Processor Kit for HPE ProLiant DL380 Gen10	P28387-B21

**Notes:**

Requires high performance fan kit (867810-B21), unless 24SFF or 12LFF server models are selected, which provide high performance fans as the default.

Not supported with NVMe SSDs, nor 2SFF HDD kits (826687-B21; 826688-B21) installed in rear, nor GPUs, nor 4LFF mid-tray. Detailed configuration and facilities requirements can be found under "Intel Xeon Scalable Series 6250, 6250L, and 6256 Configuration and Facilities Requirements Matrix" with this document.

Intel Xeon-Gold 6250 (3.9GHz/8-core/185W) Processor Kit for HPE ProLiant DL380 Gen10	P24475-B21
--	------------

**Notes:**

Requires high performance fan kit (867810-B21), unless 24SFF or 12LFF server models are selected, which provide high performance fans as the default.

Not supported with NVMe SSDs, nor 2SFF HDD kits (826687-B21; 826688-B21) installed in rear, nor GPUs,

### Core Options

nor 4LFF mid-tray. Detailed configuration and facilities requirements can be found under "Intel Xeon Scalable Series 6250, 6250L, and 6256 Configuration and Facilities Requirements Matrix" with this document.

Intel Xeon-Gold 6248R (3.0GHz/24-core/205W) Processor Kit for HPE ProLiant DL380 Gen10	P24473-B21
Intel Xeon-Gold 6248 (2.5GHz/20-core/150W) Processor Kit for HPE ProLiant DL380 Gen10	P02514-B21
Intel Xeon-Gold 6246R (3.4GHz/16-core/205W) Processor Kit for HPE ProLiant DL380 Gen10	P24472-B21
Intel Xeon-Gold 6246 (3.3GHz/12-core/165W) Processor Kit for HPE ProLiant DL380 Gen10	P15758-B21
Intel Xeon-Gold 6244 (3.6GHz/8-core/150W) Processor Kit for HPE ProLiant DL380 Gen10	P02512-B21
Intel Xeon-Gold 6242R (3.1GHz/20-core/205W) Processor Kit for HPE ProLiant DL380 Gen10	P24471-B21
Intel Xeon-Gold 6242 (2.8GHz/16-core/150W) Processor Kit for HPE ProLiant DL380 Gen10	P02510-B21
Intel Xeon-Gold 6240R (2.4GHz/24-core/165W) Processor Kit for HPE ProLiant DL380 Gen10	P24470-B21
Intel Xeon-Gold 6240L (2.6GHz/18-core/150W) Processor Kit for HPE ProLiant DL380 Gen10	P02537-B21
Intel Xeon-Gold 6240 (2.6GHz/18-core/150W) Processor Kit for HPE ProLiant DL380 Gen10	P02509-B21
Intel Xeon-Gold 6240Y (2.6GHz/18-14-8-core/150W) Processor Kit for HPE ProLiant DL380 Gen10	P02507-B21
Intel Xeon-Gold 6238R (2.2GHz/28-core/165W) Processor Kit for HPE ProLiant DL380 Gen10	P24469-B21
Intel Xeon-Gold 6238L (2.1GHz/22-core/140W) Processor Kit for HPE ProLiant DL380 Gen10	P02536-B21
Intel Xeon-Gold 6238 (2.1GHz/22-core/140W) Processor Kit for HPE ProLiant DL380 Gen10	P02504-B21
Intel Xeon-Gold 6234 (3.3GHz/8-core/130W) Processor Kit for HPE ProLiant DL380 Gen10	P02503-B21
Intel Xeon-Gold 6230R (2.1GHz/26-core/150W) Processor Kit for HPE ProLiant DL380 Gen10	P24468-B21
Intel Xeon-Gold 6230 (2.1GHz/20-core/125W) Processor Kit for HPE ProLiant DL380 Gen10	P02502-B21
<b>Notes:</b> Do not ship with Performance Heatsink.	
Intel Xeon-Gold 6230N (2.3GHz/20-core/125W) Processor Kit for HPE ProLiant DL380 Gen10	P11830-B21
<b>Notes:</b> Do not ship with Performance Heatsink.	
Intel Xeon-Gold 6226R (2.9GHz/16-core/150W) Processor Kit for HPE ProLiant DL380 Gen10	P24467-B21
Intel Xeon-Gold 6226 (2.7GHz/12-core/125W) Processor Kit for HPE ProLiant DL380 Gen10	P02501-B21
<b>Notes:</b> Do not ship with Performance Heatsink.	
Intel Xeon-Gold 6222V (1.8GHz/20-core/115W) Processor Kit for HPE ProLiant DL380 Gen10	P11823-B21
<b>Notes:</b> Do not ship with Performance Heatsink.	
Intel Xeon-Gold 6212U (2.4GHz/24-core/165W) Processor Kit for HPE ProLiant DL380 Gen10	P11825-B21
<b>Notes:</b> 2-processor configurations not supported with this processor; secondary and tertiary risers not supported Field upgrades from 1 <sup>st</sup> generation processors (x1xx) to 2 <sup>nd</sup> generation processors (x2xx) not supported. This standalone option kit is intended to upgrade a system originally installed with a 2 <sup>nd</sup> generation Intel Xeon Scalable Series processor.	
Intel Xeon-Gold 6210U (2.5GHz/20-core/150W) Processor Kit for HPE ProLiant DL380 Gen10	P11826-B21
<b>Notes:</b> 2-processor configurations NOT supported with this processor; secondary and tertiary risers not supported Field upgrades from 1 <sup>st</sup> generation processors (x1xx) to 2 <sup>nd</sup> generation processors (x2xx) not supported. This standalone option kit is intended to upgrade a system originally installed with a 2 <sup>nd</sup> generation Intel Xeon Scalable Series processor.	
Intel Xeon-Gold 6209U (2.1GHz/20-core/125W) Processor Kit for HPE ProLiant DL380 Gen10	P11827-B21
<b>Notes:</b> 2-processor configurations NOT supported with this processor; secondary and tertiary risers not supported Field upgrades from 1 <sup>st</sup> generation processors (x1xx) to 2 <sup>nd</sup> generation processors (x2xx) not supported. This standalone option kit is intended to upgrade a system originally installed with a 2 <sup>nd</sup> generation Intel Xeon Scalable Series processor. Do not ship with Performance Heatsink.	

## Core Options

Intel Xeon-Gold 6208U (2.9GHz/16-core/150W) Processor Kit for HPE ProLiant DL380 Gen10 P24477-B21

**Notes:**

2-processor configurations NOT supported with this processor; secondary and tertiary risers not supported  
Field upgrades from 1<sup>st</sup> generation processors (x1xx) to 2<sup>nd</sup> generation processors (x2xx) not supported.

This standalone option kit is intended to upgrade a system originally installed with a 2<sup>nd</sup> generation Intel Xeon Scalable Series processor.

Intel Xeon-Gold 5222 (3.8GHz/4-core/105W) Processor Kit for HPE ProLiant DL380 Gen10 P02500-B21

Intel Xeon-Gold 5220S (2.7GHz/18-core/125W) Processor Kit for HPE ProLiant DL380 Gen10 P11824-B21

**Notes:** Do not ship with Performance Heatsink.

Intel Xeon-Gold 5220R (2.2GHz/24-core/150W) Processor Kit for HPE ProLiant DL380 Gen10 P23553-B21

Intel Xeon-Gold 5220 (2.2GHz/18-core/125W) Processor Kit for HPE ProLiant DL380 Gen10 P02499-B21

**Notes:** Do not ship with Performance Heatsink.

Intel Xeon-Gold 5218R (2.1GHz/20-core/125W) Processor Kit for HPE ProLiant DL380 Gen10 P24466-B21

**Notes:** Do not ship with Performance Heatsink.

Intel Xeon-Gold 5218B (2.3GHz/16-core/125W) Processor Kit for HPE ProLiant DL380 Gen10 P12513-B21

**Notes:**

5218B has consistent features with the 5218 processor but from a different die. Mixing both 5218B & 5218 in a system is not supported

Do not ship with Performance Heatsink.

Intel Xeon-Gold 5218N (2.3GHz/16-core/110W) Processor Kit for HPE ProLiant DL380 Gen10 P11831-B21

**Notes:** Do not ship with Performance Heatsink.

Intel Xeon-Gold 5218 (2.3GHz/16-core/125W) Processor Kit for HPE ProLiant DL380 Gen10 P02498-B21

**Notes:** Do not ship with Performance Heatsink.

Intel Xeon-Gold 5217 (3.0GHz/8-core/115W) Processor Kit for HPE ProLiant DL380 Gen10 P02497-B21

**Notes:** Do not ship with Performance Heatsink.

Intel Xeon-Gold 5215L (2.5GHz/10-core/85W) Processor Kit for HPE ProLiant DL380 Gen10 P02533-B21

**Notes:** Do not ship with Performance Heatsink.

Intel Xeon-Gold 5215 (2.5GHz/10-core/85W) Processor Kit for HPE ProLiant DL380 Gen10 P02496-B21

**Notes:** Do not ship with Performance Heatsink.

**2nd Generation Intel Xeon-Silver****Notes:**

Field upgrades from 1<sup>st</sup> generation processors (x1xx) to 2<sup>nd</sup> generation processors (x2xx) not supported.

All the below models do not ship with Performance Heatsink unless otherwise noted

Intel Xeon-Silver 4216 (2.1GHz/16-core/100W) Processor Kit for HPE ProLiant DL380 Gen10 P02495-B21

Intel Xeon-Silver 4215R (3.2GHz/8-core/130W) Processor Kit for HPE ProLiant DL380 Gen10 P24465-B21

**Notes:** Ships with Performance Heatsink.

Intel Xeon-Silver 4215 (2.5GHz/8-core/85W) Processor Kit for HPE ProLiant DL380 Gen10 P02494-B21

Intel Xeon-Silver 4214Y (2.2GHz/12-10-8-core/85W) Processor Kit for HPE ProLiant DL380 Gen10 P02506-B21

Intel Xeon-Silver 4214R (2.4GHz/12-core/100W) Processor Kit for HPE ProLiant DL380 Gen10 P23550-B21

Intel Xeon-Silver 4214 (2.2GHz/12-core/85W) Processor Kit for HPE ProLiant DL380 Gen10 P02493-B21

Intel Xeon-Silver 4210R (2.4GHz/10-core/100W) Processor Kit for HPE ProLiant DL380 Gen10 P23549-B21

Intel Xeon-Silver 4210 (2.2GHz/10-core/85W) Processor Kit for HPE ProLiant DL380 Gen10 P02492-B21

Intel Xeon-Silver 4208 (2.1GHz/8-core/85W) Processor Kit for HPE ProLiant DL380 Gen10 P02491-B21



### Core Options

#### 2<sup>nd</sup> Generation Intel Xeon-Bronze

##### Notes:

Field upgrades from 1<sup>st</sup> generation processors (x1xx) to 2<sup>nd</sup> generation processors (x2xx) not supported.  
All the below models do not ship with Performance Heatsink.

Intel Xeon-Bronze 3206R (1.9GHz/8-core/85W) Processor Kit for HPE ProLiant DL380 Gen10	P23547-B21
Intel Xeon-Bronze 3204 (1.9GHz/6-core/85W) Processor Kit for HPE ProLiant DL380 Gen10	P02489-B21

##### Notes:

Up to two processors supported.  
HT indicates that the processor model supports Intel® Hyper-Threading Technology.  
Turbo2: Intel® Turbo Boost Technology 2.0 provides more computing power when you need it with performance that adapts to spikes in your workload and delivers more performance upside than previous generation turbo technology.  
DDR4 speed is the maximum memory speed of the processor. Actual memory speed may depend on the quantity and type of DIMMs installed.  
The xxxxx-L21 is the first processor shipped, the xxxxx-B21 is the 2nd processor and ships with 2 additional fans for factory of field installation.  
Maximum memory per socket depends on the processor selected.  
Processors above 130W use a High Performance Heatsink, along with the 8256, 8156, 6128, 5222, and 5122.

### Memory Selection

To streamline the configuration process for HPE ProLiant Gen10 servers and to provide the best product availability, HPE recommends memory from the list located here:

<http://www.hpe.com/products/recommend>.

Best product availability is limited to US, Canada, and Latin America at this time.

##### Notes:

Maximum memory capacity and speed per processor is dependent on processor model selection or limitation.  
DDR4-2933 Memory Kits are only supported with 2nd Generation Intel Xeon Scalable Series Processors and DDR4-2666 Memory Kits are only supported with 1<sup>st</sup> Generation Intel Xeon Scalable Series Processors.

### HPE DDR4 Memory

#### Registered DIMMs (RDIMMs)

HPE 8GB (1x8GB) Single Rank x8 DDR4-2933 CAS-21-21-21 Registered Smart Memory Kit	P00918-B21
HPE 8GB (1x8GB) Single Rank x8 DDR4-2666 CAS-19-19-19 Registered Smart Memory Kit	815097-B21
HPE 16GB (1x16GB) Single Rank x4 DDR4-2933 CAS-21-21-21 Registered Smart Memory Kit	P00920-B21
HPE 16GB (1x16GB) Single Rank x4 DDR4-2666 CAS-19-19-19 Registered Smart Memory Kit	815098-B21
HPE 16GB (1x16GB) Dual Rank x8 DDR4-2933 CAS-21-21-21 Registered Smart Memory Kit	P00922-B21
HPE 16GB (1x16GB) Dual Rank x8 DDR4-2666 CAS-19-19-19 Registered Smart Memory Kit	835955-B21
HPE 32GB (1x32GB) Single Rank x4 DDR4-2933 CAS-21-21-21 Registered Memory Kit	P38446-B21
HPE 32GB (1x32GB) Dual Rank x4 DDR4-2933 CAS-21-21-21 Registered Smart Memory Kit	P00924-B21
HPE 32GB (1x32GB) Dual Rank x4 DDR4-2666 CAS-19-19-19 Registered Smart Memory Kit	815100-B21

## Core Options

HPE 64GB (1x64GB) Dual Rank x4 DDR4-2933 CAS-21-21-21 Registered Smart Memory Kit P00930-B21

**Notes:** For configurations exceeding 1TB/socket, the "M" series (2TB/socket) or "L" series processors (4.5TB/socket) are required.

**Load Reduced DIMMs (LRDIMMs)**

HPE 128GB (1x128GB) Quad Rank x4 DDR4-2933 CAS-21-21-21 Load Reduced Smart Memory Kit P11040-B21

**Notes:**

Memory DIMM availability with a server platform is dependent upon completion of certification testing. The maximum memory speed is a function of the memory type, memory configuration, and processor model.

Mixing of RDIMM and LRDIMM is not supported.

For configurations exceeding 1TB/socket, the "M" series (2TB/socket) or "L" series processors (4.5TB/socket) are required.

**Intel Optane persistent memory for HPE**

Intel Optane 128GB persistent memory 100 Series for HPE 835804-B21

Intel Optane 256GB persistent memory 100 Series for HPE 835807-B21

Intel Optane 512GB persistent memory 100 Series for HPE 835810-B21

**Notes:**

A maximum of 12 Intel Optane Persistent Memory for HPE supported with select 2nd Generation Intel Xeon Scalable Series Processors ONLY (82xx/62xx/52xx/4215R/4215) and can only be mixed with either RDIMMs or LRDIMMs.

For configurations exceeding 1TB/socket, the "M" series (2TB/socket) or "L" series processors (4.5TB/socket) are required.

When mixing Intel Optane persistent memory with RDIMM, all RDIMM must be of same capacity and type.

For information regarding Intel Optane Persistent Memory for HPE visit:

<http://www.hpe.com/info/persistentmemory>

**HPE NVDIMMs**

HPE 16GB NVDIMM Single Rank x4 DDR4-2666 Module Kit 845264-B21

**Notes:**

A maximum of 12 HPE NVDIMMs supported with 1<sup>st</sup> Generation Intel Xeon Scalable Processors and can only be mixed with RDIMMs.

Can only be mixed with RDIMMs.

For General Server Memory and HPE NVDIMM Population Rules and Guidelines for Gen10 see details here:

<http://www.hpe.com/docs/memory-population-rules>

**HPE DDR-4 Blank Kit**

HPE DDR4 DIMM Blank Kit P07818-B21

**HPE Optical Drives**

HPE 9.5mm SATA DVD-ROM Optical Drive 726536-B21

**Notes:** HPE DL38X Gen10 Universal Media Bay Kit (826708-B21) is required for this option on a SFF model. No support in 12 LFF or 24 SFF models.

HPE 9.5mm SATA DVD-RW Optical Drive 726537-B21

**Notes:** HPE DL38X Gen10 Universal Media Bay Kit (826708-B21) is required for this option on a SFF model. No support in 12 LFF or 24 SFF models.

HPE Mobile USB DVD-RW Optical Drive 701498-B21



## Core Options

**Notes:** This is only supported on USB 3.0 ports.

**Media Bay Kits**

HPE DL38X Gen10 Universal Media Bay Kit 826708-B21

**Notes:**

The HPE DL380 Gen10 Universal Media bay provides front Display Port and 2xUSB 2.0; plus support for 2x SFF front drives or 2 NVME front drives (826687-B21, riser required) and ODD support (Not included); and can only be located in Box1 in either an 8 SFF or 8+8 SFF model.

This is a SFF model option only.

**HPE Hard Disk Drives****Enterprise - 12G SAS - Basic Carrier SFF Drives**

HPE 2.4TB SAS 12G Mission Critical 10K SFF BC 3-year Warranty 512e Multi Vendor HDD P28352-B21

HPE 1.8TB SAS 12G Mission Critical 10K SFF BC 3-year Warranty 512e Multi Vendor HDD P53562-B21

HPE 1.2TB SAS 12G Mission Critical 10K SFF BC 3-year Warranty Multi Vendor HDD P28586-B21

HPE 900GB SAS 12G Mission Critical 15K SFF BC 3-year Warranty Multi Vendor HDD P40432-B21

HPE 600GB SAS 12G Mission Critical 15K SFF BC 3-year Warranty Multi Vendor HDD P53560-B21

HPE 600GB SAS 12G Mission Critical 10K SFF BC 3-year Warranty Multi Vendor HDD P53561-B21

HPE 300GB SAS 12G Mission Critical 15K SFF BC 3-year Warranty Multi Vendor HDD P28028-B21

HPE 300GB SAS 12G Mission Critical 10K SFF BC 3-year Warranty Multi Vendor HDD P40430-B21

**Notes:** Supported on Basic Carrier Model-X only.

**Enterprise - 12G SAS - SFF Drives**

HPE 2.4TB SAS 12G Mission Critical 10K SFF SC 3-year Warranty 512e Multi Vendor HDD 881457-B21

HPE 1.8TB SAS 12G Mission Critical 10K SFF SC 3-year Warranty 512e Multi Vendor HDD 872481-B21

HPE 1.2TB SAS 12G Mission Critical 10K SFF SC 3-year Warranty Multi Vendor HDD 872479-B21

HPE 900GB SAS 12G Mission Critical 15K SFF SC 3-year Warranty Multi Vendor HDD 870759-B21

HPE 600GB SAS 12G Mission Critical 15K SFF SC 3-year Warranty Multi Vendor HDD 870757-B21

HPE 600GB SAS 12G Mission Critical 10K SFF SC 3-year Warranty Multi Vendor HDD 872477-B21

HPE 300GB SAS 12G Mission Critical 15K SFF SC 3-year Warranty Multi Vendor HDD 870753-B21

HPE 300GB SAS 12G Mission Critical 10K SFF SC 3-year Warranty Multi Vendor HDD 872475-B21

**Midline - 12G SAS - Basic Carrier SFF Drives**

HPE 2TB SAS 12G Business Critical 7.2K SFF BC 1-year Warranty 512e HDD P28505-B21

HPE 1TB SAS 12G Business Critical 7.2K SFF BC 1-year Warranty HDD P53563-B21

**Notes:** Supported on Basic Carrier Model-X only.

**Midline - 12G SAS - SFF Drives**

HPE 2TB SAS 12G Business Critical 7.2K SFF SC 1-year Warranty 512e HDD 765466-B21

HPE 1TB SAS 12G Business Critical 7.2K SFF SC 1-year Warranty HDD 832514-B21

**Midline - 6G SATA - SFF Drives**

HPE 2TB SATA 6G Business Critical 7.2K SFF SC 1-year Warranty 512e HDD 765455-B21

HPE 1TB SATA 6G Business Critical 7.2K SFF SC 1-year Warranty HDD 655710-B21

**Midline - 12G SAS - LFF Drives**

## Core Options

HPE 20TB SAS 12G Business Critical 7.2K LFF SC 1-year Warranty Helium 512e ISE Multi Vendor HDD	P53552-B21
HPE 16TB SAS 12G Business Critical 7.2K LFF SC 1-year Warranty Helium 512e ISE Multi Vendor HDD	P23863-B21
HPE 14TB SAS 12G Business Critical 7.2K LFF SC 1-year Warranty Helium 512e Multi Vendor HDD	P09153-B21
HPE 12TB SAS 12G Business Critical 7.2K LFF SC 1-year Warranty Helium 512e Multi Vendor HDD	881779-B21
HPE 10TB SAS 12G Business Critical 7.2K LFF SC 1-year Warranty 512e ISE Multi Vendor HDD	P53558-B21
HPE 10TB SAS 12G Business Critical 7.2K LFF SC 1-year Warranty Helium 512e Multi Vendor HDD	857644-B21
HPE 8TB SAS 12G Business Critical 7.2K LFF SC 1-year Warranty 512e Multi Vendor HDD	819201-B21
HPE 6TB SAS 12G Business Critical 7.2K LFF SC 1-year Warranty 512e Multi Vendor HDD	861754-B21
HPE 4TB SAS 12G Business Critical 7.2K LFF SC 1-year Warranty Multi Vendor HDD	872487-B21
HPE 2TB SAS 12G Business Critical 7.2K LFF SC 1-year Warranty Multi Vendor HDD	872485-B21

**Midline - 6G SATA - LFF Drives**

HPE 20TB SATA 6G Business Critical 7.2K LFF SC 1-year Warranty Helium 512e ISE Multi Vendor HDD	P53555-B21
HPE 16TB SATA 6G Business Critical 7.2K LFF SC 1-year Warranty Helium 512e ISE Multi Vendor HDD	P23857-B21
HPE 14TB SATA 6G Business Critical 7.2K LFF SC 1-year Warranty Helium 512e Multi Vendor HDD	P09163-B21
HPE 12TB SATA 6G Business Critical 7.2K LFF SC 1-year Warranty Helium 512e Multi Vendor HDD	881785-B21
HPE 10TB SATA 6G Business Critical 7.2K LFF SC 1-year Warranty 512e ISE Multi Vendor HDD	P53559-B21
HPE 10TB SATA 6G Business Critical 7.2K LFF SC 1-year Warranty Helium 512e Multi Vendor HDD	857648-B21
HPE 8TB SATA 6G Business Critical 7.2K LFF SC 1-year Warranty 512e Multi Vendor HDD	819203-B21
HPE 6TB SATA 6G Business Critical 7.2K LFF SC 1-year Warranty 512e Multi Vendor HDD	861750-B21
HPE 4TB SATA 6G Business Critical 7.2K LFF SC 1-year Warranty Multi Vendor HDD	872491-B21
HPE 2TB SATA 6G Business Critical 7.2K LFF SC 1-year Warranty Multi Vendor HDD	872489-B21
HPE 1TB SATA 6G Business Critical 7.2K LFF SC 1-year Warranty Multi Vendor HDD	861691-B21

**SSD Selection**

For SSD selection guidance, please visit <https://ssd.hpe.com/>

**Read Intensive - 12G SAS - SFF - Basic Carrier SSD**

HPE 3.84TB SAS 24G Read Intensive SFF BC Multi Vendor SSD	P49035-B21
HPE 3.84TB SAS 12G Read Intensive SFF BC Value SAS Multi Vendor SSD	P40508-B21
HPE 1.92TB SAS 12G Read Intensive SFF BC Value SAS Multi Vendor SSD	P40507-B21

**Notes:** Supported on Basic Carrier Model-X only.

**Read Intensive - 12G SAS - SFF - SC Value SAS Digitally Signed Firmware SSD**

## Core Options

HPE 15.36TB SAS 12G Read Intensive SFF SC Multi Vendor SSD	P49044-B21
HPE 7.68TB SAS 12G Read Intensive SFF SC Value SAS Multi Vendor SSD	P37003-B21
HPE 7.68TB SAS 12G Read Intensive SFF SC Multi Vendor SSD	P49039-B21
HPE 3.84TB SAS 12G Read Intensive SFF SC Value SAS Multi Vendor SSD	P37001-B21
HPE 3.84TB SAS 12G Read Intensive SFF SC Multi Vendor SSD	P49034-B21
HPE 1.92TB SAS 12G Read Intensive SFF SC Value SAS Multi Vendor SSD	P36999-B21
HPE 1.92TB SAS 12G Read Intensive SFF SC Multi Vendor SSD	P49030-B21
HPE 960GB SAS 12G Read Intensive SFF SC Value SAS Multi Vendor SSD	P36997-B21
HPE 960GB SAS 12G Read Intensive SFF SC Multi Vendor SSD	P49028-B21

**Write Intensive - 12G SAS - SFF - Solid State Drives**

HPE 1.6TB SAS 12G Write Intensive SFF SC PM6 SSD	P26376-B21
HPE 800GB SAS 12G Write Intensive SFF SC PM6 SSD	P26372-B21
HPE 400GB SAS 12G Write Intensive SFF SC PM6 SSD	P26295-B21

**Mixed Use - 12G SAS - Basic Carrier SFF SSD**

HPE 6.4TB SAS 24G Mixed Use SFF BC Multi Vendor SSD	P49057-B21
HPE 3.2TB SAS 24G Mixed Use SFF BC Multi Vendor SSD	P49053-B21
HPE 1.6TB SAS 24G Mixed Use SFF BC Multi Vendor SSD	P49049-B21
HPE 800GB SAS 24G Mixed Use SFF BC Multi Vendor SSD	P49047-B21

**Notes:** Supported on Basic Carrier Model-X only.

**Mixed Use - 12G SAS - SFF - Basic Carrier Value SAS Digitally Signed Firmware SSD**

HPE 3.84TB SAS 12G Mixed Use SFF BC Value SAS Multi Vendor SSD	P40512-B21
HPE 1.92TB SAS 12G Mixed Use SFF BC Value SAS Multi Vendor SSD	P40511-B21
HPE 960GB SAS 12G Mixed Use SFF BC Value SAS Multi Vendor SSD	P40510-B21

**Notes:** Supported on Basic Carrier Model-X only.

**Mixed Use - 12G SAS - SFF - SC Value SAS Digitally Signed Firmware SSD**

HPE 6.4TB SAS 12G Mixed Use SFF SC Multi Vendor SSD	P49056-B21
HPE 3.84TB SAS 12G Mixed Use SFF SC Value SAS Multi Vendor SSD	P37017-B21
HPE 3.2TB SAS 12G Mixed Use SFF SC Multi Vendor SSD	P49052-B21
HPE 1.92TB SAS 12G Mixed Use SFF SC Value SAS Multi Vendor SSD	P37011-B21
HPE 1.6TB SAS 12G Mixed Use SFF SC Multi Vendor SSD	P49048-B21
HPE 960GB SAS 12G Mixed Use SFF SC Value SAS Multi Vendor SSD	P37005-B21
HPE 800GB SAS 12G Mixed Use SFF SC Multi Vendor SSD	P49046-B21

**Read Intensive - 6G SATA - Basic Carrier SFF - Solid State Drives**

HPE 3.84TB SATA 6G Read Intensive SFF BC Multi Vendor SSD	P40500-B21
HPE 1.92TB SATA 6G Read Intensive SFF BC Multi Vendor SSD	P40499-B21
HPE 960GB SATA 6G Read Intensive SFF BC Multi Vendor SSD	P40498-B21
HPE 480GB SATA 6G Read Intensive SFF BC Multi Vendor SSD	P40497-B21
HPE 240GB SATA 6G Read Intensive SFF BC Multi Vendor SSD	P40496-B21

**Notes:** Supported on Basic Carrier Model-X only.

**Read Intensive - 6G SATA - SFF - Solid State Drives**

HPE 7.68TB SATA 6G Read Intensive SFF SC Multi Vendor SSD	P18430-B21
HPE 3.84TB SATA 6G Read Intensive SFF SC Multi Vendor SSD	P18428-B21
HPE 3.84TB SATA 6G Read Intensive SFF SC S4520 SSD	P47321-B21
HPE 3.84TB SATA 6G Read Intensive SFF SC PM893 SSD	P47813-B21

## Core Options

HPE 1.92TB SATA 6G Read Intensive SFF SC Multi Vendor SSD	P18426-B21
HPE 1.92TB SATA 6G Read Intensive SFF SC S4520 SSD	P47319-B21
HPE 1.9TB SATA 6G Read Intensive SFF SC PM893 SSD	P47812-B21
HPE 960GB SATA 6G Read Intensive SFF SC Multi Vendor SSD	P18424-B21
HPE 960GB SATA 6G Read Intensive SFF SC PM893 SSD	P47811-B21
HPE 480GB SATA 6G Read Intensive SFF SC Multi Vendor SSD	P18422-B21
HPE 480GB SATA 6G Read Intensive SFF SC PM893 SSD	P47810-B21
HPE 240GB SATA 6G Read Intensive SFF SC Multi Vendor SSD	P18420-B21

**Mixed Use - 6G SATA - Basic Carrier SFF - Solid State Drives**

HPE 3.84TB SATA 6G Mixed Use SFF BC Multi Vendor SSD	P40505-B21
HPE 1.92TB SATA 6G Mixed Use SFF BC Multi Vendor SSD	P40504-B21
HPE 960GB SATA 6G Mixed Use SFF BC Multi Vendor SSD	P40503-B21
HPE 480GB SATA 6G Mixed Use SFF BC Multi Vendor SSD	P40502-B21

**Notes:** Supported on Basic Carrier Model-X only.

**Mixed Use - 6G SATA - SFF - Solid State Drives**

HPE 3.84TB SATA 6G Mixed Use SFF SC Multi Vendor SSD	P18438-B21
HPE 3.84TB SATA 6G Mixed Use SFF SC S4620 SSD	P47326-B21
HPE 1.92TB SATA 6G Mixed Use SFF SC Multi Vendor SSD	P18436-B21
HPE 1.92TB SATA 6G Mixed Use SFF SC S4620 SSD	P47325-B21
HPE 1.92TB SATA 6G Mixed Use SFF SC PM897 SSD	P47816-B21
HPE 960GB SATA 6G Mixed Use SFF SC Multi Vendor SSD	P18434-B21
HPE 960GB SATA 6G Mixed Use SFF SC PM897 SSD	P47815-B21
HPE 480GB SATA 6G Mixed Use SFF SC Multi Vendor SSD	P18432-B21
HPE 480GB SATA 6G Mixed Use SFF SC S4620 SSD	P47323-B21
HPE 480GB SATA 6G Mixed Use SFF SC PM897 SSD	P47814-B21

**Very Read Optimized - QLC-NAND SATA - SFF - Solid State Drives**

HPE 7.68TB SATA 6G Very Read Optimized SFF SC 5210 SSD	P23493-B21
--	------------

**Read Intensive - 12G SAS - LFF - SC Value SAS Digitally Signed Firmware SSD**

HPE 7.68TB SAS 24G Read Intensive LFF SCC Multi Vendor SSD	P49038-B21
--	------------

**Mixed Use - 12G SAS - LFF - SC Value SAS Digitally Signed Firmware SSD**

HPE 1.92TB SAS 12G Mixed Use LFF SCC Value SAS Multi Vendor SSD	P37013-B21
---	------------

**Read Intensive - 6G SATA - LFF - Solid State Drives**

HPE 480GB SATA 6G Read Intensive LFF SCC Multi Vendor SSD	P47807-B21
---	------------

**Mixed Use - 6G SATA - LFF - Solid State Drives**

HPE 960GB SATA 6G Mixed Use LFF SCC Multi Vendor SSD	P47419-B21
--	------------

**Read Intensive - 6G SATA - M.2 - Solid State Media (2280 type)**

HPE 480GB SATA 6G Read Intensive M.2 Multi Vendor SSD	P47818-B21
HPE 240GB SATA 6G Read Intensive M.2 Multi Vendor SSD	P47817-B21

**Notes:**

M.2 drives supported in the Primary Riser and use S100i SATA controller only.

M.2 supports Software RAID only.

**Internal Dual M.2 Kit**

HPE Universal SATA 6G AIC HHHL M.2 SSD Enablement Kit	878783-B21
---	------------

**Notes:** This is a M.2 enablement standup card.

**Dual Mixed Use - 6G SATA - UFF SCM M.2 - Solid State Drives**

### Core Options

**Notes:** SCM dual drive functionality supported on the Premium 2SFF HDD Kit (826687-B21) and 2SFF HDD Riser Kit (826688-B21). Installation on any other bay will show one M.2 drive per bay.

#### Read Intensive - NVMe - SFF - Solid State Drives

HPE 15.36TB NVMe Gen4 High Performance Read Intensive SFF SCN U.3 PM1733 SSD	P22282-B21
HPE 7.68TB NVMe Gen4 High Performance Read Intensive SFF SCN U.2 P5520 SSD	P51456-B21
HPE 7.68TB NVMe Gen4 High Performance Read Intensive SFF SCN U.3 PM1733a SSD	P50220-B21
HPE 7.68TB NVMe Gen4 High Performance Read Intensive SFF SCN U.3 PM1733 SSD	P22280-B21
HPE 7.68TB NVMe Gen4 Mainstream Performance Read Intensive SFF SCN U.2 Multi Vendor SSD	P47825-B21
HPE 4TB NVMe Gen3 High Performance Read Intensive SFF SCN U.2 P4510 SSD	P13697-B21
HPE 3.84TB NVMe Gen4 High Performance Read Intensive SFF SCN U.2 P5520 SSD	P51454-B21
HPE 3.84TB NVMe Gen4 High Performance Read Intensive SFF SCN U.3 PM1733a SSD	P50217-B21
HPE 3.84TB NVMe Gen4 High Performance Read Intensive SFF SCN U.3 PM1733 SSD	P22278-B21
HPE 3.84TB NVMe Gen4 Mainstream Performance Read Intensive SFF SCN U.2 Multi Vendor SSD	P47824-B21
HPE 2TB NVMe Gen3 High Performance Read Intensive SFF SCN U.2 P4510 SSD	P13695-B21
HPE 1.92TB NVMe Gen4 High Performance Read Intensive SFF SCN U.2 P5520 SSD	P51452-B21
HPE 1.92TB NVMe Gen4 High Performance Read Intensive SFF SCN U.3 PM1733a SSD	P50214-B21
HPE 1.92TB NVMe Gen4 High Performance Read Intensive SFF SCN U.3 PM1733 SSD	P22276-B21
HPE 1.92TB NVMe Gen4 Mainstream Performance Read Intensive SFF SCN U.2 Multi Vendor SSD	P47823-B21

#### Write Intensive - NVMe - SFF - Solid State Drives

HPE 750GB NVMe Gen3 High Performance Low Latency Write Intensive SFF SCN U.2 P4800X SSD	P06952-B21
---	------------

#### Mixed Use - NVMe - SFF - Solid State Drives

HPE 12.8TB NVMe Gen4 High Performance Mixed Use SFF SCN U.3 PM1735 SSD	P22274-B21
HPE 6.4TB NVMe Gen4 High Performance Mixed Use SFF SCN U.2 P5620 SSD	P51462-B21
HPE 6.4TB NVMe Gen4 High Performance Mixed Use SFF SCN U.3 PM1735a SSD	P50231-B21
HPE 6.4TB NVMe Gen4 High Performance Mixed Use SFF SCN U.3 CM6 SSD	P20100-B21
HPE 6.4TB NVMe Gen4 High Performance Mixed Use SFF SCN U.3 PM1735 SSD	P22272-B21
HPE 6.4TB NVMe Gen4 Mainstream Performance Mixed Use SFF SCN U.2 Multi Vendor SSD	P47822-B21
HPE 3.2TB NVMe Gen4 High Performance Mixed Use SFF SCN U.2 P5620 SSD	P51460-B21
HPE 3.2TB NVMe Gen4 High Performance Mixed Use SFF SCN U.3 PM1735a SSD	P50228-B21
HPE 3.2TB NVMe Gen4 High Performance Mixed Use SFF SCN U.3 PM1735 SSD	P22270-B21
HPE 3.2TB NVMe Gen3 High Performance Mixed Use SFF SCN U.2 P4610 SSD	P13701-B21
HPE 3.2TB NVMe Gen4 Mainstream Performance Mixed Use SFF SCN U.2 Multi Vendor SSD	P47821-B21
HPE 6.4TB NVMe Gen4 High Performance Mixed Use SFF SCN U.2 P5620 SSD	P51462-B21
HPE 1.6TB NVMe Gen4 High Performance Mixed Use SFF SCN U.3 PM1735a SSD	P50225-B21
HPE 1.6TB NVMe Gen4 High Performance Mixed Use SFF SCN U.3 CM6 SSD	P20096-B21
HPE 1.6TB NVMe Gen4 High Performance Mixed Use SFF SCN U.3 PM1735 SSD	P22268-B21
HPE 1.6TB NVMe Gen3 High Performance Mixed Use SFF SCN U.2 P4610 SSD	P13699-B21
HPE 1.6TB NVMe Gen4 Mainstream Performance Mixed Use SFF SCN U.2 Multi Vendor SSD	P47820-B21



### Core Options

HPE 800GB NVMe Gen4 High Performance Mixed Use SFF SCN U.3 PM1735 SSD P22329-B21

**Notes:**

A NVMe (826689-B21 or 873781-B21) or Premium (826690-B21) drive cage is required to support these drives in conjunction with a NVMe riser kit.

HPE has qualified the NVMe drive portfolio using the Operating System inbox drivers, full detail on the

**HPE Solid State Drive QuickSpecs.**

NVMe drives not supported by HPE Smart Array controllers.

NVMe drives require the addition of the High Performance Fan kit (867810-B21).

**Mixed Use - NVMe - SFF - FIPS Solid State Drives**

HPE 1.6TB NVMe Gen4 High Performance Mixed Use SFF SCN Self-encrypting FIPS U.3 CM6 SSD P44588-B21

HPE 3.2TB NVMe Gen4 High Performance Mixed Use SFF SCN Self-encrypting FIPS U.3 CM6 SSD P44596-B21

**Read Intensive - NVMe - SFF - FIPS Solid State Drives**

HPE 1.92TB NVMe Gen4 High Performance Read Intensive SFF SCN Self-encrypting FIPS U.3 CM6 SSD P44572-B21

HPE 3.84TB NVMe Gen4 High Performance Read Intensive SFF SCN Self-encrypting FIPS U.3 CM6 SSD P44580-B21

**HPE NVMe x8 Lanes Mixed Use HHHL**

HPE 3.2TB NVMe Gen4 x8 High Performance Mixed Use AIC HHHL PM1735 SSD P26936-B21

HPE 1.6TB NVMe Gen4 x8 High Performance Mixed Use AIC HHHL PM1735 SSD P26934-B21

### HPE PCIe Workload Accelerator Options

**Hard Drive Blank Kits**

HPE Large Form Factor Hard Drive Blank Kit 666986-B21

HPE Small Form Factor Hard Drive Blank Kit 666987-B21

**Hard Drive Kits**

HPE DL38X Gen10 8LFF Front 2SFF SAS/SATA HDD Kit 867805-B21

**Notes:** For 2 SFF SAS/SATA in UMB on 8 LFF model only.

HPE DL38X Gen10 3LFF Rear SAS/SATA Drive Kit 826685-B21

**Notes:**

This is supported in the LFF model only.

3 LFF rear drives will consume the 2nd riser expansion slot.

HPE DL38X Gen10 4LFF Midplane SAS/SATA HDD Kit 826686-B21

**Notes:**

Supported with both the 8 LFF and 12 LFF models.

Ships with low-profile heatsink for installation. Supporting processors below 125W. Additional processors supported with system inlet ambient temperature limitations. See "CPUs Supported with 4LFF mid-tray" below

With this mid-tray only single-wide (8.5-inch cards with connections or less) cards are supported.

This drive does support hot-swap drives.

This requires High Performance Fans (867810-B21).

### CPUs Supported with 4LFF mid-tray

### Core Options

Must install DIMM blanks on all empty DIMM Slots		
System Inlet Ambient	8LFF/12LFF with 4LFF mid-tray	8LFF/12LFF + 4LFF mid-tray + any rear SAS/SATA HDDs
<b>35C</b>	<ul style="list-style-type: none"> <li>• CPU?125W</li> <li>• 135W (6262V)</li> <li>• 140W (6238, 6152, 6140)</li> </ul>	
<b>30C</b>	<ul style="list-style-type: none"> <li>• 140W (6132)</li> <li>• 150W (6210U)</li> <li>• 165 W (8276, 8260, 8260Y, 6240R, 6238R, 8176, 8170, 6150)</li> </ul>	<ul style="list-style-type: none"> <li>• CPU?125W</li> <li>• 135W (6262V)</li> <li>• 140W (6238, 6152, 6140)</li> </ul>
<b>25C</b>	<ul style="list-style-type: none"> <li>• 105W (8256, 5222, 5122, 8156)</li> <li>• 115W (5217, 6128)</li> <li>• 125W (6230N)</li> <li>• 130W (6234, 4215R, 6134)</li> <li>• 150W (6252, 6248, 6240, 6242, 6230R, 6226R, 6208U, 5220R, 8164, 8160, 8158, 6148, 6142, 6136)</li> </ul>	<ul style="list-style-type: none"> <li>• 140W (6132)</li> <li>• 150W (6210U)</li> <li>• 165 W (8276, 8260, 8260Y, 6240R, 6238R, 8176, 8170, 6150)</li> </ul>
<b>20C</b>	<ul style="list-style-type: none"> <li>• 150W (6252N, 6244, 6240Y, 6144)</li> <li>• 165W (6246, 6146)</li> <li>• 200W (6254, 6154)</li> <li>• 205W (8280, 8270, 8268, 8180, 8168)</li> </ul>	<ul style="list-style-type: none"> <li>• 105W (8256, 5222, 5122, 8156)</li> <li>• 115W (5217, 6128)</li> <li>• 125W (6230N)</li> <li>• 130W (6234, 4215R 6134)</li> <li>• 150W (6252, 6248, 6242, 6240, 6230R, 6226R, 6208U, 5220R, 8164, 8160, 8158, 6148, 6142, 6136)</li> </ul>

HPE DL38X Gen10 2SFF Premium HDD Front NVMe or Front/Rear SAS/SATA Kit 826687-B21

**Notes:**

- HPE DL38X Gen10 Universal Media Bay Kit (826708-B21).
- NVMe drives require the addition of the High Performance Fan kit (867810-B21).
- NVMe drives require the addition of an NVMe capable riser.
- Drive cage can be used in the rear of the chassis, but will not support NVMe drives rear.

HPE DL38X Gen10 2SFF HDD SAS/SATA Riser Kit 826688-B21

**Notes:**

- Supports 2 SFF rear in Riser1 or 2 location - max 2 supported SFF model.
- Supports 2 SFF rear in Riser1 or 2 location in LFF model. Note is 3 LFF rear option is selected maximum of one in riser 1 location.
- Supports uFF drives.

HPE DL38X NVMe 8 Solid State Drive Express Bay Enablement Kit 826689-B21

**Notes:**

- This option provides support for up to 8NVMe drives, and can be populated in all Boxes in the 8 SFF model.
- A maximum of 20 NVMe drives are supported; this will mean partial population (4 drives) when the 3<sup>rd</sup> cage is populated in Box 1.
- This will require the HPE DL38X Gen10 4-port 8 NVMe SlimSAS Riser (867807-B21).
- NVMe drives require the addition of the High Performance Fan kit (867810-B21).

HPE DL38X Gen10 SFF Box1/2 Cage/Backplane Kit 826691-B21

**Notes:** Supports 8 SAS/SATA SFF drives in Box 1 or 2 to a max of 24 SFF SAS/SATA front.

HPE DL38X Gen10 Premium 6 SFF SAS/SATA + 2 NVMe or 8 SFF SAS/SATA Bay Kit 826690-B21



## Core Options

**Notes:**

This kit can be supported in Box 1, 2 or 3 and provides support for up to 6 SAS/SATA + 2 NVMe or 8 SFF SAS/SATA drives per Box. If only populating SFF SAS/SATA, the HPE DL38X Gen10 SFF Box1/2 Cage/Backplane Kit (826691-B21) is the more appropriate option.

With NVMe drives a specific riser is required.

NVMe drives require the addition of the High Performance Fan kit (867810-B21).

HPE DL38X Gen10 8LFF Front 2NVMe HDD Bay Kit

873781-B21

**Notes:**

Supports 2 NVMe in the Universal Media bay (included) on the 8 LFF model.

For support of the 2 NVMe drives this will require the addition of the HPE DL38X Gen10 x8/x8/x8 1-port 2 NVMe SlimSAS Riser (867806-B21); or the HPE DL38X Gen10 2-port 4 NVMe SlimSAS Riser (867808-B21).

NVMe drives require the addition of the High Performance Fan kit (867810-B21).

## HPE Networking

**1 Gigabit Ethernet adapters**

HPE Ethernet 1Gb 4-port BASE-T BCM5719 Adapter

647594-B21

HPE Ethernet 1Gb 2-port BASE-T BCM5720 Adapter

615732-B21

HPE Ethernet 1Gb 2-port BASE-T I350-T2V2 Adapter

652497-B21

HPE Ethernet 1Gb 4-port BASE-T I350-T4V2 Adapter

811546-B21

**10 Gigabit Ethernet adapters**

**Notes:** Unless otherwise noted, one of the below 10Gb networking adapters below can be selected as the primary networking choice when configuring a Networking Choice (NC) Configure-to-Order (CTO) chassis. The DL380 Gen10 NC CTO chassis does not come with embedded networking, hence the requirement to configure with either a FlexibleLOM or select PCIe networking adapter.

HPE Ethernet 10Gb 2-port BASE-T QL41401-A2G Adapter

867707-B21

HPE Ethernet 10Gb 2-port SFP+ QL41401-A2G Adapter

P08446-B21

**Notes:** Legacy FIO Mode (758959-B22) not supported with this option on Networking Choice (NC) Configure-to-Order (CTO) chassis. To continue with the combined selection of this networking option and Legacy FIO Mode on NC CTO chassis, an additional networking option (stand-up NIC or FlexibleLOM) without the Legacy FIO mode restriction must be selected.

HPE Ethernet 10Gb 2-port BASE-T 57810S Adapter

656596-B21

HPE Ethernet 10Gb 2-port SFP+ 57810S Adapter

652503-B21

HPE Ethernet 10Gb 2-port BASE-T BCM57416 Adapter

813661-B21

**Notes:** Legacy FIO Mode (758959-B22) not supported with this option on Networking Choice (NC) Configure-to-Order (CTO) chassis. To continue with the combined selection of this networking option and Legacy FIO Mode on NC CTO chassis, an additional networking option (stand-up NIC or FlexibleLOM) without the Legacy FIO mode restriction must be selected.

HPE Ethernet 10Gb 2-port SFP+ BCM57414 Adapter

P08421-B21

**Notes:** Cannot be selected as the primary networking choice when configuring a Networking Choice (NC) Configure-to-Order (CTO) chassis.

HPE Ethernet 10Gb 2-port SFP+ X710-DA2 Adapter

727055-B21

HPE Ethernet 10Gb 2-port BASE-T X550-AT2 Adapter

817738-B21

## Core Options

**25 Gigabit Ethernet adapters**

**Notes:** Unless otherwise noted, one of the below 10/25Gb networking adapters below can be selected as the primary networking choice when configuring a Networking Choice (NC) Configure-to-Order (CTO) chassis.

The DL380 Gen10 NC CTO chassis does not come with embedded networking, hence the requirement to configure with either a FlexibleLOM or select PCIe networking adapter.

HPE Ethernet 10/25Gb 2-port SFP28 QL41401-A2G Adapter 867328-B21

HPE Ethernet 10/25Gb 2-port SFP28 BCM57414 Adapter 817718-B21

**Notes:** Legacy FIO Mode (758959-B22) not supported with this option on Networking Choice (NC) Configure-to-Order (CTO) chassis. To continue with the combined selection of this networking option and Legacy FIO Mode on NC CTO chassis, an additional networking option (stand-up NIC or FlexibleLOM) without the Legacy FIO mode restriction must be selected.

HPE Ethernet 10/25Gb 2-port SFP28 MCX4121A-ACUT Adapter 817753-B21

Intel E810-XXVDA2 Ethernet 10/25Gb 2-port SFP28 Adapter for HPE P08443-B21

Intel E810-XXVDA4 Ethernet 10/25Gb 4-port SFP28 Adapter for HPE P08458-B21

**100 Gigabit Ethernet Adapters**

HPE Ethernet 100Gb 1-port QSFP28 MCX515A-CCAT Adapter 874253-B21

**Notes:**

The DL380 Gen10 embedded LOM chassis ships standard with 4x 1 Gb embedded

A minimum of two Gigabytes (2 GB) of server memory is required per each adapter.

Direct Attach Cable (DAC) for copper environments or fiber transceivers and cables for fiber-optic environments must be purchased separately. Please see the related NIC QuickSpecs for Technical Specifications and additional information:

<https://www.hpe.com/us/en/product-catalog/servers/adapters/pip.models.hpe-storefabric-converged-network-adapters.4118472.html>

**FlexibleLOM adapters**

Pensando Distributed Services Platform for HPE iLO Sideband Management Adaptive LOM Module P26969-B21

**Notes:**

This option requires the selection of Pensando DSP 10/25G 2p SFP28 Card (P26966-B21).

Legacy FIO Mode (758959-B22) not supported with this option on Networking Choice (NC) Configure-to-Order (CTO) chassis. To continue with the combined selection of this networking option and Legacy FIO Mode on NC CTO chassis, an additional networking option (stand-up NIC or FlexibleLOM) without the Legacy FIO mode restriction must be selected.

This option cannot be selected with any GPU

HPE Ethernet 1Gb 4-port FLR-T I350-T4V2 Adapter 665240-B21

HPE Ethernet 1Gb 4-port FLR-T BCM5719 Adapter 629135-B22

HPE FlexFabric 10Gb 2-port FLR-T 57810S Adapter 700759-B21

HPE FlexFabric 10Gb 2-port FLR-SFP+ 57810S Adapter 700751-B21

HPE Ethernet 10Gb 2-port FLR-T BCM57416 Adapter 817721-B21

HPE FlexFabric 10Gb 4-port FLR-T 57840S Adapter 764302-B21

HPE Ethernet 10Gb 2-port FLR-SFP+ BCM57414 Adapter P08440-B21

HPE Ethernet 10/25Gb 2-port FLR-SFP28 BCM57414 Adapter 817709-B21

HPE Ethernet 10/25Gb 2-port FLR-SFP28 MCX4121A-ACFT Adapter 817749-B21

HPE Ethernet 10Gb 2-port FLR-SFP+ X710-DA2 Adapter 727054-B21

HPE Ethernet 10Gb 2-port FLR-T X550-AT2 Adapter 817745-B21

HPE Ethernet 10/25Gb 2-port FLR-SFP28 QL41401-A2G Converged Network Adapter 867334-B21

**Notes:**

## Core Options

The DL380 Gen10 Embedded LOM Configure-to-Order (CTO) chassis ships with 4x 1Gb embedded.

When configuring a DL380 Gen10 Networking Choice (NC) Configure-to-Order (CTO) chassis, a FlexibleLOM adapter or select stand-up card networking adapter in the "HPE Networking" section must be selected.

Only one FlexibleLOM can be added to the server. These options are upgradeable and can be changed from the original configuration after the server is shipped.

Direct Attach Cable (DAC) for copper environments or fiber transceivers and cables for fiber-optic environments must be purchased separately. Please see the related NIC QuickSpecs for Technical Specifications and additional information: <https://www.hpe.com/us/en/product-catalog/servers/adapters/pip.models.hpe-storefabric-converged-network-adapters.4118472.html>

## HPE InfiniBand

HPE InfiniBand FDR/Ethernet 40/50Gb 2-port 547FLR-QSFP Adapter 879482-B21

HPE InfiniBand EDR/Ethernet 100Gb 2-port 841QSFP28 Adapter 872726-B21

**Notes:** 8SFF, 16SFF, 8LFF no restrictions; 24SFF, 12LFF supported, but limited to 25C.

HPE InfiniBand EDR 100Gb 1-port 841QSFP28 Adapter 872725-B21

HPE 100Gb 1-port OP101 QSFP28 x16 PCIe Gen3 with Intel Omni-Path Architecture Adapter 829335-B21

HPE InfiniBand HDR100/Ethernet 100Gb 1-port QSFP56 PCIe3 x16 MCX653105A-ECAT Adapter P06250-B21

HPE InfiniBand HDR100/Ethernet 100Gb 2-port QSFP56 PCIe3 x16 MCX653106A-ECAT Adapter P06251-B21

HPE InfiniBand HDR/Ethernet 200Gb 1-port QSFP56 PCIe3 x16 MCX653105A-HDAT Adapter P06154-B21

**Notes:** Max Qty=1; Must be ordered with HPE Infiniband HDR PCIe G3 Auxiliary Card (P06154-B23)

Pair must be installed in same riser. If installed in separate riser, the risers should be adjacent to each other example riser 1 and riser 2 or riser2 and riser 3.

HPE InfiniBand HDR PCIe3 Auxiliary Card with 350mm Cable Kit P06154-B23

**Notes:** Max Qty=1; Must be ordered with HPE Infiniband HDR/Ethernet 200G 1p 9400QSFP56 (P06154-B21)

Pair must be installed in same riser. If installed in separate riser, the risers should be adjacent to each other example riser 1 and riser 2 or riser2 and riser 3.

## HPE Smart IO

### Pensando Distributed Services Card (DSC)

Pensando Distributed Services Platform DSC-25 Enterprise 10/25Gb 2-port SFP28 Card P26966-B21

#### Notes:

Legacy FIO Mode (758959-B22) not supported with this option on Networking Choice (NC) Configure-to-Order (CTO) chassis. To continue with the combined selection of this networking option and Legacy FIO Mode on NC CTO chassis, an additional networking option (stand-up NIC or FlexibleLOM) without the Legacy FIO mode restriction must be selected.

DSC card must be installed in slot 1 when configured with Pensando for HPE iLO Adaptive LOM module (P26969-B21)

Each card instance requires one RTU license of Silver or Platinum software. In case of more than one adapter, RTU licenses do not need to be of the same part number.

One 3yr/4yr/5yr Silver or 3yr/4yr/5yr Platinum software license must be purchased for every DSC-25 card/adapter in a server.

1yr Silver, 1yr Platinum software licenses are reserved for renewals only.

### Pensando Distributed Services Platform FlexibleLOM Adapter

### Core Options

Pensando Distributed Services Platform for HPE iLO Sideband Management Adaptive LOM Module P26969-B21

**Notes:**

This option requires the selection of Pensando DSP 10/25G 2p SFP28 Card (P26966-B21). Legacy FIO Mode (758959-B22) not supported with this option on Networking Choice (NC) Configure-to-Order (CTO) chassis. To continue with the combined selection of this networking option and Legacy FIO Mode on NC CTO chassis, an additional networking option (stand-up NIC or FlexibleLOM) without the Legacy FIO mode restriction must be selected  
This option cannot be selected with any GPU; If a GPU is required, contact your field services representative to have the configuration evaluated.

**DSP Silver Software Licenses**

Pensando Distributed Services Platform Enterprise 1-year Renewal Subscription 24x7 Support E-RTU R6A06AAE

Pensando Distributed Services Platform Enterprise 3-year Subscription 24x7 Support E-RTU R6A07AAE

Pensando Distributed Services Platform Enterprise 4-year Subscription 24x7 Support E-RTU R6F68AAE

Pensando Distributed Services Platform Enterprise 5-year Subscription 24x7 Support E-RTU R6A08AAE

**DSP Platinum Software Licenses**

Pensando Distributed Services Platform Enterprise Pro 1-year Renewal Subscription 24x7 Support E-RTU R6A09AAE

Pensando Distributed Services Platform Enterprise Pro 3-year Subscription 24x7 Support E-RTU R6A10AAE

Pensando Distributed Services Platform Enterprise Pro 4-year Subscription 24x7 Support E-RTU R6F69AAE

Pensando Distributed Services Platform Enterprise Pro 5-year Subscription 24x7 Support E-RTU R6A11AAE

### HPE I/O Expansion Options

**Notes:**

The Primary Riser shipping default in the chassis is a x8 FH, FL, x16 FH, FL and x8 FH, HL with m.2 support.

For a Secondary/Tertiary riser, the second processor is required.

HPE DL38X Gen10 Slot 1/2 x16/x16 FIO Riser Kit 871674-B21

**Notes:**

Slot 1 (Top slot) and 2 (Middle slot) available in Primary riser location

Replaces the default Primary riser

Max Qty=1 Double-wide Accelerator/GPU can be populated

Supports Full Height and Full length cards.

Bus width x16, x16, Connector Width x16, x16.

HPE DL38X Gen10 x16/x16 GPU Slot2/3 FIO Riser Kit 871676-B21

**Notes:**

Slot 2 (Middle slot) and Slot 3 (Bottom slot) available in Primary riser location

Replaces the default Primary riser

Max Qty=1 Double-wide Accelerator/GPU can be populated

Supports Full Height and Full length cards.

Bus width x16, x16, Connector Width x16, x16.

HPE DL38X Gen10 x8/x8/x8 1-port 2 NVMe Slim SAS FIO Riser Kit 871673-B21

## Core Options

**Notes:**

Slot 1 (Top slot) and 2 (Middle Slot) and 3 (Bottom slot) available in Secondary riser location with support for 2 NVMe drives

Supports Full Height and half-length cards.

Bus width x8, x8, x8 Connector Width x8, x8, x8.

If this option is selected and the Premium 2SFF HDD Kit (826687-B21) has also been ordered, then the 2SFF NVMe Instruction Spec (878189-B21) MUST be selected; does not apply to 8LFF server model

If this option is selected and HPE DL38X Gen10 Premium 6SFF SAS/SATA + 2SFF NVMe Bay Kit (826690-B21) has also been ordered, then the 6+2 NVMe Instruction Spec (878192-B21) MUST be selected.

HPE DL38X Gen10 x16/x16/x16 Primary GPU FIO Riser Kit

P14374-B21

**Notes:**

Slot 1 (Top slot) and 2 (Middle Slot) and 3 (Bottom slot) available in Primary riser location and must be populated. Supports up to (3) full-height, half-length, single-width GPU/Accelerators (depending on model)

Replaces the default Primary riser

Bus width x8, x16, x8; Connector width x16, x16, x16

This is a factory-integrated only (FIO) option. All slots (3) must be populated.

HPE DL38X Gen10 x16/x16/x16 Secondary GPU FIO Riser Kit must also be selected and requires all slots (3) be populated.

HPE DL38X Gen10 x16/x16/x16 Secondary GPU FIO Riser Kit

P14373-B21

**Notes:**

Slot 1 (Top slot) and 2 (Middle Slot) and 3 (Bottom slot) available in Secondary riser location; all slots must be populated. Supports up to (3) full-height, half-length, single-width GPU/Accelerators (depending on model)

Bus width x8, x16, x8; Connector width x16, x16, x16

This is a factory-integrated only (FIO) option. All slots (3) must be populated.

HPE DL38X Gen10 x16/x16 Riser Kit

826694-B21

**Notes:**

Slot 1 (Top slot) and 2 (Middle slot) available in Secondary riser location.

NMax Qty=1 Double-wide Accelerator/GPU can be populated

Supports Full Height and Full length cards.

Bus width x16, x16, Connector Width x16, x16.

HPE DL Gen10 x8/x16/x8 Riser Kit

870548-B21

**Notes:**

Slot 1 (Top slot) and 2 (Middle slot) and 3 (Bottom slot) available in Secondary riser location.

No M.2 support on this riser.

Supports Full Height, Half-length cards; Full Height, Full-length cards and Full Height, Half-length cards.

Bus width x8, x16, x8, Connector Width x8, x16, x8.

HPE DL38X Gen10 4-port 8 NVMe Primary SlimSAS Riser

867807-B21

**Notes:**

Riser supporting up to 8 NVMe drives in Primary location. All PCIe lanes dedicated to NVMe; no additional slots available for expansion via stand-up cards in the Primary riser location.

Replaces the default Primary riser

This is a factory integrated only option.

This can be connected to an 8SFF NVMe drive cage in box 3.

To achieve max 20 NVMe support, connect 4 NVMe drives to the tertiary riser.

HPE DL Gen10 x16/x16 GPU Riser Kit

826704-B21

**Notes:**

Slot 2 (Middle slot) and 3 (Bottom slot) available in Secondary riser location.

Max Qty=1 Double-wide Accelerator/GPU can be populated

Supports Full Height and Full length cards.



## Core Options

Bus width x16, x16, Connector Width x16, x16.

For additional details on ProLiant DL Gen10 server risers please visit:

<https://www.hpe.com/h20195/v2/Getdocument.aspx?docname=a00043229enw>

HPE ProLiant DL38x Gen10 2SFF BC HDD SAS/SATA Riser Kit

P57772-B21

**Notes:**

This option is housed into a Riser assembly and will be installed in the rear of the chassis. It can be installed into either the Primary Riser location, the Secondary Riser location, or both if Qty=2 are ordered.

Requires selection of a second processor

Supported only with the 8SFF Basic Carriers Model-X

Requires selection of a tri-mode controller

Requires selection of 2SFF riser tri-mode cable kit (P55471-B21)

HPE DL38X Gen10 2SFF HDD SAS/SATA Riser Kit

826688-B21

**Notes:**

Premium bay supporting SFF SAS/SATA; can be configured in Primary or Secondary riser location Slot 3 (Bottom slot) available in Primary or Secondary Riser location, depending on configuration

Bus width x16, Connector width x16

HPE DL38X Gen10 x8/x8/x8 1-port 2 NVMe SlimSAS Riser

867806-B21

**Notes:**

Slot 1 (Top slot) or 2 (Middle Slot) or 3 (Bottom slot) available in Secondary riser location with support for 2 NVMe drives

Supports Full Height and half-length cards.

Bus width x8, x8, x8 Connector Width x8, x8, x8.

If this option is selected and the Premium 2SFF HDD Kit (826687-B21) has also been ordered, then the 2SFF NVMe Instruction Spec (878189-B21) MUST be selected; does not apply to 8LFF server model

If this option is selected and HPE DL38X Gen10 Premium 6SFF SAS/SATA + 2SFF NVMe Bay Kit (826690-B21) has also been ordered, then the 6+2 NVMe Instruction Spec (878192-B21) MUST be selected.

HPE DL38X Gen10 2-port 4 NVMe SlimSAS Riser

867808-B21

**Notes:** Supports up to 4 NVMe drives in Tertiary riser location; All PCIe lanes dedicated to NVMe; no additional slots available for expansion via stand-up cards in the Tertiary riser location.

HPE DL38X Gen10 4-port 8 NVMe Secondary Slim SAS Riser

873732-B21

**Notes:** Riser supporting up to 8 NVMe drives in Secondary riser location; All PCIe lanes dedicated to NVMe; no additional slots available for expansion via stand-up cards in the Secondary riser location.

HPE DL38X Gen10 2 x8 PCIe Tertiary Riser Kit

875780-B21

**Notes:**

Slot 1 (Top slot) and slot (2) available in Tertiary riser location.

Bus width x8, x8; Connector Width x8, x8.

HPE DL38X Gen10 x16 Tertiary Riser Kit

826700-B21

**Notes:**

Slot 1 (Top slot) available in Tertiary riser location.

Supports Full Height and full-length card.

Bus width x16; Connector Width x16.

HPE DL380 Gen10 Pri/Sec Rsr w/o Retainer

P38515-  
B21

**Notes:**

This riser cage removes the retainer clip for proper fitment of certain NVIDIA GPUs in the primary and/or secondary riser.

For such applicable NVIDIA GPUs to be populated in the primary riser, first select the appropriate primary riser unless the

### Core Options

default x8x16x8 primary is preferred. Then add P38515-B21. For such applicable NVIDIA GPUs in the secondary riser, a secondary riser must first be selected; then add P38515-B21. See "Riser Information" table within this document to select the appropriate primary and/or secondary riser options.

If an applicable NVIDIA GPU is installed in both primary and secondary risers, a minimum quantity of (2) of P38515-B21 must be selected if the tertiary riser will not be populated; OR (1) P38515-B21 + (1) P38517-B21 HPE DL380 Gen10 Tertiary Riser without Retainer must be selected if, in addition to both primary and secondary risers containing applicable NVIDIA GPUs, the tertiary riser is being populated with any option, including NVIDIA GPUs.

HPE DL380 Gen10 Tert Riser w/o Retainer

P38517-B21

**Notes:** This tertiary riser cage is a butterfly cage for both the secondary riser and tertiary riser. It removes the retainer clip in the secondary riser for proper fitment of certain NVIDIA GPUs, while allowing for a tertiary riser selection as well. This option should be selected if the tertiary riser is being populated with any option, including NVIDIA GPUs, and the secondary riser contains an applicable NVIDIA GPU. First select the appropriate secondary riser and tertiary riser (see "Riser Information" table for riser options); then add P38517-B21.

### Risers

Riser Information*									
Part number	Description	Riser position			Bus width (Gen3 lanes)			NVMe Direct Connect	
		Primary	Secondary	Tertiary	Top slot	Middle Slot	Bottom slot	Ports	Drive count
n/a	This is the default riser in the chassis	D	N	N	x8	x16	x8	-	-
870548-B21	HPE DL Gen10 x8/x16/x8 Riser Kit	N	O	N	x8	x16	x8	-	-
826704-B21	HPE DL Gen10 x16/x16 GPU Riser Kit	O <sup>2</sup>	O	N	0	x16	x16	-	-
826694-B21	HPE DL38X Gen10 x16/x16 Riser Kit	O <sup>2</sup>	O	N	x16	x16	0	-	-
867807-B21	HPE DL38X Gen10 4-port 8 NVMe Primary SlimSAS Riser	O	N	N	0	0	0	4	8
867808-B21	HPE DL38X Gen10 2-port 4 NVMe SlimSAS Riser	N	N	O	0	0	0	2	4
873732-B21	HPE DL38X Gen10 4-port 8 NVMe Secondary SlimSAS Riser	N	O	N	0	0	0	4	8
867806-B21	HPE DL38X Gen10 x8/x8/x8 1-port 2 NVMe SlimSAS Riser	N	O	N	x8	x8	x8	1	2
871673-B21	HPE DL38X Gen10 x8/x8/x8 1-port 2 NVMe SlimSAS FIO Riser Kit	O	N	N	x8	x8	x8	1	2
826688-B21	HPE DL38X Gen10 2SFF HDD SAS/SATA Riser Kit	O	O	N	0	0	x16	-	-



### Core Options

826700-B21	HPE DL38X Gen10 x16 Tertiary Riser Kit	N	N	O	X16	0	0	-	-
875780-B21	HPE DL38X Gen10 2 x8 PCIe Tertiary Riser Kit	N	N	O	X8	X8	0	-	-
871674-B21	HPE DL38X Gen10 Slot 1/2 x16/x16 FIO Riser Kit	O	N	N	x16	x16	0	-	-
871676-B21	HPE DL38X Gen10 x16/x16 GPU Slot2/3 FIO Riser Kit	O	N	N	0	x16	x16	-	-
P14374-B21	HPE DL38X Gen10 x16/x16/x16 Primary GPU FIO Kit <sup>1</sup>	O	N	N	x8	x16	x8	-	-
P14373-B21	HPE DL38X Gen10 x16/x16/x16 Secondary GPU FIO Kit <sup>1</sup>	N	O	N	x8	x16	x8	-	-

#### Notes:

<sup>1</sup> P14374-B21 and P14373-B21 each support up to (3) full-height, half-length, single-width Accelerators/GPUs (depending on Accelerator model selected), totaling (6) Accelerators in the primary riser and secondary riser (balanced across both processors in a 2-processor configuration). Connector width = x16/x16/x16; Bus width = x8/x16/x8.

<sup>2</sup> Field upgrade only

D = Default on chassis; O = Optional; N = not supported or slot/connector not present.

The 826687-B21 premium 2SFF cage is leveraged both UMB, plus 2SFF rear over PS.

\*For additional details on ProLiant DL Gen10 server risers please visit:

<https://www.hpe.com/h20195/v2/Getdocument.aspx?docname=a00043229enw>

### HPE Power Supplies

HPE 500W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit 865408-B21

**Notes:** Flex Slot Platinum power supplies support power efficiency of up to 94% and include a standard C-14 power inlet connector.

HPE 800W Flex Slot Titanium Hot Plug Low Halogen Power Supply Kit 865438-B21

**Notes:** Flex Slot Titanium power supplies support power efficiency of up to 96% and include a standard C-14 power inlet connector.

HPE 800W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit 865414-B21

**Notes:** Flex Slot Platinum power supplies support power efficiency of up to 94% and include a standard C-14 power inlet connector.

HPE 800W Flex Slot -48VDC Hot Plug Low Halogen Power Supply Kit 865434-B21

**Notes:** Flex Slot -48VDC power supplies support power efficiency of up to 94%.

HPE 800W Flex Slot Universal Hot Plug Low Halogen Power Supply Kit 865428-B21

**Notes:** Flex Slot universal power supplies support power efficiency of up to 94% and support both 277VAC/380VDC power inputs.

HPE 1600W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit 830272-B21

**Notes:** Flex Slot Platinum Plus power supplies support power efficiency of up to 94% and include a C-14 power inlet connector that can support HPE Power Discovery Services (blue connector).

HPE 1600W Flex Slot -48VDC Hot Plug Power Supply Kit P17023-B21

### Core Options

#### Notes:

Flex Slot -48VDC power supplies support power efficiency of up to 94%.

Requires selection of HPE 1600W DC PSU Power Cable Kit (P22173-B21) or HPE 1600W DC PSU Power

Lug Option Kit (P36877-B21). P22173-B21 includes the power cable with lugs installed while P36877-

B21 is intended for customers using their own cabling and only require the lugs.

Not supported with Intel Optane Persistent Memory (128/256/512GB)

### Accelerators

Accelerators Information												
Part number	Description	Qty	Processor supported	Processor Generation	8 SFF	8 LFF	16SFF +UMB with 2SFF	16 SFF +8NVM e	24 SFF	24 SFF +SFF rear	12 LFF	12 LFF+ 2SFF rear
Q1K38C	AMD Radeon Instinct MI25	3	165W or below	1st Gen	35C	25C	25C	25C <sup>1</sup>	25C	25C <sup>1</sup>	N/S*	N/S*
Q9B37C	Intel Arria 10 GX FPGA Accelerator	5	205W or below	1st and 2nd Gen	35C	35C	30C	30C	30C	30C	25C	25C
R0X82C	Intel FPGA PAC D5005 (Stratix 10 SX) FPGA Accelerator	3	205W or below	2nd Gen	30C	N/S*	20C	N/S*	N/S*	N/S*	N/S*	N/S*
Q7G75C	NEC Vector Engine Accelerator Module	3	165W or below	2nd Gen	30C	N/S*	N/S*	N/S*	N/S*	N/S*	N/S*	N/S*
R6B53C	HPE NVIDIA A100 40GB GPU	2	205W or below	2nd Gen	30C	25C	20C	N/S*	20C	20C	N/S*	N/S*
R9S37C	NVIDIA A40 48GB GPU NonCEC Accelerator	2	205W or below	2nd Gen	25C	20C	N/S*	N/S*	N/S*	N/S*	N/S*	N/S*
R7E31C	NVIDIA A40 PCIe 48GB GPU for HPE	2	205W or below	2nd Gen	25C	20C	N/S*	N/S*	N/S*	N/S*	N/S*	N/S*

### Core Options

R7G39C	NVIDIA A30 24GB PCIe GPU Module	2	205W or below	2nd Gen	35C*	30C*	30C*	N/S*	30C*	N/S*	N/S*	N/F*
R9H23C	NVIDIA A2 16GB PCIe NonCEC Accelerator	8	205W or below	2nd Gen	30C	25C	20C	N/S*	N/S*	N/S*	N/S*	N/S*
R9H23C	NVIDIA A2 GPU Accelerator	8	205W or below	2nd Gen	30C	25C	20C	N/S*	N/S*	N/S*	N/S*	N/S*
R2U55C	HPE NVIDIA Quadro P2200 GPU Module	5	205W or below	2nd Gen	35C	35C	35C	35C <sup>1</sup>	35C	35C <sup>1</sup>	35C	35C <sup>1</sup>
R1F95C	HPE NVIDIA Quadro RTX4000 GPU Module	5	205W or below	2nd Gen	35C	35C	35C	35C <sup>1</sup>	35C	35C <sup>1</sup>	30C	30C <sup>1</sup>
R0Z45C	HPE NVIDIA Quadro RTX 6000	3	205W or below	1st and 2nd Gen	35C	35C	35C	35C	35C	35C	25C	25C
R1F97C	HPE NVIDIA Quadro RTX8000 GPU Module	2	205W or below	2nd Gen	35C	35C	35C	35C	35C	35C	30C	30C
Q0J62C	NVIDIA Tesla M10 32GB Module <sup>2</sup>	2	165W or below	1st Gen and 2nd Gen	35C	35C	35C	25C <sup>1</sup>	35C	35C	30C	30C <sup>1</sup>
Q0V80C	NVIDIA Tesla P40 24GB Module	3	165W or below	1st and 2nd Gen	35C	35C	25C	25C <sup>1</sup>	25C	25C <sup>1</sup>	20C	20C <sup>1</sup>
R0W29C	NVIDIA Tesla T4 16GB Computational Accelerator	7	205W or below	1st and 2nd Gen	35C	N/S*	? 30C	?20C	? 20C	? 20C	N/S*	N/S*

### Core Options

Q9U36C	HPE NVIDIA Tesla V100 PCIe 32GB Module	3	165W or below	1st and 2nd Gen	30C	20C	20C	20C <sup>1</sup>	20C	20C <sup>1</sup>	N/S*	N/S*
R4D73C	HPE NVIDIA Tesla V100S PCIe 32GB Module	3	165W or below	2nd Gen	30C	20C	20C	20C <sup>1</sup>	20C	20C <sup>1</sup>	N/S*	N/S*
R4B02C	HPE Xilinx Alveo U50 Accelerator	7	205W or below	2nd Gen	30C	20C	20C	N/S*	20C	N/S*	N/S*	N/S*
R4B03C	HPE Xilinx Alveo U250 Accelerator	3	205W or below	2nd Gen	35C	20C	20C	N/S*	N/S*	N/S*	N/S*	N/S*

#### Notes:

\*Not Supported

\*\*Fan at 100% duty

<sup>1</sup> Invalid configuration or no HW support may apply to multiple GPUs installed. HW limitation may not be a thermal limitation.

<sup>2</sup> Only 2xM10 can be supported (on any x16 slot 2, 5 or 7) due to system running out of PCIe lanes.

Within the column labeled "Processor Generation Supported", "1st Gen" and/or "2nd Gen" denotes which generation of Intel Scalable Series processors is supported on the respective GPU/FPGA; for reference, the 2nd digit of the processor model number "x1xx" and "x2xx" is used to identify the processor generation (i.e. 1=1st generation and 2=2nd generation)

1x 1600W PS recommended, but this card will work with 1x800W PS (per GPU). However check the power usage via the HPE Power Advisor Tool located at <http://www.hpe.com/info/hppoweradvisor>.

Performance fans (867810-B21) are required for all GPU installations (Note these ship as standard with the 24SFF and 12LFF models).

Performance Heatsinks (826706-B21) are required for Double Wide GPU installations (Note these ship as standard on Processors over 130W processors and the 8256, 8156, 6128, 5222 and 5122)

Mixing of GPUs is not supported.

With the Standard Primary Riser the top x8 PCIe Slot connector will not be accessible with the installation of a doublewide GPU.

Only 2 SFF rear drives supported over Power Supply as would require Riser 1 and Riser 2 for GPU support.

4 LFF mid-tray will not support any GPU cards.

The M10 is limited to a max memory support of under 1TB.

Any GPU installation does not meet Energy Star requirements.

Installations with Graphics cards do not support Microsoft Windows Server 2012 R2 installations.

System memory should be 2x GPU memory.

For Graphics cards there is a limitation of 1 single wide GPU on the slot 2/3 riser (826704-B21 Secondary and 871676-B21 Primary).

### HPE Computation and Graphics Accelerators

NVIDIA A16 64GB PCIe Non-CEC Accelerator for HPE

R8T26C

#### Notes:

– Max Qty = 2

– This GPU requires Pwr Cable Kit (871829-B21) to also be selected.

– This option requires the High Performance Fan Kit (867810-B21) to be selected

– This option requires the selection of the High Performance Heatsink (826706-B21)

## Core Options

- Not supported on 12LFF Model-X
- Only supported with 2<sup>nd</sup> generation processors
- Requires selection of HPE DL380 Gen10 Pri/Sec Rsr w/o Retainer (P38515-B21) and/or HPE DL380 Gen10 Tert Riser w/o Retainer (P38517-B21). Selection is based on quantity of Graphics Option selected
- This option cannot be selected if more than 8NVMe Drives are selected.

## NVIDIA A30 PCIe Non-CEC Accelerator for HPE

R9S38C

**Notes:**

- Max Qty = 2
- This GPU requires Pwr Cable Kit (871829-B21) to also be selected.
- This option requires the High Performance Fan Kit (867810-B21) to be selected
- This option requires the selection of the High Performance Heatsink (826706-B21)
- Not supported on 12LFF Model-X
- Only supported with 2<sup>nd</sup> generation processors
- Requires selection of HPE DL380 Gen10 Pri/Sec Rsr w/o Retainer (P38515-B21) and/or HPE DL380 Gen10 Tert Riser w/o Retainer (P38517-B21). Selection is based on quantity of Graphics Option selected
- This option cannot be selected if more than 8NVMe drives are selected.

## NVIDIA A40 48GB PCIe Non-CEC Accelerator for HPE

R9S37C

**Notes:**

- Max Qty = 2
- This GPU requires Pwr Cable Kit (871829-B21) to also be selected.
- This option requires the High Performance Fan Kit (867810-B21) to be selected
- This option requires the selection of the High Performance Heatsink (826706-B21)
- Not supported on 12LFF Model-X
- Only supported with 2<sup>nd</sup> generation processors
- Requires selection of HPE DL380 Gen10 Pri/Sec Rsr w/o Retainer (P38515-B21) and/or HPE DL380 Gen10 Tert Riser w/o Retainer (P38517-B21). Selection is based on quantity of Graphics Option selected
- This option cannot be selected if more than 8NVMe drives are selected.
- If Qty 2 of 8SFF Drive Cage (P57774-B21) is selected then this Graphics option cannot be selected.

## NVIDIA A2 16GB PCIe Non-CEC Accelerator for HPE

R9H23C

**Notes:**

- This option requires the High Performance Fan Kit (867810-B21) to be selected
- This option requires the selection of the High Performance Heatsink (826706-B21)
- Not supported on 12LFF or 24SFF Model-X
- Only supported with 2<sup>nd</sup> generation processors
- Requires selection of HPE DL380 Gen10 Pri/Sec Rsr w/o Retainer (P38515-B21) and/or HPE DL380 Gen10 Tert Riser w/o Retainer (P38517-B21). Selection is based on quantity of Graphics Option selected
- This option cannot be selected if more than 16NVMe drives are selected.
- If Qty 2 of 8SFF Drive Cage (P57774-B21) is selected then this Graphics option cannot be selected.

## NVIDIA A40 48GB PCIe Non-CEC Accelerator for HPE

R9S37C

**Notes:**

- Max Qty = 2

- ? If installed in Primary riser position, the Primary/Secondary Riser w/out Retainer (P38515-B21) must be selected in addition to the appropriate Primary Riser to support this GPU, which may include the default x8/x16/x8 Primary Riser that comes standard on all DL380 Gen10 chassis.
- The second GPU, if desired, will be defaulted to the Secondary Riser position unless one of two slimSAS risers (873732-B21/867806-B21) is selected. If neither of the aforementioned slimSAS risers are selected and no option will be populated in the tertiary riser, P38515-B21 must be selected in addition to the appropriate secondary riser. If neither of the aforementioned slimSAS risers are selected but the

## Core Options

tertiary riser will be populated with any option, including an NVIDIA GPU, P38517-B21 should be selected in addition to the appropriate secondary and tertiary risers. If one of the aforementioned slimSAS risers are selected, the second GPU can be installed with the selection of HPE DL38X Gen10 x16 Tertiary Riser Kit (826700-B21) and without the need for a riser cage without retainer kit (P38515-B21/P38517-B21). \*The first GPU in the primary riser would still need P38515-B21.

- ? If installed in Tertiary Riser, the Tertiary Riser w/out Retainer (P38517-B21) must also be selected.
  - ? This requires the HPE DL380 Gen10 8P Keyed Cable Kit 871829-B21. One Pwr Cable Kit can support multiple (Max=3 Doublewide or Max=6 Singlewide) GPUs.
  - ? This option requires the High Performance Fan Kit (867810-B21) and the High Performance Heatsink (826706-B21).
    - System memory should be 2x GPU memory.
    - Only Supported with 2nd Generation Intel Scalable Series Processors "x2xx"
    - Not supported on 12LFF chassis
    - Not supported if more than 8 NVMe drives are selected
- NVIDIA A2 16GB PCIe Non-CEC Accelerator for HPE R9H23C

**Notes:**

- Max Qty = 8
- ? Requires selection of HPE DL380 Gen10 Pri/Sec Rsr w/o Retainer (P38515-B21) and/or HPE DL380 Gen10 Tert Riser w/o Retainer (P38517-B21). Selection is based on quantity of Graphics Option selected
  - If Qty 3 or less number of this GPU is selected then Qty 1 of Pri/Sec Rsr w/o Retainer (P38515-B21) must be selected.
  - If more than Qty 3 of this GPU is selected then anyone of below combination must be selected:
- ? Qty2 of Pri/Sec Rsr w/o Retainer (P38515-B21) if Secondary 4Port Slimline Riser (873732-B21) or 1Port Slimline Riser (867806-B21) or Tertiary riser is NOT selected.
- ? Qty1 of Pri/Sec Rsr w/o Retainer (P38515-B21) and Tert Riser w/o Retainer (P38517-B21) must be selected if Secondary 4Port Slimline Riser (873732-B21) or 1Port Slimline Riser (867806-B21) or Tertiary riser is selected.
  - If more than Qty 6 of this GPU is selected then Qty1 of Pri/Sec Rsr w/o Retainer (P38515-B21) and Tert Riser w/o Retainer (P38517-B21) must be selected.
- ? This option requires the High Performance Fan Kit (867810-B21) and the High Performance Heatsink (826706-B21).
- ? System memory should be 2x GPU memory.
- ? Only Supported with 2nd Generation Intel Scalable Series Processors "x2xx"
- ? Not supported on 12LFF chassis or 24SFF chassis

NVIDIA T4 16GB Computational Accelerator for HPE R0W29C

**Notes:**

Max Qty=7 per server; Requires selection of 3x16 Primary and Secondary GPU Risers (P14374-B21, P14373-B21) for Qty=6; Requires the addition of x16 Tertiary Riser for Qty=7. If ordering with a 24SFF CTO server model (868704-B21, or 875783-B21, or P19719-B21), the HPE DL380 Gen10 Tertiary x16 Riser (826700-B21) is required. To achieve a max of 7 with 24SFF model, the pre-selected HPE Smart

### Core Options

Array P408i and SAS Expander must be replaced with HPE Smart Array P816i-a SR Gen10 Ctrlr (804338-B21). Otherwise, Max Qty=6 for 24SFF CTO server models.

This option requires the High Performance Fan Kit (867810-B21), and the High Performance Heatsink (826706-B21)

System Memory Restriction <128TB

System memory should be 2x GPU memory.

Xilinx Alveo U50 Accelerator for HPE

R4B02C

#### Notes:

Max Qty=7 per server

This option requires the High Performance Fan Kit (867810-B21), and the High Performance Heatsink (826706-B21); heatsink rule does not apply if ordering processors above 126W or higher.

System Memory Restriction <128TB.

Only Supported with 2nd Generation Intel Scalable Series Processors "x2xx"

Mixing of GPUs is not supported

Not supported on 12LFF chassis; not supported on 24SFF chassis when SFF rear drives installed

Not supported with NVMe 8 SSD Express bay (826689-B21) nor Premium 8SFF Bay Kit (826690-B21) nor 2SFF HDD Riser Kit (826688-B21)

Supported DAC cables are HPE 100Gb QSFP28 to QSFP28 5m DAC (845408-B21) and HPE 100Gb QSFP28 to QSFP28 3m DAC (845406-B21)

Xilinx Alveo U250 Accelerator for HPE

R4B03C

#### Notes:

Max Qty=3 per server

This option requires the High Performance Fan Kit (867810-B21), and the High Performance Heatsink (826706-B21); heatsink rule does not apply if ordering processors above 126W or higher.

This GPU requires Pwr Cable Kit (871828-B21) to also be selected.

One Pwr Cable Kit can support multiple (Max=3 Doublewide or Max=6 Singlewide) GPUs.

System Memory Restriction <128TB.

Only Supported with 2nd Generation Intel Scalable Series Processors "x2xx"

Mixing of GPUs is not supported

Not supported on 12LFF Chassis nor 24SFF Chassis

Not supported with NVMe 8 SSD Express bay (826689-B21) nor Premium 8SFF Bay Kit (826690-B21) nor 2SFF HDD Riser Kit (826688-B21)

### Graphics Cable Kits

HPE DL38x GPU 6px6p Y-Power Cable Kit	874212-B21
HPE DL38X Gen10 8-pin Cable Kit	871828-B21
HPE DL38x Gen10 8-pin Keyed Cable Kit	871829-B21
HPE GPU 2x 8-pin Cable Kit	P03849-B21
HPE DL38X Gen10 8x 6-pin Cable Kit	871830-B21

### HPE Cooling Options

HPE DL38X Gen10 High Performance Temperature Fan Kit	867810-B21
--	------------

#### Notes:

This kit is required for specific **Ambient temperature environments**.

High Performance fan kit consists of 6 fans, these will need to replace all the standard fans in the unit, and fill all 6 fan cages.

The 12 LFF and 24 SFF models (including field upgrades to 24 SFF) will already include 6 High Performance fan kits.

The High Performance fan kit is needed to support certain Passive GPGPU (Graphics cards) configurations; or ASHRAE operating environments.



## Core Options

For elevated ambient temperature support please see: <http://www.hpe.com/servers/ashrae>.

---

### Additional Options

Some options may not be integrated at the factory. To ensure only valid configurations are ordered, Hewlett Packard Enterprise recommends the use of an HPE approved configurator. Contact your local sales representative for additional information.

#### Embedded Management

##### HPE iLO Common Password FIO Setting

HPE iLO Common Password FIO Setting P08040-B21

##### Notes:

Replaces iLO default randomized password by an HPE defined common password. HPE highly recommends changing this password immediately after the initial onboarding process. Customers who want to choose their own custom iLO default password should use the HPE Factory Express Integration Services

##### HPE iLO Advanced

HPE iLO Advanced Electronic License with 1yr Support on iLO Licensed Features	E6U59ABE
HPE iLO Advanced 1-server License with 1yr Support on iLO Licensed Features	512485-B21
HPE iLO Advanced Flexible Quantity License with 1yr Support on iLO Licensed Features	512486-B21
HPE iLO Advanced AKA Tracking License with 1yr Support on iLO Licensed Features	512487-B21
HPE iLO Advanced Electronic License with 3yr Support on iLO Licensed Features	E6U64ABE
HPE iLO Advanced 1-server License with 3yr Support on iLO Licensed Features	BD505A
HPE iLO Advanced Flexible Quantity License with 3yr Support on iLO Licensed Features	BD506A
HPE iLO Advanced AKA Tracking License with 3yr Support on iLO Licensed Features	BD507A

##### HPE Converged Infrastructure Management Software

HPE OneView including 3yr 24x7 Support Physical 1-server LTU	E5Y34A
HPE OneView including 3yr 24x7 Support Flexible Quantity E-LTU	E5Y35AAE
HPE OneView w/o iLO including 3yr 24x7 Support 1-server LTU	P8B24A
HPE OneView w/o iLO including 3yr 24x7 Support Track 1-server LTU	P8B25A
HPE OneView w/o iLO including 3yr 24x7 Support Flexible Quantity E-LTU	P8B26AAE

**Notes:** Licenses ship without media. The HPE OneView Media Kit can be ordered separately, or can be downloaded.

#### HPE Security

HPE Trusted Supply Chain FIO Configuration P36394-B21

##### Notes:

HPE Trusted Supply Chain (P36394-B21) is an optional security upgrade intended for agencies and regulated industries needing enhanced security and compliance needs. Applying this option to a DL380 Gen10 CTO server ensures it is built in the USA in a secured facility by vetted HPE personnel assigned to the manufacturing processes. A multitude of checkpoints/inspections for malicious microcode and counterfeit parts are performed throughout the server build, and additional safeguards are put in place against cyber-exploits throughout the server lifecycle. The HPE ProLiant DL380 Gen10 server is re-branded as a HPE ProLiant DL380T Gen10 to denote the HPE Trusted Supply Chain security enhancements. The DL380T Gen10 is currently supported in the USA, exclusively, and is Trade Agreement Act (TAA) compliant. Learn more at <http://www.hpe.com/security>  
This option requires the selection of HPE Gen10 Intrusion Detection Kit (867824-B21)

## Additional Options

This option requires the selection of either HPE iLO Advanced 1-server License with 3yr Support on iLO Licensed Features (BD505A) or HPE iLO Advanced 1-server License with 1yr Support on iLO Licensed Features (512485-B21)

This option is limited to stand-alone DL380 Gen10 CTO servers only. The HPE Trusted Supply Chain configuration will not be available if the server is ordered as factory integrated into a rack

- One instance of the following Electronic License to Use is required per order (not per server):  
R6X85AAE - HPE Trusted Supply Chain E-LTU
- Logistics delivery speeds and services are available and selectable within Next Gen Quoter.
- This option cannot be selected with TAA instruction SKU nor TAA CTO Models

HPE iLO Common Password FIO Setting P08040-B21

### Notes:

Replaces iLO default randomized password by an HPE defined common password. HPE highly recommends changing this password immediately after the initial onboarding process.

Customers who want to choose their own custom iLO default password should use the HPE Factory Express Integration Services

HPE Gen10 2U Bezel Kit 867809-B21

HPE Bezel Lock Kit 875519-B21

**Notes:** Requires the bezel kit

HPE Gen10 Chassis Intrusion Detection Kit 867824-B21

**Notes:** This provides a physical connection from the chassis board and hood and detects any physical intrusion into the chassis, providing security during the entire supply chain process of shipping, receiving, distribution, and operation.

HPE Trusted Platform Module 2.0 Gen10 Option 864279-B21

### Notes:

HPE Trusted Platform Module 2.0 option works with Gen10 servers with UEFI Mode not Legacy Mode. It is not compatible with HPE ProLiant Gen8 servers or earlier generation variants.

HPE server systems can have a TPM module (of any type) installed only once. It cannot be replaced with any other TPM module.

HPE Gen10 TPM 1.2 FIO Setting 872108-B21

**Notes:** This is a FIO setting to allow the TPM 2.0 module to operate in a TPM 1.2 mode.

## HPE Boot Controllers

HPE NS204i-p x2 Lanes NVMe PCIe3 x8 OS Boot Device P12965-B21


**Notes:** This option is pre-configured for HW RAID 1 for OS boot only and, by default, comes with 2x 480GB M.2 Read-Intensive enterprise-class NVMe with Power Loss Protection (PLP) by default

## HPE Smart Array Controllers

The Gen10 controller naming framework has been updated to simplify identification as depicted below. For a more detailed breakout of the available Gen10 Smart Array controllers visit the

[https://www.hpe.com/psnow/doc/a00047736enw?jumpid=in\\_hpesitesearch](https://www.hpe.com/psnow/doc/a00047736enw?jumpid=in_hpesitesearch)

### Additional Options



### HPE Flexible Smart Array Performance RAID Controllers

#### Notes:

All performance RAID controllers are supported by the HPE Smart Storage Hybrid Capacitor (P02377-B21) or HPE Smart Storage Battery (P01366-B21), which supports multiple devices and are sold separately.

Flexible Smart Array controllers do not consume a PCIe slot.

HPE Smart Array P816i-a SR Gen10 (16 Internal Lanes/4GB Cache/SmartCache) 12G SAS Modular Controller 804338-B21

#### Notes:

Includes SmartCache license.

The P816i-a cable ships in the 12LFF chassis only (868705-B21).

HPE Smart Array P408i-a SR Gen10 (8 Internal Lanes/2GB Cache) 12G SAS Modular Controller 804331-B21

### HPE Flexible Smart Array Essential Controllers

HPE Smart Array E208i-a SR Gen10 (8 Internal Lanes/No Cache) 12G SAS Modular Controller 804326-B21

### Performance RAID Controllers

**Notes:** All performance RAID controllers are supported by the HPE Smart Storage Hybrid Capacitor (P02377-B21) or HPE Smart Storage Battery (P01366-B21), which support multiple devices and are sold separately.

HPE Smart Array P408i-p SR Gen10 (8 Internal Lanes/2GB Cache) 12G SAS PCIe Plug-in Controller 830824-B21

HPE Smart Array P408e-p SR Gen10 (8 External Lanes/4GB Cache) 12G SAS PCIe Plug-in Controller 804405-B21

### Essential RAID Controllers

HPE Smart Array E208i-p SR Gen10 (8 Internal Lanes/No Cache) 12G SAS PCIe Plug-in Controller 804394-B21

HPE Smart Array E208e-p SR Gen10 (8 External Lanes/No Cache) 12G SAS PCIe Plug-in Controller 804398-B21

### Tri-mode RAID Controllers

Broadcom MegaRAID MR416i-a x16 Lanes 4GB Cache NVMe/SAS 12G Controller for HPE Gen10 Plus P26279-B21

Broadcom MegaRAID MR416i-p x16 Lanes 4GB Cache NVMe/SAS 12G Controller for HPE Gen10 Plus P06367-B21

Broadcom MegaRAID MR216i-a x16 Lanes without Cache NVMe/SAS 12G Controller for HPE Gen10 Plus P26325-B21

Broadcom MegaRAID MR216i-p x16 Lanes without Cache NVMe/SAS 12G Controller for HPE Gen10 Plus P26324-B21

### Additional Options

**Notes:** Supported with 8SFF Basic Carriers Model-X only. Only supports SAS/SATA.

#### HPE Cable Options

HPE ProLiant DL38x 8SFF SAS/SATA Tri-Mode Cable Kit P55467-B21

**Notes:** Max = 2.

Supported with 8SFF Basic Carriers Model-X only.

HPE ProLiant DL38x Gen10 Plus 2SFF SAS/SATA Tri-Mode Cable Kit P55469-B21

**Notes:** Max = 2.

Supported with 8SFF Basic Carriers Model-X only.

HPE ProLiant DL38x Gen10 Plus 2SFF Rear Tri-Mode Cable Kit P55471-B21

**Notes:** Max = 2.

Supported with 8SFF Basic Carriers Model-X only.

HPE DL380 SFF Smart Array HBA H200/P400 Series SAS Cable Kit 786092-B21

HPE DL38X Gen10 2 Drive NVMe Slim SAS Cable Kit 871827-B21

HPE DL380 Gen10 Mini SAS 3POS Cable Kit 826709-B21

**Notes:** If more than 8 SATA devices are being supported on the AHCI Embedded SATA controller, then Qty=1 of the SAS 3POS Cable Kit (826709-B21) is required. The AHCI Embedded SATA Controller is standard with all DL380 Gen10 models and can support up to 12 "SATA Only" devices.

HPE DL38X/560/580/ML350 Gen10 P824i-p Cable Kit P00614-B21

**Notes:** For details on cabling options, additional information available here:

<http://www.hpe.com/info/CablingMatrixGen10>

#### Optional Software

HPE Smart Array SR Secure Encryption (Data at Rest Encryption/per Server Entitlement) E-LTU Q2F26AAE

HPE Smart Array SR SmartCache (Single Key/Single Server) LTU D7S26A

HPE Smart Array SR SmartCache (Single Key/Multiple Servers) LTU D7S27A

HPE Smart Array SR SmartCache (Single Key/Multiple Servers) E-LTU D7S27AAE

**Notes:** SmartCache is offered on HPE Smart Array performance RAID controllers and comes standard (no licensing is required) if the HPE Smart Array P816i-a SR Gen10 Controller is installed in the server.

#### Optional Upgrades

HPE 96W Smart Storage Lithium-ion Battery with 145mm Cable Kit P01366-B21

HPE Smart Storage Hybrid Capacitor with 145mm Cable Kit P02377-B21

**Notes:** Provides backup power for multiple HPE Smart Array controllers or other devices. Is required with performance RAID controllers.

### Additional Options

#### HPE Tape Backup

For the complete range of tape drives, autoloaders, libraries and media see:

<https://www.hpe.com/us/en/storage/storeever-tape-storage.html> For hardware and software compatibility of Hewlett Packard Enterprise tape backup products <http://www.hpe.com/storage/BURAccompatibility>

### HPE Storage Options

#### Emulex Fibre Channel HBAs

HPE SN1200E 16Gb Single Port Fibre Channel Host Bus Adapter	Q0L13A
HPE SN1200E 16Gb Dual Port Fibre Channel Host Bus Adapter	Q0L14A
HPE SN1600E 32Gb Single Port Fibre Channel Host Bus Adapter	Q0L11A
HPE SN1600E 32Gb Dual Port Fibre Channel Host Bus Adapter	Q0L12A
HPE SN1610E 32Gb 1-port Fibre Channel Host Bus Adapter	R2J62A
HPE SN1610E 32Gb 2-port Fibre Channel Host Bus Adapter	R2J63A

#### QLogic Fibre Channel HBAs

HPE SN1100Q 16Gb Single Port Fibre Channel Host Bus Adapter	P9D93A
HPE SN1100Q 16Gb Dual Port Fibre Channel Host Bus Adapter	P9D94A
HPE SN1600Q 32Gb Single Port Fibre Channel Host Bus Adapter	P9M75A
HPE SN1600Q 32Gb Dual Port Fibre Channel Host Bus Adapter	P9M76A
HPE SN1610Q 32Gb 1-port Fibre Channel Host Bus Adapter	R2E08A
HPE SN1610Q 32Gb 2-port Fibre Channel Host Bus Adapter	R2E09A

#### Converged Network Adapters

HPE CN1200R 10GBASE-T Converged Network Adapter	Q0F26A
HPE CN1300R 10/25Gb Dual Port Converged Network Adapter	Q0F09A

### HPE Racks

- Please see the [HPE Advanced Series Racks QuickSpecs](#) for information on additional racks options and rack specifications.
- Please see the [HPE Enterprise Series Racks QuickSpecs](#) for information on additional racks options and rack specifications.
- Please see the [HPE Standard Series Racks QuickSpecs](#) for information on additional racks options and rack specifications.

### HPE Power Distribution Units (PDUs)

- Please see the [HPE Basic Power Distribution Units \(PDU\) QuickSpecs](#) for information on these products and their specifications.
- Please see the [HPE Metered Power Distribution Units \(PDU\) QuickSpecs](#) for information on these products and their specifications. Please see the [HPE Intelligent Power Distribution Unit \(PDU\) QuickSpecs](#) for information on these products and their specifications.
- Please see the [HPE Metered and Switched Power Distribution Units \(PDU\) QuickSpecs](#) for information on these products and their specifications.



### Additional Options

---

#### HPE Uninterruptible Power Systems (UPS)

- To learn more, please visit the [HPE Uninterruptible Power Systems \(UPS\)](#) web page.
- Please see the [HPE DirectFlow Three Phase Uninterruptible Power System QuickSpecs](#) for information on these products and their specifications.
- Please see the [HPE Line Interactive Single Phase UPS QuickSpecs](#) for information on these products and their specifications.

#### HPE Rack Options

- Please see the [HPE KVM Switches web page](#) for information on these products and their specifications.
- 

#### Rail Kits

Ball bearing and Easy Install rail kits contain telescoping rails which allow for in-rack serviceability.

To assist in the installation of the server into the rack an optional installation tool is available by contacting your local services representative (695539-001).

**Notes:** Hewlett Packard Enterprise recommends that a minimum of two people are required for all Rack Server installations. Please refer to your installation instructions for proper tools and number of people to use for any installation.

HPE 2U Small Form Factor Easy Install Rail Kit 733660-B21

**Notes:** Does not include CMA (733664-B21).

HPE 2U Large Form Factor Easy Install Rail Kit 733662-B21

**Notes:** Does not include CMA (733664-B21).

HPE 2U Cable Management Arm for Easy Install Rail Kit 733664-B21

HPE 2U Small Form Factor Ball Bearing Rail Kit 720863-B21

**Notes:** Does not include CMA (720865-B21).

HPE 2U Large Form Factor Ball Bearing Rail Kit 720864-B21

**Notes:** Does not include Cable Management Arm (720865-B21).

HPE 2U Cable Management Arm for Ball Bearing Rail Kit 720865-B21

---

### Additional Options

#### HPE USB and SD Options

**Notes:** In vSphere 7.0, VMware made changes that impact the use of an SD Card/USB media as a standalone boot device and will be removing support for them after version 7.x. SD Card/USB media can still be used as a standalone boot option through all 7.x releases via published Customer Advisory [Usage of SD Card/USB Devices As Standalone Boot Devices Has Changed Due to System Storage Changes For VMware ESXi 7.0 \(Or Later\)](#).

For any major release beyond VMware ESXi 7.x, VMware will require M.2 or another local persistent device as the standalone boot option.

#### HPE Enterprise Mainstream Flash Media Kits for Memory Cards

HPE 32GB microSD RAID 1 USB Boot Drive P21868-B21

HPE 32GB microSD Flash Memory Card 700139-B21

**Notes:** Not supported with Legacy FIO mode (758959-B22)

---

### HPE Support Services

#### Installation & Startup Services

HPE Install ProLiant DL38x(p) Service U4554E

HPE Installation and Startup DL38x(p) Service U4555E

#### Tech Care

HPE 5 Year Tech Care Essential DL380 Gen10 Service HS7Y9E

HPE 5 Year Tech Care Essential wDMR DL380 Gen10 Service HS7Z4E

HPE 3 Year Tech Care Essential DL380 Gen10 Service HS7Y7E


HPE 3 Year Tech Care Essential wDMR DL380 Gen10 Service HS7Z2E

**Notes:** For a full listing of support services available for this server, please visit <http://www.hpe.com/services>.

---

### Memory

#### Memory Population guidelines



**HPE ProLiant Gen10 DL360 / DL380 / DL560**  
**Notes:** \* Servers Front Server2 Slots per Channel

HPE ProLiant Gen10 12 slot per CPU												
DIMM population order												
1 DIMM								8				
2 DIMM s								8		10		
3 DIMM s								8		10		12
4 DIMM s			3		5			8		10		
5 DIMM s*			3		5			8		10		12
6 DIMM s	1		3		5			8		10		12
7 DIMM s*	1		3		5		7	8		10		12
8 DIMM s			3	4	5	6	7	8	9	10		
9 DIMM s*	1		3		5		7	8	9	10	11	12
10 DIMM s*	1		3	4	5	6	7	8	9	10		12
11 DIMM s*	1		3	4	5	6	7	8	9	10	11	12
12 DIMM s	1	2	3	4	5	6	7	8	9	10	11	12

**Notes:** \*Unbalanced, not recommended

#### General Memory Population Rules and Guidelines:

- Install DIMMs only if the corresponding processor is installed.
- If only one processor is installed in a two-processor system, only half of the DIMM slots are available.
- To maximize performance, it is recommended to balance the total memory capacity between all installed processors.
- When two processors are installed, balance the DIMMs across the two processors.
- White DIMM slots denote the first slot to be populated in a channel.
- Mixing of DIMM types (UDIMM, RDIMM, and LRDIMM) is not supported.
- The maximum memory speed is a function of the memory type, memory configuration, and processor model.
- The maximum memory capacity is a function of the number of DIMM slots on the platform, the largest DIMM capacity qualified on the platform, and the number and model of installed processors qualified on the platform.
- For details on the HPE Server Memory Options Population Rules, visit:

### Memory

<http://www.hpe.com/docs/memory-population-rules>

- To realize the performance memory capabilities listed in this document, HPE DDR4 SmartMemory is required.  
For additional information, please see the [HPE DDR4 SmartMemory QuickSpecs](#).

<b>Registered DIMM (RDIMM)</b>				
HPE SKU P/N	815097-B21	815098-B21	835955-B21	815100-B21
SKU Description	HPE 8GB (1x8GB) Single Rank x8 DDR4-2666 CAS-19-19-19 Registered Smart Memory Kit	HPE 16GB (1x16GB) Single Rank x4 DDR4-2666 CAS-19-19-19 Registered Smart Memory Kit	HPE 16GB (1x16GB) Dual Rank x8 DDR4-2666 CAS-19-19-19 Registered Smart Memory Kit	HPE 32GB (1x32GB) Dual Rank x4 DDR4-2666 CAS-19-19-19 Registered Smart Memory Kit
DIMM Capacity	8GB	16GB	16GB	32GB
DIMM Rank	Single Rank (1R)	Single Rank (1R)	Dual Rank (2R)	Dual Rank (2R)
Voltage	1.2 V	1.2 V	1.2 V	1.2 V
DRAM Depth [bit]	1G	2G	1G	2G
DRAM Width [bit]	x8	x4	x8	x4
DRAM Density	8Gb	8Gb	8Gb	8Gb
CAS Latency	19-19-19	19-19-19	19-19-19	19-19-19
DIMM Native Speed	2666 MT/s	2666 MT/s	2666 MT/s	2666 MT/s
<b>Processors Officially Supported Memory Speed</b>				
<b>Intel Xeon®Platinum/Gold 81xx/61xx</b>				
1 RDIMM Per Channel	2666 MT/s	2666 MT/s	2666 MT/s	2666 MT/s
2 RDIMMs Per Channel	2666 MT/s	2666 MT/s	2666 MT/s	2666 MT/s
<b>Intel Xeon®Gold/Silver 51xx/41xx</b>				
1 RDIMM Per Channel	2400 MT/s	2400 MT/s	2400 MT/s	2400 MT/s
2 RDIMMs Per Channel	2400 MT/s	2400 MT/s	2400 MT/s	2400 MT/s
<b>Intel Xeon®Bronze 31xx</b>				
1 RDIMM Per Channel	2133 MT/s	2133 MT/s	2133 MT/s	2133 MT/s
2 RDIMMs Per Channel	2133 MT/s	2133 MT/s	2133 MT/s	2133 MT/s
<b>HPE Server Memory Speed: Intel Xeon® Platinum/Gold 81xx/61xx Processors *</b>				
1 RDIMM Per Channel	2666 MT/s	2666 MT/s	2666 MT/s	2666 MT/s
2 RDIMMs Per Channel	2666 MT/s	2666 MT/s	2666 MT/s	2666 MT/s
<b>HPE Server Memory Speed: Intel Xeon® Gold/Silver 51xx/41xx Processors *</b>				
1 RDIMM Per Channel	2400 MT/s	2400 MT/s	2400 MT/s	2400 MT/s
2 RDIMMs Per Channel	2400 MT/s	2400 MT/s	2400 MT/s	2400 MT/s
<b>HPE Server Memory Speed: Intel Xeon® Bronze 31xx Processors *</b>				

### Memory

1 RDIMM Per Channel	2133 MT/s	2133 MT/s	2133 MT/s	2133 MT/s
2 RDIMMs Per Channel	2133 MT/s	2133 MT/s	2133 MT/s	2133 MT/s

**Notes:** The maximum memory speed is a function of the memory type, memory configuration, and processor model.

For details on the HPE Server Memory speed, visit: <https://www.hpe.com/docs/memory-speed-table>

RDIMM					
HPE SKU P/N	P00918-B21	P00920-B21	P00922-B21	P00924-B21	P00930-B2
SKU description	HPE 8GB 1Rx8 PC4-2933Y-R Smart Kit	HPE 16GB 1Rx4 PC4-2933Y-R Smart Kit	HPE 16GB 2Rx8 PC4-2933Y-R Smart Kit	HPE 32GB 2Rx4 PC4-2933Y-R Smart Kit	HPE 64GB 2Rx4 PC4-2933Y-R Smart Kit
DIMM rank	Single rank (1R)	Single rank (1R)	Dual rank (2R)	Dual rank (2R)	Dual rank (2R)
<b>DIMM capacity</b>	8 GB	16 GB	16 GB	32 GB	64 GB
Voltage	1.2V	1.2V	1.2V	1.2V	1.2V
DRAM depth	1 Gb	2 Gb	1 Gb	2 Gb	4 Gb
DRAM width (bit)	x8	x4	x8	x4	x4
DRAM density	8 Gb	8 Gb	8 Gb	8 Gb	16 Gb
CAS latency	21-21-21	21-21-21	21-21-21	21-21-21	21-21-21
DIMM native speed (MT/s)	2933	2933	2933	2933	2933
<b>Maximum capacity (GB)</b>					
16-slot servers	128	256	256	512	1024
24-slot servers	192	384	384	768	1536
48-slot servers	384	768	768	1536	3072
<b>HPE Server Memory speed (MT/s): Intel Xeon Platinum/Gold 82xx/62xx processors*</b>					
1 DIMM per channel	2933	2933	2933	2933	2933
2 DIMM per channel	2933	2933	2933	2933	2933
<b>HPE Server Memory speed (MT/s): Intel Xeon Gold 52xx processors*</b>					
1 DIMM per channel	2666	2666	2666	2666	2666
2 DIMM per channel	2666	2666	2666	2666	2666
<b>HPE Server Memory speed (MT/s): Intel Xeon Silver 42xx processors</b>					
1 DIMM per channel	2400	2400	2400	2400	2400
2 DIMM per channel	2400	2400	2400	2400	2400
<b>HPE Server Memory speed (MT/s): Intel Xeon Bronze 32xx processors</b>					
1 DIMM per channel	2133	2133	2133	2133	2133
2 DIMM per channel	2133	2133	2133	2133	2133

### Notes: \*

Intel Xeon Gold 52xx processors support 2933 MT/s.

HPE ProLiant DL560 and DL580 servers do not support 32xx or 42xx processors.

Memory DIMM availability and maximum memory speed with a server platform is dependent upon completion of certification testing.

The maximum memory speed is a function of the memory type, memory configuration, and processor model.

When HPE Persistent Memory for second-generation Intel Xeon Scalable processors is installed, the maximum supported memory speed is 2666 MT/s.

### Memory

LRDIMM			
HPE SKU P/N	P00926-B21	P00928-B21	P11040-B21
SKU description	HPE 64GB 4Rx4 PC4-2933Y-L Smart Kit	HPE 128GB 8Rx4 PC4-2933Y-L 3DS Smart Kit	HPE 128GB 4Rx4 PC4-2933Y-L Smart Kit
DIMM rank	Quad rank (4R)	Octal rank (8R)	Quad rank (4R)
<b>DIMM capacity</b>	64 GB	128 GB	128 GB
Voltage	1.2V	1.2V	1.2V
DRAM depth	2 Gb	2 Gb	4 Gb
DRAM width (bit)	x4	x4	x4
DRAM density	8 Gb	8 Gb	16 Gb
CAS latency	21-21-21	24-21-21	21-21-21
DIMM native speed (MT/s)	2933	2933	2933
<b>Maximum capacity (GB)</b>			
16-slot servers	1024	2048	2048
24-slot servers	1536	3072	3072
48-slot servers	3072	6144	6144
<b>HPE Server Memory speed (MT/s): Intel Xeon Platinum/Gold 82xx/62xx processors*</b>			
1 DIMM per channel	2933	2933	2933
2 DIMM per channel	2933	2933	2933
<b>HPE Server Memory speed (MT/s): Intel Xeon Gold 52xx processors*</b>			
1 DIMM per channel	2666	2666	2666
2 DIMM per channel	2666	2666	2666
<b>HPE Server Memory speed (MT/s): Intel Xeon Silver 42xx processors</b>			
1 DIMM per channel	2400	2400	2400
2 DIMM per channel	2400	2400	2400
<b>HPE Server Memory speed (MT/s): Intel Xeon Bronze 32xx processors</b>			
1 DIMM per channel	2133	2133	2133
2 DIMM per channel	2133	2133	2133

#### Notes: \*

Intel Xeon Gold 52xx processors support 2933 MT/s.

HPE ProLiant DL560 and DL580 servers do not support 32xx or 42xx processors.

Memory DIMM availability and maximum memory speed with a server platform is dependent upon completion of certification testing.

The maximum memory speed is a function of the memory type, memory configuration, and processor model.

When HPE Persistent Memory for second-generation Intel Xeon Scalable processors is installed, the maximum supported memory speed is 2666 MT/s.



### Memory

Standard and Maximum Memory Capacity (Pre-configured Models)			
Pre Configured Models	Standard Memory	Maximum Memory Plus Optional Memory	Standard Memory Replaced with Optional Memory
3106	16 GB (1x16 GB RDIMM DR)	384 GB (24x 16 GB)	3072 GB (24x 128 GB)
4110	32 GB (2x16 GB RDIMM DR)	384 GB (24x 16 GB)	3072 GB (24x 128 GB)
4114	32 GB (2x16 GB RDIMM DR)	384 GB (24x 16 GB)	3072 GB (24x 128 GB)
5118	64 GB (2x32 GB RDIMM DR)	768 GB (24x 32 GB)	3072 GB (24x 128 GB)
6130	64 GB (2x32 GB RDIMM DR)	768 GB (24x 32 GB)	3072 GB (24x 128 GB)

#### DDR4 memory options part number decoder

**Notes:** Capacity references are rounded to the common gigabyte (GB) values.

8GB = 8,192 MB

16GB = 16,384 MB

32GB = 32,768 MB


64GB = 65,536 MB

For more information on memory, please see the Memory Quickspecs: [HPE DDR4 SmartMemory](#)



#### Memory Speed Table for HPE ProLiantDL380 Gen 10

For details on the HPE Server Memory speed, please visit: <https://www.hpe.com/docs/memory-speed-table>


### Storage



8LFF chassis with Universal media bay and optional 2SFF and optical drive shown




12 LFF + 3 rear LFF drives



12 LFF + 2 rear SFF drives

### Storage



6 rear SFF drives



24 SFF + rear 2 SFF drives

### Technical Specifications

#### System Unit

##### Dimensions

- **SFF Drives:**  
8.73 x 44.54 x 67.94 cm / 3.44 x 17.54 x 26.75 in
- **LFF Drives:**  
8.73 x 44.54 x 73.02 cm / 3.44 x 17.54 x 28.75 in

##### Weight (approximate)

- **Minimum:** 8 SFF chassis with 1x SFF HDD and 7 HDD blanks, 2x Drive Bay blanks, 1x processor including standard heatsink, 1x power supply (plus blank), 1x Smart Array, 1x Riser installed, cables for the above)
  - Maximum:**  
19.5 kg / 43.00 lbs
  - Minimum:**  
14.9 kg / 32.75 lbs
- **Maximum:** 12 LFF hard drives (no rear drives), 2x processors, 2x power supplies, 1x Smart Array, 2x Risers installed)
  - Maximum:**  
24.5 kg / 54 lbs
  - Minimum:**  
17.1 kg / 37.75 lbs

---

#### Input Requirements (per power supply)

##### Rated Line Voltage

- For 1600W (Platinum): 200-240 VAC
- For 800W (Titanium) Power Supply: 200-240 VAC
- For 800W (Platinum): 100-240 VAC
- For 800W (Universal) Power Supply: 200-277 VAC
- For 800W (-48VDC): -40 Vdc to -72 Vdc
- 500W (Platinum) Power Supply: 100-240 VAC
- For 1600W (-48VDC): -40 to -72

---

#### BTU Rating

##### Maximum

- For 1600W Power Supply: 5918 BTU/hr (at 200 VAC), 5888 BTU/hr (at 220 VAC), 5884 BTU/hr (at 240 VAC)
- For 800W (Titanium) Power Supply: 2905 BTU/hr (at 200 VAC), 2899 BTU/hr (at 220 VAC), 2893 BTU/hr (at 240 VAC)
- For 800W (Platinum) Power Supply: 3067 BTU/hr (at 100 VAC), 2958 BTU/hr (at 200 VAC), 2949 BTU/hr (at 240 VAC)
- For 800W (Universal) Power Supply: 2964 BTU/hr (at 200 VAC), 2951 BTU/hr (at 230 VAC), 2936 BTU/hr (at 277 VAC)
- For 800W(-48Vdc) Power Supply: 2983 BTU/hr (at -40 Vdc), 2951 BTU/hr (at -48Vdc), 2912 BTU/hr

### Technical Specifications

(at -72Vdc)

- For 500W (Platinum) Power Supply: 1902 BTU/hr (at 100 VAC), 1840 BTU/hr (at 200 VAC), 1832 BTU/hr (at 240 VAC)
  - For 1600W-(-48Vdc) Power Supply: 6026 BTU/hr (at -40 Vdc), 6000 BTU/hr (at -48Vdc), 5989 BTU/hr (at -72Vdc)
- 

### Relative Humidity (non-condensing)

- **Operating**  
8% to 90% - Relative humidity (Rh), 28°C maximum wet bulb temperature, non-condensing.
  - **Non-operating**  
5 to 95% relative humidity (Rh), 38.7°C (101.7°F) maximum wet bulb temperature, non-condensing..
- 

### Power Supply Output

(per power supply)

#### Rated Steady-State Power

- For 1600W Power Supply: 1600W (at 240 VAC), 1600W (at 240 VDC) for China only
- For 800W (Titanium) Power Supply: 800W (at 200 VAC), 800W (at 240 VAC), 800W (at 240 VDC) for China only
- For 800W (Platinum) Power Supply: 800W (at 100 VAC), 800W (at 240 VAC), 800W (at 240 VDC) input for China only
- For 800W (Universal) Power Supply: 800W (at 200 VAC), 800W (at 277 VAC)
- For 800W (-48VDC) Power Supply: 800W (at -40 Vdc), 800W (at -72Vdc)
- For 500W (Platinum) Power Supply: 500W (at 100 VAC), 500W (at 240 VAC), 500W (at 240 VDC) input for China only
- For 1600W (-48VDC) Power Supply: 1600W (at -40 Vdc), 1600W (at -72Vdc)

#### Maximum Peak Power

- For 1600W Power Supply: 1600W (at 240 VAC), 1600W (at 240 VDC) for China only
  - For 800W (Titanium) Power Supply: 800W (at 200 VAC), 800W (at 240 VAC), 800W (at 240 VDC) for China only
  - For 800W (Platinum) Power Supply: 800W (at 100 VAC), 800W (at 240 VAC), 800W (at 240 VDC) input for China only
  - For 800W (Universal) Power Supply: 800W (at 200 VAC), 800W (at 277 VAC)
  - For 800W (-48VDC) Power Supply: 800W (at -40 Vdc), 800W (at -72Vdc)
  - For 500W (Platinum) Power Supply: 500W (at 100 VAC), 500W (at 240 VAC), 500W (at 240 VDC) input for China only
  - For 1600W (-48VDC) Power Supply: 1600W (at -40 Vdc), 1600W (at -72Vdc)
- 

### System Inlet Temperature

- **Standard Operating Temperature**  
10° to 35°C (50° to 95°F) at sea level with an altitude derating of 1.0°C per every 305 m (1.8°F per every 1000 ft) above sea level to a maximum of 3050 m (10,000 ft), no direct sustained sunlight. Maximum rate of change is 20°C/hr (36°F/hr). The upper limit and rate of change may be limited by the type and number of options installed.
-

### Technical Specifications

System performance during standard operating support may be reduced if operating with a fan fault or above 30°C (86°F).

- **Extended Ambient Operating Temperature**

For approved hardware configurations, the supported system inlet range is extended to be: 5° to 10°C (41° to 50°F) and 35° to 40°C (95° to 104°F) at sea level with an altitude derating of 1.0°C per every 175 m (1.8°F per every 574 ft) above 900 m (2953 ft) to a maximum of 3050 m (10,000 ft). The approved hardware configurations for this system are listed at the URL: <http://www.hpe.com/servers/ashrae>

For approved hardware configurations, the supported system inlet range is extended to be: 40° to 45°C (104° to 113°F) at sea level with an altitude derating of 1.0°C per every 125 m (1.8°F per every 410 ft) above 900 m (2953 ft) to a maximum of 3050 m (10,000 ft). The approved hardware configurations for this system are listed at the URL: <http://www.hpe.com/servers/ashrae>

System performance may be reduced if operating in the extended ambient operating range or with a fan fault.

- **Non-operating**

-30° to 60°C (-22° to 140°F). Maximum rate of change is 20°C/hr (36°F/hr).

---

### Altitude

- **Operating**

3050 m (10,000 ft). This value may be limited by the type and number of options installed. Maximum allowable altitude change rate is 457 m/min (1500 ft/min).

- **Non-operating**

9144 m (30,000 ft). Maximum allowable altitude change rate is 457 m/min (1500 ft/min).

---

### Acoustic Noise

Listed are the declared A-Weighted sound power levels ( $L_{WAd}$ ) and declared average bystander position A-Weighted sound pressure levels ( $L_{pAm}$ ) when the product is operating in a 23°C ambient environment. Noise emissions were measured in accordance with ISO 7779 (ECMA 74) and declared in accordance with ISO 9296 (ECMA 109). The listed sound levels apply to standard shipping configurations. Additional options may result in increased sound levels. Please have your HPE representative provide information from the HPE EMESC website for further technical details regarding the configurations listed below.



### Technical Specifications

Acoustic Noise	
<b>Idle</b>	
LWAd	4.8 B Entry 4.4 B Base 4.6 B Perf
LpAm	37 dBA Entry 31 dBA Base 31 dBA Perf
<b>Operating</b>	
LWAd	4.8 B Entry 4.4 B Base 4.6 B Perf
LpAm	37 dBA Entry 31 dBA Base 31 dBA Perf

#### Notes:

Acoustics levels presented here are generated by the test configuration only. Acoustics levels will vary depending on system configuration. Values are subject to change without notification and are for reference only. Product conformance to cited product specifications is based on sample (type) testing, evaluation, or assessment. This product or family of products is eligible to bear the appropriate compliance logos and statements. The Listed sound levels apply to standard shipping configurations. Additional options may result in increased sound levels

### Emissions Classification (EMC) - Regulatory Information

To view the regulatory information for your product, view the Safety and Compliance Information for Server, Storage, Power, Networking, and Rack Products, available at the Hewlett Packard Enterprise Support Center:

<http://www.hpe.com/support/Safety-Compliance-EnterpriseProducts>

### HPE Smart Array

For latest information on [HPE Smart Array Gen10 Controllers for HPE ProLiant DL, ML and Apollo Servers](#) please refer to their QuickSpecs. (E208i-a,E208i-p,E208e-p,P408i-a,P408i-p,P408e-p,P816i-a)

### Environment-friendly Products and Approach End-of-life Management and Recycling

Hewlett Packard Enterprise offers **end-of-life product return, trade-in, and recycling programs**, in many geographic areas, for our products. Products returned to Hewlett Packard Enterprise will be recycled, recovered or disposed of in a responsible manner.

The EU WEEE directive (2002/95/EC) requires manufacturers to provide treatment information for each product type for use by treatment facilities. This information (product disassembly instructions) is posted on the Hewlett Packard Enterprise web site. These instructions may be used by recyclers and other WEEE treatment facilities as well as Hewlett Packard Enterprise OEM customers who integrate and re-sell Hewlett Packard Enterprise equipment.

### TCO Certified

The HPE ProLiant DL380 Gen10 server has been TCO Certified. All HPE TCO Certified products can be found on TCO Certified Product Finder. More information on TCO Certified can be downloaded here:

<https://www.hpe.com/us/en/about/environment/eco-labels.html> .

Technical Specifications

---

### Summary of Changes

Date	Version History	Action	Description of Change
06-Sep-2022	Version 55	Change d	Pre-configured Models and Core Options sections were updated. Obsolete SKUs were removed.
01-Aug-2022	Version 54	Change d	Pre-configured Models and Core Options sections were updated. Obsolete SKUs were removed.
05-Jul-2022	Version 53	Change d	Standard Features section was updated. Obsolete SKUs were removed.
06-Jun-2022	Version 52	Change d	Configuration Information, Additional Options, Pre-configured Models and Core Options sections were updated. Obsolete SKUs were removed.
02-May-2022	Version 51	Change d	Core Options section was updated. Obsolete SKUs were removed.
07-Feb-2022	Version 50	Change d	Standard Features, Core Options and Technical Specifications sections were updated. Obsolete SKUs were removed.
06-Dec-2021	Version 49	Change d	Core Options, Pre-configured Models and Additional Options sections were updated.
01-Nov-2021	Version 48	Change d	Core Options and Service and Support sections were updated. Obsolete SKUs were removed.
07-Sep-2021	Version 47	Change d	Core Options and Technical Specifications sections were updated. Obsolete SKUs were removed.
02-Aug-2021	Version 46	Change d	Overview, Core Options and Configuration Information sections were updated.
06-Apr-2021	Version 45	Change d	Service and Support and Additional Options sections were updated. Obsolete SKUs were removed.
01-Mar-2021	Version 44	Change d	Overview, Pre-configured Models, and Configuration Information sections were updated. Obsolete SKUs were removed.
01-Feb-2021	Version 43	Change d	Pre-configured Models section was updated. Obsolete SKUs were removed.
07-Dec-2020	Version 42	Change d	Standard Features, Core Options and Technical Specifications sections were updated. Obsolete SKUs were removed.
02-Nov-2020	Version 41	Change d	Pre-configured Models, Core Options and Additional Options sections were updated. Obsolete SKUs were removed.
05-Oct-2020	Version 40	Change d	Overview, Standard Features, Pre-configured Models, Configuration Information and Core Options sections were updated. Obsolete SKUs were removed.
01-Oct-2020	Version 39	Change d	Overview, Configuration Information and Additional Options sections were updated. Obsolete SKUs were removed.
03-Aug-2020	Version 38	Change d	Overview, Standard Features, Core Options and Additional Options sections were updated. Obsolete SKUs were removed.

### Summary of Changes

01-Jun-2020	Version 37	Change d	Standard Features, Configuration Information and Core Options sections were updated.
04-May-2020	Version 36	Change d	Pre-configured Models, Core Options and Additional Options sections were updated.

Date	Version History	Action	Description of Change
06-Apr-2020	Version 35	Change d	Overview, Standard Features, Pre-configured Models, Configuration Information and Core Options sections were updated
16-Mar-2020	Version 34	Change d	Configuration Information and Core Options sections were updated.
02-Mar-2020	Version 33	Change d	Standard Features, Configuration Information, Core Options and Additional Options sections were updated
24-Feb-2020	Version 32	Change d	Standard Features, Pre-configured Models, Configuration Information, Core Options and Additional Options sections were updated
03-Feb-2020	Version 31	Change d	Overview, Core Options, and Aditonal Options . sections were updated. Obsolete SKUs were removed.
20-Jan-2020	Version 30	Change d	Standard Features, Pre-configured Models and Configuration Information sections were updated.
02-Dec-2019	Version 29	Change d	Overview, Standard Features, Configuration Information, Core Options and Additional Options sections were updated. Obsolete SKUs were removed.
07-Oct-2019	Version 28	Change d	Overview, Standard Features, Pre-configured Models, Core Options and Additional Options sections were updated. Obsolete SKU was removed.
16-Sep-2019	Version 27	Change d	Configuration Information section was updated. Obsolete SKU was removed
03-Sep-2019	Version 26	Change d	Overview, Configuration Information - Factory Integrated Models, Pre-configured Models, Core Options, and Additional Options sections were updated. Obsolete SKUs were removed.
12-Aug-2019	Version 25	Change d	Overview, Standard Features, Pre-configured Models, Configuration Information - Factory Integrated Models, Core Options, SMB Models and Additional Options sections were updated. Obsolete SKUs were removed.
01-Jul-2019	Version 24	Change d	Pre-Configured models section was updated. The 5218N wattage has changed from 105 to 110W TDP. The U.S. version of QuickSpecs is no longer being updated, please reference the Worldwide QuickSpecs for latest information
03-Jun-2019	Version 23	Change d	Overview, Standard Features, Configuration Information, Core Options, and Additional Options sections were updated. SKU descriptions were updated. Obsolete SKUs were removed.
15-Apr-2019	Version 22	Change d	Standard Features section was updated

### Summary of Changes

02-Apr-2019	Version 21	Change d	Overview, Standard Features, Pre-configured Models, Configuration Information, Core Options, Additional Options and Memory sections were updated
04-Feb-2019	Version 20	Change d	Overview, Core Options and Optional Features sections were updated.
03-Dec-2018	Version 19	Change d	Overview, Standard Features, Core Options and Storage sections were Updated.
15-Oct-2018	Version 18	Change d	Configuration Information, Core Options and Additional Options sections were updated
01-Oct-2018	Version 17	Change d	Overview, Standard Features, Preconfigured Models, Configuration Information, Core Options, Additional Options, and Memory sections were updated. SKU descriptions were updated. Obsolete SKUs were removed.
13-Aug-2018	Version 16	Change d	Core Options and Additional Options were revised.

Date	Version History	Action	Description of Change
06-Aug-2018	Version 15	Change d	Added new Solid State Drives offering, Added new GPU option. Configuration Information - Factory Integrated Models, Core Options, and Additional Options were revised. Obsolete SKUs were removed from the QuickSpecs.
11-Jun-2018	Version 14	Change d	Smart Buy Models section for the NA version was revised.
04-Jun-2018	Version 13	Change d	Added new SSDs offering to the HPE Drives section. Core Options, Additional Options, and Memory were updated. Obsolete SKUs were removed from the QuickSpecs.
07-May-2018	Version 12	Change d	New SMB Models offering was added. Riser Information was revised. Obsolete SKUs were removed from the QuickSpecs.
02-Apr-2018	Version 11	Change d	SKUs description were updated. Obsolete SKUs were removed from the QuickSpecs.
05-Mar-2018	Version 10	Remove d	Obsolete SKUs were removed from the QuickSpecs.
05-Feb-2018	Version 9	Added	Added new SATA SSDs, NVMe drives, and PCIe accelerator cards.
18-Dec-2017	Version 8	Change d	Weight specifications were revised.
04-Dec-2017	Version 7	Change d	Added HPE Scalable Persistent Memory. Added HPE Specific IST Processor offering Gold 6143 and Platinum 8165 bins. Added Large capacity 15.3TB SSDs. Added new AMD and NVIDIA Graphics card options. Processors, Memory, Maximum Internal Storage, Configuration Information - Factory Integrated Models, Core Options, and Additional Options were revised.
23-Oct-2017	Version 6	Change d	Memory speed table was updated to display the 61XX processors running at 2666MT/s.

### Summary of Changes



16-Oct-2017	Version 5	Change d	8GB Dual Rank Memory was added. Riser table was added under Core Options. Platform Information, FlexibleLOM adapters, GPGPU table under Core Options, HPE Computation and Graphics Accelerators, and HPE Smart Array Controllers were revised.
25-Sep-2017	Version 4	Change d	Added new 128GB GB DIMM. Additional Intel® Xeon® Processor Scalable Family processor bins were added. Added new NVIDIA GPU cards. Added new drive options offering (SSD, m.2, NVMe). Memory, Standard Features, Configuration Information - Factory Integrated Models, Core Options, Additional Options, and Technical Specifications were revised. Obsolete SKUs were removed from the QuickSpecs.
04-Sep-2017	Version 3	Change d	Smart Buy models section was revised (NA version only).
07-Aug-2017	Version 2	Change d	Added new Solid State Drives offering to the HPE Drives section. Platform Information, Standard Features, Optional Features, Pre-configured Models, Configuration Information - Factory Integrated Models, Core Options, and Additional Options section were revised.
11-Jul-2017	Version 1	New	New QuickSpecs.



### Copyright

---

Make the right purchase decision. Contact our presales specialists.



---

© Copyright 2022 Hewlett Packard Enterprise Development LP. The information contained herein is subject to change without notice. The only warranties for Hewlett Packard Enterprise products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. Hewlett Packard Enterprise shall not be liable for technical or editorial errors or omissions contained herein.

Intel® and Xeon® are registered trademarks of Intel Corporation in the U.S. and other countries.

Microsoft®, Windows®, and Windows Server® are U.S. registered trademarks of the Microsoft group of companies.

For hard drives, 1GB = 1 billion bytes. Actual formatted capacity is less.

a00008180enw - 15930 - Worldwide - V55 - 06-September-2022

